

UNIVERSITÀ DI PARMA

UNIVERSITA' DEGLI STUDI DI PARMA

DOTTORATO DI RICERCA IN
INGEGNERIA INDUSTRIALE

CICLO XXXIV

EEG investigation of the spatial sound perception for the automotive industry

Coordinatore:
Chiar.mo Prof. GIANNI ROYER CARFAGNI

Tutore:
Chiar.mo Prof. ANGELO FARINA

Co-tutore:
Ph.D. LUCA ASCARI

Co-tutore:
Ing. CHRISTOPHER RAYMAEKERS

Dottorando: ANDREA BELLOTTI

Anni Accademici 2018/2019 - 2019/2020 - 2020/2021

Acknowledgments

The authors gratefully acknowledge the European Commission for its support of the Marie Sklodowska Curie program through the ETN PBNv2 project (GA 721615), and Toyota Motor Europe for supporting and co-hosting this research.

Chi la dura la vince

Abstract

Interior and exterior vehicle noise comfort have improved significantly in recent years thanks to the increasingly strict pass-by noise regulations and the emergence of quieter electric vehicles. Unfortunately, this noise reduction is preventing the delivery of an appropriate level of informative and emotional feedback to the humans inside and outside the vehicle.

The need, therefore, rises for new artificial sounds to provide suitable acoustic feedback for different levels of human-vehicle interaction while maintaining a comfortable acoustic environment. Considering the increasing application of Advanced Driver-Assistance Systems (ADAS), the vehicle soundscape will ever more contribute to vehicle safety by creating continuous situational awareness for surrounding pedestrians and occupants. The design of such enhanced soundscapes requires a data-driven approach to balance the possible conflicts between subjective acoustic perception and objective criteria such as driver response time and quality.

To go beyond of classical subjective evaluations, the aim of the present work is to leverage patterns in electroencephalography (EEG) measurements that correlate with aspects of human acoustic perception, exploiting them in the design and selection phases of vehicle sounds. In particular, the research focuses on horizontal sound localization and perception of radial sound motion.

Initially, a portable multimodal acquisition infrastructure designed for the investigations of this thesis is presented and the results of its validation in a real-world driving experiment are discussed. The validation consists in the implementation of a Brain-Computer Interface (BCI) allowing to control the

infotainment menu of the vehicle via the detection of Event-Related Potentials (ERPs) in the EEG signals, and thus without the need of any physical interventions while driving.

It is shown that the infrastructure can be effectively used for the collection of physiological signals along with vehicle telemetry and that it guarantees high signal quality in laboratory as well as in more demanding driving conditions. Considering the BCI itself, a single Convolutional Neural Network (CNN), trained on as few as three EEG electrodes combining the data of ten participants achieved an average classification accuracy of 49% with five unseen test participants. This accuracy is three times greater than the random baseline, which corresponds to 16.6% since the menu was composed of six icons. Notably, the performance of the general model is just 6% lower than the average performance of the individualized models which is 54% and, moreover, it has withstood also totally unseen people.

Then, the correlation between EEG signals and the localization of sound sources on the horizontal plane is investigated, initially in a pilot study with five participants, and then in a complete experiment involving thirty participants. The pilot study consisted in an active sound localization task and employed a short static wood-cracking sound played from eight directions. Based on the preliminary results and the refined research questions thereafter, the main experiment implemented a passive sound localization task with no attended directions and adopted a sound made up of a series of four hand claps simulating approaching or receding motion from four directions. Statistical analyses of the brain responses and single-trial classification accuracies achieved by the best machine learning model reveal a moderate correlation between EEG responses and the azimuth of a sound source.

Average classification accuracies greater than the random baseline have been achieved in all configurations, with peak discriminability in the "longitudinal vs lateral" localization configuration (front and rear directions against left and right directions), independently from the motion direction. In particular, the average individualized classification accuracy obtained in this binary configuration is 62.7% whereas the leave-one-participant-out performance is 59.1%. Grand average EEG responses associated to this configuration present major differences in the N1 and P2 ERP peak amplitudes located in the frontal and occipital lobes, and frontal lobe alone respectively. Additionally, different amplitudes, latencies, and shapes associated with the N2 peak and other late components have been identified mainly in the parietal

lobe.

These results are in line with other studies which identified noticeable EEG patterns correlating with the eccentricity of the sound source with respect to the listener. Indeed, eccentricity greatly influences the availability of localization cues as, the more we move from the extreme case of longitudinal sounds to the other extreme of lateral sounds, the more we move from uniquely monoaural cues, which carry little localization information, to more expressive fully binaural cues. It is hypothesized that this macroscopic difference is the origin of the distinct cerebral mechanisms that produce the identified patterns in the EEG signals.

A complementary habituation effect correlated with eccentricity has also been identified. It consists in the presence of statistically significant differences between subsequent sounds coming from the same direction and from different directions only in case of lateral sounds, and not in case of longitudinal ones.

No late information buildup associated with the perception of the sound direction has been found in the experiment as statistically significant differences have been identified uniquely in the onset ERPs and not in the responses to the following impulses. In contrast, statistically significant amplitude differences in the N1 and P2 components, directly proportional to sound intensity, have been found comparing the grand average EEG responses associated with approaching and receding sounds. As expected, the statistically significant windows of interest correspond to the first and last impulse, i.e., where the difference of intensity is maximum, thus suggesting a relationship with the sound pressure level (SPL) rather than the perception of motion direction.

To summarize, the first preparatory result presented in this work demonstrates the reliability of the proposed infrastructure for cognitive assessment of secondary tasks while driving. The purpose is to use it in the future to make objective choices in the design and evaluation phase of vehicle sounds that need to address the tradeoff between subjective perception and quality of the resulting behavioral outcomes. A spatial warning sound is an example of such scenario as it needs to successfully deliver as much information as possible in the shortest time possible, while avoiding to overload or confuse the recipient inside or outside the vehicle which would result in erroneous behavioral outcomes.

In this regard, the infrastructure has been used throughout the doctoral

work to investigate the EEG responses associated with the perception of two aspects of horizontal sound localization: angle of the sound source and motion direction.

Statistically significant population-wide results have been achieved in discriminating the angle of the sound source from single-trial EEG responses, especially when comparing longitudinal and lateral sounds or sounds coming from left and right, while no meaningful EEG patterns correlating with sound motion perception have been identified.

Keywords: EEG, ERP, BCI, embedded, sound localization, automotive

Contents

Acronyms **XVI**

1 Introduction **1**
1.1 Motivation . . . 3
1.2 Aim of the thesis . . . 5
1.3 Structure of the thesis . . . 6

2 Background **9**
2.1 Brain structure and function . . . 9
2.2 Electroencephalography . . . 15
2.3 Event-Related Potentials (ERPs) . . . 20
2.4 ERP components . . . 26
2.4.1 P1-N1-P2 complex . . . 27
2.4.2 Mismatch negativity (MMN) . . . 32
2.4.3 P3 . . . 35
2.4.4 N400 . . . 37
2.4.5 Error-Related Negativity (ERN) . . . 39
2.5 Acoustic processing . . . 40

3 State of the art **47**
3.1 Sound location classification . . . 47
3.2 EEG application in the automotive industry . . . 49

4 Infrastructure **51**
4.1 Introduction . . . 52
4.2 Proposed solution . . . 56
4.3 Experimental validation . . . 59
4.3.1 Experiment description . . . 60
4.3.2 Experimental settings in the laboratory . . . 61

4.3.3 Experimental settings on the proving ground 62
4.3.4 Data acquisition and analysis 64
4.3.5 Classification models 65
4.4 Results 68
4.4.1 Signal quality: laboratory and driving settings 68
4.4.2 Classification results 70
4.5 Limitations 76
4.6 Conclusions 77

5 Sound localization **81**
5.1 Introduction 82
5.2 Pilot study 85
5.2.1 Experiment description 86
5.2.2 Data preprocessing 88
5.2.3 Data analysis 90
5.2.4 Physiological responses 92
5.2.5 Classification 92
5.2.6 Population size computation 95
5.2.7 Conclusions 97
5.3 Main experiment 97
5.3.1 Experiment description 99
5.3.2 Behavioral results 101
5.3.3 Data preprocessing and classification methods 103
5.3.4 Data analysis 106
5.3.4.1 Physiological responses 106
5.3.4.1.1 Localization configurations 108
5.3.4.1.2 Motion perception 111
5.3.4.1.3 Habituation 114
5.3.4.2 Classification 117
5.3.4.2.1 Localization configurations 118
5.3.4.2.2 Auxiliary configurations 119
5.4 Conclusions 121

6 Conclusions and future work **125**
6.1 Main results 125
6.2 Future directions 127

Bibliography **128**

List of Figures

2.1 Three main structures composing the brain. Brainstem (magenta), cerebellum (green), and cerebrum (violet). The area highlighted in yellow represents the limbic system, and in particular the thalamus. 10

2.2 Limbic system. It is composed of hypothalamus, thalamus, hippocampus, and amygdala. 11

2.3 Representation of the cerebral cortex. Each hemisphere is subdivided in 4 lobes: frontal lobe (red), parietal lobe (yellow), occipital lobe (lime), and temporal lobe (green). A general overview of the high-level functional specialization is provided. 12

2.4 **A)** Representation of two interconnected neurons. The action potentials of the presynaptic neuron on the left travel through its axon and reach its terminals where the chemical synaptic communication toward the dendrites of the postsynaptic neuron on the right takes place. This process consists in the release of neurotransmitters that produce voltage variations in the downstream neuron. **B)** Pyramidal cells of the cerebral cortex, considered the main responsible of the electrical activity measurable at the scalp with the EEG recording technique. Source [1]. 14

2.5 High-quality EEG signals collected during an acoustic experiment. Each row corresponds to a different measurement site on the scalp (see Figure 2.6 for the exact positions). 15

2.6 Top view of the international 10-20 system for EEG electrodes placement. Electrode names beginning with the letter "F" represent positions covering the frontal lobe, and the same applies to the letters "C", "T", "P", and "O", representing central, temporal, parietal, and occipital positions respectively. 17

2.7 Artificial representation of an ERP response (red) resulting from the interaction of three components which differ in peak activation amplitude, magnitude, and timing. The electrical scalp recordings can exhibit reductions, amplifications, or even cancellations of relevant peaks, as well as deformations in latency and topography. The resulting response (red) presents amplitude reductions and temporal shifts of all three peaks compared to the corresponding underlying components. 24

2.8 Stereotypical representation an auditory evoked potential (AEP) which illustrates the four main auditory component. The first component is associated with the P1 peak, which is normally measured around 100 ms after the sound onset. The second, which is usually more informative when cognitive acoustic processing is concerned, is the N1, and its peak is usually observed between 120 and 200 ms from the onset. The following is the P2, which is the one normally exhibiting the greatest amplitude. It is the second positive peak and is usually found around 300 ms. Finally, the long-latency N2 component peaks around 350-400 ms from the sound onset. Source [2]. 27

2.9 Electrical and topographical representations of the two main acoustic evoked components varying the inter-stimulus interval. As can be seen, both the N1 and the P2 component are modulated by the temporal separation dimension: the more temporally isolated are the sounds, the larger are the amplitudes of both vertex components. Source [3] 30

2.10 Representation of the human auditory cortex. It is both anatomically and functionally subdivided in primary and secondary auditory cortex. Closely linked to the to this cerebral region are the temporal pole on one side (front) and the planum temporale on the other (rear). 31

2.11 Representation of both early (N1 & P2) and late (N2 & N4) auditory components, along with the corresponding topographies. The figure on the left shows the classical fronto-central topography of the N1 and P2 components, whereas the figure on the right reveals more frontal topographies for the N2 and N4 components. Source [4] 33

2.12 EEG trace resulting from the average of twenty-four 16-second-long responses displaying the classical P1-N1-P2 complex in evoked by 8 impulsive sounds. Unsurprisingly, the onset response exhibits significantly larger amplitudes both in the N1 and P2 peaks with respect to the subsequent responses. Additionally, a habituation behavior is visible in the decreasing peak amplitudes trend, especially in the first evoked responses. Source [5] 33

2.13 Oddball paradigm representation (A) with the corresponding target (deviant) and non-target (standard) average evoked responses (B). Notably, the same outcome is measured if non-target stimuli are dropped but the temporal separation of target stimuli is preserved (C). 38

2.14 Electrical representation of the error-related negativity (ERN) and error positivity in terms of difference wave and topography. The ERN (blue) starts even slightly in advance with respect to the error time, and it exhibits the largest amplitude in the frontocentral region. Source [6] 40

2.15 Subcortical acoustic processing flow starting from the cochlea to the auditory cortex. The path includes the superior olivary nucleus, the inferior colliculus, and the medial geniculate body and consists of a parallel route with multiple integration points for the aggregation and enhancement of the monoaural and binaural cues. Source [7] 41

2.16 Areas involved in the "what" (red) and "where" (blue) acoustic processing activity resulting from a meta-analysis of 38 PET and fMRI studies. It is clearly visible the dual pathway consisting in the red ventral "what" pathway that spans from the PAC to the IFC, and the blue "where" pathway mainly involving the PT, the IPL, and the PMC. Some areas are shared between the two pathways, in particular, the posterior auditory cortex and the IPL. Adapted from [8] 43

2.17 Representation of the dual-stream model, consisting of the ventral "what" pathway (green) and the dorsal "where" pathway (red). Source [9] 44

2.18 The top section shows the flow of source activation identified in a passive spatial listening experiment [10]. The PAC is activated first (violet region shown in panel a), then the PT (green region shown in panel b), and finally the IPL (teal region shown in panel c). The bottom section presents the results of a MEG study from an active sound localization task that highlights an activation flow similar to the top one, but exhibiting slightly earlier regional activations than reported by [10]. Both flows exhibit a bilateral activation with a stronger involvement of the right hemisphere. Adapted from [10, 11] . . 45

4.1 Artifact removal: statistical reconstruction of noisy time intervals based on prior knowledge about channels correlation in clean conditions. In red the original noisy signals (two eye blinks highlighted in pink), in blue the resulting clean signals. As a preliminary step, entire channels identified as noisy due to their excessively large and irregular variance (see green box) are discarded and reconstructed interpolating the clean neighboring channels. 53

4.2 Characteristic shape of Event-Related Potential (ERP). It is the average response measured in terms of electrical activity (EEG) in specific areas of the brain when an infrequent attended event (target) takes place, being it visual, auditory, or tactile. ERPs are characterised by known peaks, such as the P1, N2 and P3, that are named after deflection orientation (either Negative or Positive) and latency with respect to the onset of the event. The average shape of target and non-target responses is generally different and this allows, provided a sufficiently large number of repetitions, to discriminate between attended and unattended events. The bottom two plots show the great variability of the single-trial responses in the two conditions and the respective mean value (which are plotted together in the top plot for an easier comparison). 54

4.3 Schema of the proposed embedded infrastructure. It allows to acquire and process in real-time a fully synchronized flexible combination of psychophysiological signals (EEG, EMG, EKG, GSR, etc.), contextual information and vehicle telemetry (CAN, GPS, CAMERAS, etc.). Additionally, it optionally allows to provide visual, acoustic or tactile feedback to the users and to record their interaction with auxiliary devices such as smartphones and buttons. One of the key components is the EEG helmet prototype which is based on an OpenBCI that, thanks to a physical decoupling between sensors and electronics, ensures the smallest possible sensors motion and thus the smallest possible electromechanical noise. 57

4.4 Schema of the recording system employed in the experimental setup. 60

4.5 Experimental session design. A, laboratory protocol: one session comprised 6 runs (each having 60 trials; each icon repeating 10 times) of visual oddball task, with 30 s rest periods in between. B, driving protocol: one session included around 50 runs (each having 18 trials; each icon repeating 3 times) that were self-initiated by the participant. In both conditions the colors for the items were randomly chosen in the beginning of the session and remained constant within the session; items in a run were block-randomized on each repetition of a 6-item block. 63

4.6 Ranking of the most important subset of features provided by the random forest classifier, averaged across training sets and subjects. Considering that the window of interest spans between 0.2 s and 0.7 s, and that it is subdivided in 5 subwindows, each WM feature corresponds to the average over 100 ms. In particular, the features WM3 & WM4 correspond to the late subwindows between 0.5 s and 0.6 s, and 0.6 s and 0.7 s respectively. 66

4.7 EEG signals collected in laboratory and driving conditions. A, Grand average RMS values (channels Cz and Pz combined) of baseline and whole ERP trial for the two conditions; individual subjects' data are shown as black dots within the box plots. B, Grand average PSD values of channel Pz. Shaded areas show standard deviation across participants, gray area indicates statistical significant differences between the two conditions conditions ($p < 0.05$). C, Median grand averaged EEG responses for target and non-target trials; shaded area represents the standard error. 69

4.8 Trial rejection rates in the different sections of the proving ground. The sections are color-coded based on the magnitude of the corresponding rejection rates. The arrow on the top-left corner indicates the driving direction, and the dashed markers highlight the lane-merging sections. The bottom aerial picture shows the real proportions of the proving ground. 71

4.9 Average participant-specific classification accuracy varying EEG channels configuration and the number of repetitions of the menu icons. 72

4.10 Subject-specific performance achieved on the test session by the Deep4Net architecture varying the training dataset configuration. In-lab and in-car models are trained only on trials recorded in laboratory and in driving sessions respectively, whereas hybrid models are trained on the combination of the former two. 74

4.11 Average responses to the target of all the 15 available participants (channel Pz) and classification performance achieved by the general model on the corresponding test set. The general model was trained on both laboratory and car data (hybrid training configuration) of the original 10 participants and tested on the last driving session that was kept as separate test set. On the bar plot, the classification performance of the five new participants is highlighted (light blue dashed box) as well as the random chance (black dashed line, 16.6%) and the overall mean accuracy (magenta dashed line, 49%). Higher performances are associated with a larger P3 component and a smaller variability among the single trials (not visible in this plot). 76

5.1 Experimental setup. A) The natural wood-cracking sound was reproduced from 8 evenly separated loudspeakers positioned on the horizontal plane at a distance of 1.3 m from the center of the participants' head, where the listening level had been adjusted to peak values of 80 dB(A). B) Characteristics of the adopted wood-cracking sound (raw signal in the top panel and spectrogram in the bottom one). 86

5.2 Experimental paradigm. Each recording session was composed of two runs consisting of 80 trials. Each trial consisted of the presentation of the sound from a given direction. The randomized sequence of 80 directions within a run was balanced (10 repetitions for each of the 8 directions). A subjective feedback was provided after each trial through a custom mobile application. After the feedback, a random inter-trial time interval between 1 and 1.5 s was implemented to avoid inter-trial phase-locking effects. 87

5.3 Average response to the sound onset from lateral (red) and longitudinal (blue) directions (configuration S in Table 5.3). Panel A shows the ERP in the representative channel Cp1, highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). The same information is highlighted in the spatio-temporal domain in Panel B with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference among the two conditions. 89

5.4 Average response to the sound onset from left (orange) and right (violet) directions (configuration 5 in Table 5.3). Panel A shows the ERP in the representative channel Cp1, highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). The same information is highlighted in the spatio-temporal domain in Panel B with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference among the two conditions. 91

5.5 Characteristics of the simulated moving sounds adopted for the main sections of the experiment. They are constituted by a burst of four hand claps separated by 0.5 s (raw signal in the top panel and spectrogram in the bottom one), processed with Ambisonics [12] to give the impression of approaching (panel A) or receding (panel B) sounds. 99

5.6 Characteristics of the simulated stationary sounds adopted for the training section of the experiment. Just as the moving sounds, they are constituted by a burst of four hand claps separated by 0.5 s (raw signal in the top panel and spectrogram in the bottom one), processed with Ambisonics [12] to give the impression of close (panel A) or far (panel B) stationary sounds (at the same extreme distances of the moving ones to allow fair comparisons). 100

5.7 Direction independent individual ERP responses to sound onset (average of the responses to the four sound directions). Apart from minor differences in peak amplitude and latency, the overall shape is robust across participants. The onset response exhibits significantly larger responses than the following three responses which, in turn, show similar amplitudes. . 102

5.8 Average population-wide responses to front (blue) and rear (magenta) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. 105

5.9 Average population-wide responses to left (blue) and rear (red) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. Panel E and F show the ERP in channels T7 and T8 respectively, to give an idea of the contralaterality of the pattern. 107

5.10 Average population-wide responses to lateral (orange) and longitudinal (violet) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. 109

5.11 Average population-wide responses to approaching (pink) and receding (dark cyan) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. 110

5.12 Average population-wide responses to approaching (gold) and close stationary (brown) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. 112

5.13 Average population-wide responses to receding (brown) and far stationary (gold) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. 114

5.14 Population-wide direction-dependent difference waves representing "long" (between semantically unrelated trials, panel A) and "short" (between semantically related onset and subsequent response, panel B) habituation effects. Consistently with Figure 5.7, the great amplitude difference between onset response and subsequent ones results in greater differences than between subsequent semantically unrelated trials. A clear difference between lateral and longitudinal sounds is visible in both conditions, with a larger effect in the "short" case (panel B). Violet=Front, Cyan=Right, Gold=Rear and Red=Left. 115

5.15 Habituation effects related to the frontal direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the absence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B). 116

5.16 Habituation effects related to the rear direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the absence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B). 117

5.17 Habituation effects related to the right direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the presence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B). 118

5.18 Habituation effects related to the left direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the presence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B). 119

1 Eigenmike32™ microphone array 174

2 The first 16 Spherical Harmonics, corresponding to Ambisonics 3^{rd} order. 175

3 Frequency-dependent regularization parameter β (β_i in-band and β_o out-band 176

4 Experimental setup for measuring the microphone array response C. 176

5 Loudspeakers arrangement at Casa della Musica, Parma, Italy. 177

6 Signal processing flow. 179

List of Tables

4.1 Trials rejection rates 68
4.2 Performance rates achieved by the different classification models varying the training configuration 73
4.3 Classification performance achieved by the single general model with totally new subjects 75

5.1 Single-trial classification performance achieved in binary localization configuration (single individual directions). Bold values indicate the configurations where the average performance among the subjects minus the standard deviation is greater than the chance level (50%). 94
5.2 Single-trial classification performance achieved in ternary localization configurations (single individual directions). Chance level is 33%. 95
5.3 Single-trial classification performance achieved in binary localization configurations (aggregated directions), and quaternary, quinary and octonary localization configurations (single individual directions). Chance levels are 50%, 25%, 20%, and 12.5% respectively. 96
5.4 Windowed Means + Random Forest (WM + RF) 118
5.5 Continuous Wavelet Transform + Random Forest (CWT + RF) 119
5.6 Discrete Wavelet Transform + Random Forest (DWT + RF) . 120
5.7 Deep4Net 120
5.8 Rocket 120
5.9 Riemannian geometry 120
5.10 Approaching sounds only (WM + RF) 121
5.11 Receding sounds only (WM + RF) 121
5.12 Fourth response only (WM + RF) 121
5.13 Onset responses to sounds that varied direction (WM + RF) . 122

Acronyms

ADAS	Advanced Driver-Assistance System
EEG	Electroencephalography
ECG	Electrocardiography
GSR	Galvanic Skin Response
fMRI	Functional Magnetic Resonance Imaging
BCI	Brain-Computer Interface
ERP	Event-Related Potential
CNN	Convolutional Neural Network
SPL	Sound Pressure Level
KPI	Key Performance Indicator
ECoG	Electrocorticography
CAR	Common Average Reference
AEP	Auditory Evoked Potential
SEP	Sensory Evoked Potential
ITD	Interaural Time Difference
ILD	Interaural Level Difference
EP	Evoked Potential
SNR	Signal-to-Noise Ratio

MMN	Mismatch Negativity
OR	Orienting Reflex
PAC	Primary Auditory Cortex
IFC	Inferior Frontal Cortex
PT	Planum Temporale
IFL	Inferior Frontal Lobe
dlPFC	Dorsolateral Prefrontal Cortex
PMC	Premotor Cortex
IPL	Inferior Parietal Lobule
DWT	Discrete Wavelet Transform
CWT	Continuous Wavelet Transform
AV	Autonomous Vehicle
EV	Electric Vehicle
AVAS	Advanced Vehicle Alerting System
LIDAR	LIght Detection And Ranging
DSS	Denoising Source Separation
ROI	Region of Interest
IMU	Inertial Measurement Unit
MI	Motor Imagery

Chapter 1

Introduction

Interior and exterior vehicle noise comfort have improved significantly in the recent years because of the increasingly strict pass-by noise regulations and the rising share of quieter electric vehicles. Unfortunately, this noise reduction is introducing several side effects in terms of vehicle perception that car manufacturers are urged to tackle, especially because the noise reduction targets will become even stricter in the near future. One of the major safety-related issues is that comfortable autonomous vehicle (AV) or electric vehicle (EV) interiors with low noise levels have a negative influence on the driver's situational awareness which results in an increase of improper driving behaviors. Similarly, such quieter vehicles are less detectable by pedestrians and thus the risk of accidents due to erroneous behaviors increases.

A possible approach to tackle these issues consists in the introduction of artificial sounds to restore the acoustic feedback loop, both inside and outside the vehicle. To be effective, these artificial sounds must be comfortable to allow constant exposure and, at the same time, informative enough to effectively convey the intended message of emergency.

Both internal and external artificial warning sounds aim at informing the corresponding recipient about an incoming danger in the shortest possible

amount of time to obtain the quickest reaction. In this regard, to achieve an optimal result, it is of utmost importance to also provide the greatest amount of information in the same short amount of time to obtain the most accurate behavior. This concept is especially relevant in those dangerous situations where accidents are caused by people not paying attention to the road (e.g., engagement in other activities while being transported by an autonomous car or being lost in thoughts while approaching a crosswalk).

In all these cases, a great amount of information could be provided by adding spatial content to the warning sound, informing the recipient not only about the danger, but also about its direction. This would prepare the target person to properly and immediately counteract without having to recognize the direction themselves before acting. A data-driven, thus objective, approach to design and evaluate alternative spatial warning sounds taking into consideration both subjective perception and objective criteria, such as response time and accuracy, is necessary to achieve the goal. Even more useful in this context would be the ability to objectively and quickly determine whether the direction of a spatial warning sound has been correctly perceived. In the most extreme cases, this would allow to put automatic countermeasures in place, especially in situations involving autonomous vehicles that have the sensors and the processing power to perform a corrective maneuver in due time. In the past, several countermeasures have been proposed to restore the missing information while keeping low noise levels. For instance, to restore vehicle detectability, Acoustic Vehicle Alerting Systems (AVAS) have been devised and are now mandatory since 2019 in all electric and hybrid vehicles. These systems continuously emit artificial sounds to warn vulnerable road users of an approaching electric/hybrid vehicle.

The eVADER project [13] focused on AVAS and aimed to determine favorable characteristics of replacement sounds for electric vehicles that allow to maximize pedestrian safety while minimizing noise pollution. An interesting characteristic of the proposed system was the flexible directivity of the artificial warning sound that could be steered towards the pedestrians detected though the on-board sensors (cameras, Light Detection And Ranging (LIDAR), etc.).

In general, objectification of acoustic perception is of interest in all fields in which sound design plays a relevant role, such as automotive, avionics or entertainment. The most appropriate sounds for the intended purposes, including spatial sounds, are usually chosen based on subjective scores pro-

vided by jury testers, sometimes in combination with psychoacoustics metrics derived from prior knowledge of the human acoustic system. This approach is time-consuming and often results in sub-optimal choices that are strongly dependent on the characteristics of the evaluation group. In particular, the key issues are the variability of the subjective perception among multiple people and, even more so, the variability of the subjective scores provided by the very same person at different times depending on the context.

This approach is even less appropriate when it is applied for selecting sounds that must not be too annoying and, at the same time, must produce the best behavioral outcome for the specific purpose, like in the case of a spatial warning sound that has to induce the fastest and most accurate reaction, regardless of the context. It is evident that objectively selecting a sound of this kind based uniquely on subjective scores and psychoacoustic insights is cumbersome and suboptimal.

1.1 Motivation

A more suitable approach to convert the continuous acoustic perception into measurable Key Performance Indicators (KPIs) is therefore needed. Such a methodology would allow to jointly evaluate the general feelings and the real-world outcomes produced by a sound without needing to run any jury tests. Moreover, these KPIs could be used to constantly monitor the effectiveness of the deployed solutions.

A promising approach to achieve this goal consists in extracting information from objective psychophysiological measurements such as brain activity, heartbeat, skin conductance, respiration, and many others, to model the continuous subjective perception. As previous studies have shown [14], this information is accessible, at least partially, within Electroencephalography (EEG), Electrocardiography (ECG), Galvanic Skin Response (GSR), and respiration signals.

In this thesis we focus on EEG because it is the technique among the mentioned ones providing the highest temporal resolution, thus the greatest reactivity, and because the measured brain signals inherently include, at least partially, the electrical activity produced by the primary auditory cortex (PAC), which is the region where the entire high-level representation of the acoustic processing starts to be shaped [15, 16, 8, 17, 18, 19].

A large research body has investigated the cerebral acoustic processing,

and a consistent agreement has been reached on a dual-pathway consisting of a ventral "what" pathway involved in sound identification and a dorsal "where" pathway implicated in spatial recognition [15, 16, 8, 17, 20, 21, 22]. Even though shared processing has also been evidenced in the inferior parietal cortex [8, 23], specific regions seem to be consistently involved in the processing of either of the two acoustic characteristics. In particular, the inferior frontal cortex (IFC) and the frontal temporal lobe seem to be mainly engaged in content identification, whereas inferior parietal lobule (IPL) and the premotor and prefrontal cortex seem to be involved mostly in the spatial characterization of a sound. Interestingly, empirical results from both functional Magnetic Resonance Imaging (fMRI) and EEG studies demonstrated noticeable differences in the brain responses mainly between centric and eccentric directions [24, 25].

Together, this rather consolidated prior knowledge suggests the possibility of inferring objective information regarding the sound direction perception directly from measured brain signals. Consequently, we ask ourselves to what extent we can reliably decode the measured brain signals and what is the achievable classification performance. Moreover, we aim to understand if this kind of decoding is feasible in a general, non-participant-specific fashion, and, more importantly, in a single-trial mode. Even a partial success in this regard would provide useful insights for the spatial sound design and selection phase, as well as a means to monitor the online the correctness of the spatial perception. Indeed, several studies have gone beyond the pure characterization of the human cortical acoustic processing from a physiological point of view and preliminary attempted to decode the cerebral signals to infer the location of sound sources in empirical settings, which is the main goal of this thesis.

To our knowledge, as part of broader investigations, three studies attempted to classify EEG responses to sounds based on the corresponding source direction in a pseudo-realistic non-oddball-like setting [26, 27, 28]. Unfortunately, all these studies involved only few participants to be able to validate any hypotheses and evaluate general classification patterns (5, 3, and 6 participants respectively), and additionally, apart from [26], they approached the classification task in a simplified manner considering an aggregation of multiple brain responses to increase the signal-to-noise ratio rather than single trials. Nevertheless, the methodology and some insights originating from the presented results suggested to investigate the same subject

more in depth with more participants and sound repetitions.

1.2 Aim of the thesis

We propose to investigate two aspects of spatial sound perception: sound source localization in the horizontal plane and sound motion perception. Concerning sound source localization, we aim at empirically validate the possibility to classify the direction of the sound source from EEG signals in a pseudo-realistic scenario. In particular, compared to the majority of the available research on this topic, we intend to avoid implementing any oddball-like paradigms which are not representative of real-world conditions. Additionally, in the main experiments, we purposely focus on passive sound localization, without any active localization task to be performed by the participants, to simulate more natural situations. To be robust against participants' mental state and EEG helmet positioning, in all the experiments presented in this thesis, the participants have been asked to undergo multiple acquisition sessions performed on different days and with fully randomized stimulation sequences.

The key goals of the thesis in terms of real applicability considering the target automotive field are the identification of single-trial population-wide EEG patterns correlated with spatial sound perception allowing to classify specific sound characteristics such as sound source angle and motion direction. To be as realistic as possible, we rendered the spatial characteristics of interest in the experiments processing the selected natural sounds with state-of-the-art audio spatialization techniques based on the Ambisonics theory [12]. This allowed us to render more accurate spatial sounds in terms of perceived motion and direction compared to more basic approaches that simulate these spatial characteristics by artificially tuning Interaural Time Differences (ITD) and Interaural Level Differences (ILD) or spectral aspects.

To achieve these goals, a preliminary objective is the implementation of a portable infrastructure, consisting of both hardware and software, to use for all the experiments of this thesis and beyond, both for data acquisition and real-time processing, thus suitable for the whole spectrum of possible experimental configurations, starting from simple laboratory settings to more demanding simulated driving platforms and even real driving contexts. The target infrastructure must provide synchronization capabilities among multiple biosignals, vehicle telemetry measurements, and contextual information.

Moreover, it must guarantee a high signal quality (i.e., no artifacts due to electrodes shifts and no, or little, contamination due to muscle activity) even in demanding conditions such as while driving, as well as real-time processing capabilities for classification and actuation.

From the software point of view, the infrastructure must integrate a pool of preprocessing pipelines for data cleaning and rejection, features extraction routines and scripts to easily train different classification models both on raw EEG signals and on aggregated, manually crafted, features. Additionally, it must provide standardized methods to quickly run statistical investigations and visualizations of the physiological signals. This because even simple parameters such as filter type and bands, or whether to apply signal re-referencing and what kind of re-referencing technique to use, play a huge role in the classification results.

1.3 Structure of the thesis

In Chapter 2 we present from a high-level point of view the basic principles associated with the human brain that are relevant for the scope of this thesis. Initially, we illustrate the composition of the human brain and the functional specialization of the various regions of the cerebral cortex. Then we provide a description of the Electroencephalography (EEG) technique. The link between neuronal activity and the electrical signals measured at the scalp through EEG sensors or magnetic resonance imaging (MRI) systems is also outlined. Then a detailed description of Event-Related Potentials (ERPs) is provided to better understand the results and physiological visualizations presented in the following Chapters, as all the presented experimental studies are based on this widely known EEG pattern. In this section, a list of the most widely known ERP components is presented with a focus on the components normally elicited by auditory stimuli, especially when spatial perception is concerned. We then provide an in-depth overview of the spatial auditory processing in the human brain referring to the specific cortical regions involved and the associated ERP components.

In Chapter 3, the results of various studies that attempted to classify the direction of a sound source from the associated brain signals are summarized, together with an overview of some applications of EEG signals in the automotive field.

In Chapter 4 we provide a description of the proposed infrastructure along

with its validation in real driving conditions implementing a Brain-Computer Interface (BCI) to automatically control the infotainment menu of a car without any active intervention but rather leveraging the ERPs elicited by the presentation of the menu icons in an oddball-like carousel manner. One of the most relevant results presented in this Chapter is the generalization obtained by a single participant-agnostic classification model trained on three EEG channels only. The achieved population-wide performances are comparable with the participant-specific ones even when tested on participants completely new to the system (i.e., never seen during the training phase).

In Chapter 5 we present the main contribution of this thesis in decoding spatial perception from the measured EEG signals. The presented study implements a methodology to infer the azimuth of a sound source (horizontal direction) from the EEG signals. It is composed of a preliminary pilot study and a main experiment. Physiological analysis and classification results are described in details for both parts.

Finally, in Chapter 6 we draw the conclusions and outline the possible future work.

Chapter 2

Background

2.1 Brain structure and function

The central nervous system is composed of the brain and spinal cord. The spinal cord allows information to travel from the peripheral nervous system to the brain where it is processed. The brain is composed of three main structures that are hierarchically organized [29]: brainstem, cerebellum, and cerebrum.

The brainstem, which is the upper extension of the spinal cord, has two main functions. Firstly, it deals with autonomic control taking care of basic life support such as breathing, keeping circulation going, digestion, swallowing, and elementary sensory processing including internal chemical monitoring. Secondly, it filters the incoming information and routes it to the appropriate higher-level structures. Given the fundamental function of the brainstem, any damages to it would be catastrophic if not fatal. On the other hand, the cerebellum is responsible for body control (e.g., coordination) and motion memory, whereas the cerebrum, which is the largest part of the human brain, takes care of integrating and making sense of all the incoming information to perform executive functions and for emotional control. In



Figure 2.1: Three main structures composing the brain. Brainstem (magenta), cerebellum (green), and cerebrum (violet). The area highlighted in yellow represents the limbic system, and in particular the thalamus.

general, the functions of the cerebrum are mainly related to emotional responses, memories, cognition, language, problem-solving, and motor control. To make these advanced cognitive functions possible, folds have formed on the cerebral cortex throughout animal evolution resulting in a larger cortical surface area within the same space. This process is known as gyrification. The cerebrum is located on top of the brainstem and the cerebellum and is divided into two hemispheres (left and right) which are interconnected by a nerve fiber bundle called corpus callosum [30].

Another important mid-layer structure of the brain is the limbic system, which is composed of thalamus, hypothalamus, amygdala, ventral striatum, and hippocampus. It carries out core valuations scanning everything outside (sensory) and inside the body searching for anything relevant to pay attention to. These valuations constitute a survival mechanism that accounts for both threatening conditions (amygdala) and enticing or rewarding conditions (ventral striatum). Any of these significant conditions are signaled, in the form of feelings, to the higher-level structures, in particular the cerebral cortex, which contextualize them based on experience both from a cognitive (facts, reasons) and an emotional (emotional linkage) point of view to decide how to behave.




Figure 2.2: Limbic system. It is composed of hypothalamus, thalamus, hippocampus, and amygdala.

The cerebral cortex, which is the outer layer of the cerebrum, is the most advanced part of the brain and is responsible for higher cognition functions such as language, higher-order object recognition, and consciousness [31]. It is made up of gray matter (surface volume where the brain processes information) which surrounds the white matter (inner connections made of nerve fibers used to relay messages). The cerebral cortex is divided in four main lobes: frontal, temporal, parietal, and occipital [32]. It enforces a distributed processing through functional specialization; different parts of the brain are specialized in different things and get dynamically activated to carry out the chain of elementary cognitive operations required to perform the task at hand.

The frontal lobe is the largest lobe in the cerebral cortex and is specialized in executive functions, both mental and physical, such as problem solving, planning, execution of voluntary muscle movements, learning, reward, decision-making, and attention [33, 34, 35, 36, 37]. Moreover, it is also involved in emotional control [38, 39]. The area of the frontal lobe in contact with the parietal lobe is called primary motor cortex and is specifically involved in initiating and executing voluntary motor actions. In contrast, the frontmost area, which is called prefrontal cortex, is more involved in impulse control and executive mental actions such as decision-making, reward, problem solving, and planning. Another relevant functional region of the frontal lobe is the Broca's area, which deals with the stimulation of muscles involved in the production of speech [40].




Figure 2.3: Representation of the cerebral cortex. Each hemisphere is subdivided in 4 lobes: frontal lobe (red), parietal lobe (yellow), occipital lobe (lime), and temporal lobe (green). A general overview of the high-level functional specialization is provided.

The remaining three lobes deal more with sensory rather than executive functions. In particular, the temporal lobe, which is located on the side of the brain, is mainly dedicated to auditory processing [41]. Sounds reaching the ears are converted into electrical signals that are sent through the auditory nervous system to the brainstem which relays the information to the primary auditory cortex. Here is where we become consciously aware of the auditory stimuli. The information is then refined in the auditory association cortex where meaning is finally associated with the sound. The temporal lobe is also involved in object and face recognition through vision [42].

Wernicke's area is a particular region located in the temporal lobe which is not involved in auditory processing. It can be seen as complementary to Broca's area, since the latter controls speech and the former is involved in spoken language comprehension [43].

The parietal lobe is located posterior to the frontal lobe. Its main function is to make us aware of somatic sensations such as touch, pain, pressure, temperature, and vibration to contextualize external stimuli. At the same time, it builds awareness of body movement, action, and location, which is known as proprioception. Just posterior to the primary motor cortex, there is the primary somatosensory cortex. It is involved in conscious awareness of the mentioned somatic sensations. Indeed, it is where we first become consciously aware of somatosensory stimuli after the information has trav-

eled from the periphery through the nervous system. An important region located in the parietal lobe is the posterior association area, which is where the somatosensory, visual and auditory information meet. The joint contextualization of such information results in spatial awareness of the body and the environment.

Finally, the occipital lobe, which is the rearmost area of the cerebral cortex, is specialized in processing visual stimuli [44]. It is the region where the visual information is processed and compared to previous visual memories to provide meaning and understanding to the visual inputs and recognize what is being seen.

The nervous system is composed of neurons and glial cells. All functions performed by the nervous system require neurons to communicate with one another. Neurons are typically composed of a body cell, a series of dendrites and synapses, and one or two axons. The communication consists of an electrochemical process in which the neurons receive information in chemical form (neurotransmitters) through the dendrites and send information out in electrical form (action potentials) through the axon (see panel A of Figure 2.4 for a representation of two interconnected neurons). The information is effectively propagated from one neuron to another at the synapses, which are junctions between the axon terminals of one neuron and the dendrites of another. In this stage, neurotransmitters are released by the axon terminals of the presynaptic neuron and received by the dendrites of the postsynaptic neurons. This communication process is possible because neurons are electrically excitable, due to the voltage difference across their membranes, and the charge of these membranes can change in response to neurotransmitters released from other neurons. If the membrane potential changes by a large amount over a short period of time, the neuron generates an action potential. This usually happens when one neuron is simultaneously excited by multiple other neurons. If the resulting difference in voltage at the cellular membrane exceeds a threshold potential the neuron fires, propagating the electrical signal through the axon towards other downstream neurons. This activity is orchestrated by the glial cells, which modulate the communication. More precisely, they make the whole neuronal functioning possible as, not only do they modulate the communication, but they also guide developing neurons to their destinations and prevent harmful electrical and chemical elements to damage the neurons.

In almost all cases, electrical activity measured at the scalp originates




Figure 2.4: **A)** Representation of two interconnected neurons. The action potentials of the presynaptic neuron on the left travel through its axon and reach its terminals where the chemical synaptic communication toward the dendrites of the postsynaptic neuron on the right takes place. This process consists in the release of neurotransmitters that produce voltage variations in the downstream neuron. **B)** Pyramidal cells of the cerebral cortex, considered the main responsible of the electrical activity measurable at the scalp with the EEG recording technique. Source [1].

from postsynaptic potentials, which occur when neurotransmitters bind to receptors at the synapses, changing the potential of the cell membrane [45]. They are typically not produced by action potentials (except for early auditory responses) as they travel quite long distances along the axons in a very quick time (around 1 millisecond) and therefore it is difficult to have large populations of neurons firing precisely at the same time (i.e., with delays in the order of microseconds). On the other hand, postsynaptic potentials typically last tens of milliseconds and are more confined as they take place in small spaces between the dendrites and the cell body. When postsynaptic potentials simultaneously develop in large populations of neurons that are oriented in the same direction, they summate and propagate through the brain and the skull reaching the scalp with a sufficiently large amplitude to be measured in the form of EEG. If the orientation of the neurons in a given region is not the same, the flow of current cancels out making it impossible to measure the underlying activity at a distant electrode. The main neurons exhibiting this property are the pyramidal cells of the cerebral cortex (the primary input-output cells of the cortex). Their orientation is perpendicular to the cortical surface, and therefore their dipoles summate almost perfectly (see panel B of Figure 2.4). Additionally, they are often active in unison. As a result, scalp-recorded electrical activity almost always reflects information




Figure 2.5: High-quality EEG signals collected during an acoustic experiment. Each row corresponds to a different measurement site on the scalp (see Figure 2.6 for the exact positions).

flow occurring in large groups of cortical pyramidal cells [1, 46]. Most of the other structures either produce currents that are too weak to be measured on the scalp or do not present the same neuronal orientation. For this reason, only a tiny fraction of electrical brain activity is measurable on the scalp.

2.2 Electroencephalography

Electroencephalography (EEG) is a widely used methodology for the non-invasive recording of brain activity. Its realization is called electroencephalogram and consists of electrical signals simultaneously recorded at various sites around the scalp by means of specific electrodes (see Figure 2.5). These electrical fields are generated by ionic current flowing through the neurons. In particular, the fields observed on the scalp are generated by large populations of neurons firing at once located in the cerebral cortex and, more generally, due to the volume conduction, from different parts of the cortex at the same time [1].

Alternatively, brain activity is also recorded from within the skull, placing electrodes (needles in this case) directly on the surface of the cerebral cortex. This technique is called Electrocorticography (ECoG) and provides stronger and more localized signals, but implantation of the electrodes involves invasive surgery and thus is undertaken with clinical patients only. Therefore, for research purposes, EEG signals are usually recorded. They are commonly measured using electrodes placed around the scalp according to high-density configurations (in most cases consisting of up to 256 elec-

trodes) deriving from the international 10-20 system [47] or the 10-10 and 10-5 extensions. These systems define the position of the electrodes relative to anatomic landmarks on the human head (inion, nasion, and pre-auricular points) to generalize across people preserving the relationship between electrodes and the underlying brain areas [48, 49, 50]. The names 10-20, 10-10, and 10-5 refer to the fact that the actual distances between adjacent electrodes are either 20%, 10%, or 5% of the total front-back or left-right distance between two landmarks.

Regardless of the placement configuration, EEG signals can be recorded by the electrodes using referential or bipolar montages. The former records the individual potential difference between each electrode and a common electrode (reference), whereas the latter records the potential difference between two adjacent electrodes. Both montages have advantages and disadvantages [51]. In particular, the referential montage is ideal to compare all electrodes and allows the usage post hoc re-referencing methods but, since a truly inactive reference doesn't exist, it contaminates all signals with the reading of the "active" reference. Bipolar montages, instead, help to identify noise and eliminate the issue of contaminated references [47] but they distort the actual waveforms, have poor expressivity with respect to widespread activity, and are not suitable for post hoc re-referencing. Re-referencing consists in applying spatial filters with the goal of revealing the true electrical activity that was blurred by the adopted physical reference montage. Common-Average Reference (CAR) [52] and Laplacian are the most widely used re-referencing techniques. CAR reduces the effect of contaminated reference and localized noise while preserving a good representation of the waveform. Laplacian reduces the effect of volume conduction and thus enhances the localization of active areas.

Despite the high density, EEG is characterized by a low spatial resolution, in the order of centimeters, which is one of its main limitations. Each electrode records activity not only from the underneath neurons but also from surrounding areas. Moreover, since the electrical signals radiate from the sources in different manners depending on the orientation of the neurons and the tissues they travel through, the same cerebral activity can be measured at different electrode sites in a different form and, at the same time, the signals measured by the electrodes represent the summation of multiple processes. For this reason, there is usually high correlation among signals recorded by nearby electrodes and the localization of the individual sources




Figure 2.6: Top view of the international 10-20 system for EEG electrodes placement. Electrode names beginning with the letter "F" represent positions covering the frontal lobe, and the same applies to the letters "C", "T", "P", and "O", representing central, temporal, parietal, and occipital positions respectively.

is difficult.

The other main limitation is the low signal-to-noise ratio. EEG signals are characterized by a typical amplitude that ranges from 10 µV to 100 µV and therefore not only do they represent the combination of cerebral activity produced by functionally distinct regions but are also easily contaminated by electrical fields produced by muscles and other sources of noise, as their amplitude is generally orders of magnitude greater. More generally, in EEG terms it is considered noise any external or internal signal that is not related to a target cognitive process. External noise can arise from faulty or mishandled equipment or untreated bad environmental conditions (e.g., excessive 50/60 Hz electrical powerline noise), whereas internal noise may arise from eye and body movements, heart activity, or cerebral processes related to phenomena other than the ones under investigation. Preprocessing is usually performed on EEG signals to increase the signal-to-noise ratio. In any case, EEG signals are non-stationary since they are continuously affected by the environment and variations in physiological factors.

On the other hand, the main advantages are the portability, the relatively low cost compared to other recording techniques, and the high temporal resolution (few milliseconds). In particular, the latter represents the main

benefit for studying the spatiotemporal dynamics associated with cognitive processes, as neural responses are modulated by internal and external events in a matter of milliseconds.

EEG signals are characterized by rhythms at different frequencies that reflect the neural oscillations in the central nervous system. These oscillations, also called brain rhythms, represent fluctuations in the excitability of large populations of neurons and they are characterized by frequency, power and phase. Brain rhythms are conventionally subdivided into five frequency bands [1, 53]: delta (δ, 0.5-4 Hz), theta (θ, 4-8 Hz), alpha (α, 8-13 Hz), beta (β, 13-30 Hz) and gamma (γ, $>$ 30 Hz). This subdivision derives from general knowledge about the neurophysiological mechanisms generating the oscillations [54, 55, 56]. A unique consolidated interpretation of the different frequency bands is still missing and therefore the mentioned boundaries are just theoretical, however, it exists a broad consensus on the fact that different frequencies are associated with distinct behavioral states [57, 54]. In particular, δ rhythms are found in deep sleep, θ rhythms have been associated with drowsiness, memory load and cognitive demand such as problem solving [58, 59], α rhythms are normally seen in relaxed states, especially in the occipital lobe when the eyes are closed [32], β rhythms are associated with active, busy or anxious thinking and concentration or excitation, and γ rhythms are associated with memory, attention and cognitive functions such as perception and consciousness [54, 60].

The electrophysiological study of cognition aims at finding a correlation between EEG signals and the cognitive processes that produce them. Cognitive processes are directly associated with cognitive events, which can be described as moments at which we perceive (become aware of) the significance of some sensory event and, accordingly, start performing memory associations, reasoning, and planning. These cognitive processes involve and/or produce complex and distributed changes in EEG dynamics that require mechanisms of information transfer between brain regions that are potentially dynamically dependent both on the nature of the stimuli themselves and on internal and external context.

Depending on the context, the mental processes under investigation are induced by external stimuli, usually visual, auditory, or tactile, or they are spontaneous and self-initiated. In the former case, the underlying processes are generally time-locked to the events and aim at recognizing the stimuli and understanding the context. In the latter case, no external events are in-

volved and therefore the cognitive processes are the actual drivers of actions like solving a mathematical problem or writing a message. As a result, while it is evident that the EEG signals following an event are the ideal candidate to make a high-level description of the associated event-related process, it is more difficult to confine the information of interest in case of spontaneous processes, especially because the actions and the underlying cognitive processes evolve co-modulating each other. For this reason, it is extremely difficult to gather reliable knowledge about the cerebral processes behind extemporaneous events like spontaneous emotions or intuitions.

EEG responses associated with an external stimulus are called Evoked Potentials (EPs) and more precisely, if a cognitive activity is involved, they are generally known as Event-Related Potentials (ERPs). Depending on the stimulus type (auditory, visual, or somatosensory), EPs occur in different regions as the information travels through a different cerebral pathway. Auditory-Evoked Potentials (AEPs) build up in the auditory pathway from ears to the auditory cortex, Visual-Evoked Potentials (VEPs) build up as the information travels from eyes to the occipital cortex, and the Somatosensory-Evoked Potentials (SEPs) build up in the pathway that goes from peripheral nerves to the somatosensory cortex (they are the response of the somatosensory cortex to stimulation of a peripheral nerve).

A common experimental procedure to investigate the cognitive processes associated with external events consists in presenting a random or pseudo-random sequence of stimuli (trials) to the subjects while recording their EEG signals. To avoid adaptation and phase-locking effects, the stimuli are interleaved with a random, sufficiently large, time period which is often referred to as inter-trial interval [61]. Normally, the stimuli are of the same nature (e.g., auditory or visual) but have different characteristics, and the goal of the investigations is to discriminate between them assuming that different characteristics are processed differently and thus produce different EEG responses. The main differences are usually in latency, amplitude or spatial location of some characteristic peaks of the responses.

Single-trial ERPs are difficult to recognize and characterize because they are contaminated by background cerebral activity and external noise that are independent of the stimuli. This results in signal-to-noise ratios as low as –5 dB [62]. To mitigate this issue, instead of evaluating single-trial ERPs, the average of many responses is considered [63, 64]. The assumptions behind this approach are that ERPs exhibit the same shape each time the same

person is presented with the same stimulus and that the background cerebral activity and external noise are zero-mean [65]. As a result, all these signals that are independent of the ongoing cognitive process cancel out because their average is equal to zero. On the contrary, the true ERP emerges as the shape stabilizes as the number of averaged responses increases. Unfortunately, there is evidence indicating that Evoked Potentials (EPs) are stochastic processes and that the variations among individual responses are related to the context [66]. In particular, the variability among single-trial ERPs may be associated with changes in the cognitive processes involved in recognizing and elaborating the stimuli. This information is lost through averaging and therefore more advanced techniques to identify and characterize single-trial ERPs are being investigated.

2.3 Event-Related Potentials (ERPs)

EEG is a coarse measure of brain activity, and therefore it is unsuitable for measuring most of the highly specific neural processes that are the focus of cognitive neuroscience. This is partly because EEG represents the superposition of dozens of different neural sources of activity, making it difficult to isolate individual cognitive processes [67, 68]. Part of the measured EEG consists in responses that are direct result of specific sensory, cognitive, affective, and motor events. These responses are called Event-Related Potentials (ERPs) to denote the fact that they are electrical potentials evoked by specific events [46]. Given that EEG reflects hundreds of simultaneous processes, brain activity specifically related to recognizing and processing a single event of interest is usually not visible in the EEG recording of a single trial. Indeed, most ERPs are rather small compared to the ongoing background EEG activity and usually become visible only when multiple trials are combined to form an average ERP. More precisely, multiple responses associated with the same stimulus are averaged so that brain activity unrelated to the stimulus cancels out revealing a more reliable ERP waveform. This approach is based on the time-locked nature of the cerebral processes involved in dealing with exogenous or endogenous events. The signal of interest, namely the average ERP waveform at any given scalp electrode site, is the result of the weighted electrical summation of multiple event-related processes taking place in different regions of the brain at different times with respect to the onset of the event. Each of these distinct event-related processes is associated with an

underlying electrical component. The resulting ERP waveforms represent the event-related neural activity and reflect the overall flow of information across the brain. These waveforms consist of series of positive and negative deflections which, in turn, are often defined in terms of a combination of amplitude, latency, and scalp topography of their peaks. Unfortunately, these peak characteristics can vary from context to context (trials, subjects, experiment, etc.) and therefore provide little information about the structure of the underlying components. For instance, the scalp distributions vary dramatically depending on the choice of reference electrode. In addition, when the values are measured at multiple electrode sites, it makes no sense to use the peak at each electrode site to measure a single component since the peak will occur at a different time at each electrode site, whereas the underlying component necessarily has the same time course at each electrode site (because of the instantaneous transmission of voltage).

Peaks are usually labelled using either the letter P or the letter N depending on the orientation of the deflection, and by a number that represents the latency (in hundreds of milliseconds) or the ordinal position of the peak in the waveform with respect of to the event onset. The most widely known peaks are named P1, N1, P2, N2, and P3. The polarity of the deflections depends on a combination of several factors, and it is usually difficult to draw strong conclusions about one underlying component based on the polarity of the associated deflections. Considering the equivalent dipole representing the congruent summation of multiple single dipoles, the electrical activity recorded on the scalp can be simultaneously positive on one side of the dipole and negative on the other. This situation is reflected in individual peaks that exhibit opposite polarity at different electrode sites at the same latency. To complicate the situation even further, the electrical properties of the skull and the scalp tissues smear the electrical fields resulting in spatially blurred distributions on the scalp surface. As a result, the main advantage of ERP analyses relies on their ability to precisely track the time course of processing. Since electrical potentials travel almost at the speed of light, the transmission through the brain, skull, and scalp is essentially instantaneous. In other words, the voltages measured on the scalp at a particular time reflect synaptic activity at that particular instant, with very little delay. On the other hand, the main limitation is the lack of the spatial resolution required to investigate the operation of specific neural systems or to precisely locate the origin of some event-related components.

Another issue arises when latency jitter is present for a component across trials and the averaging technique is applied. If it is the case, the average ERP waveform will contain a smeared version of the component. Specifically, the average ERP waveform will reflect both the earliest onset and latest offset times of the component, as opposed to reflecting the average onset and offset times. In addition, latency jitter can greatly reduce the measured peak amplitude.

The similar issue is present when averaging is performed across multiple subjects. In this case, there is usually a quite substantial variation in shape across subject-specific waveforms. For later periods of the waveform that reflect higher cognitive processes, differences in amplitude and shape may reflect differences in the strategies subjects apply when performing cognitive processing. Therefore, individual differences in the size and shape of the waveform may reflect actual processing differences. However, for the sensory processing that occurs during the first 200 ms after the onset of the stimulus, it is unlikely that differences in waveform amplitude and shape reflect differences in strategy or processing. Instead, the waveform differences most probably derive from differences across subjects in nonfunctional factors such as skull thickness and cortical folding patterns.

The characteristic peaks of an ERP waveform typically reflect the sum of multiple internal, underlying components, and the goal of ERP studies is to determine how these components differ across conditions. It is important not to confuse the peaks (reliable local voltage maxima) measured on the scalp with the internal underlying brain components (discrete intracranial sources of voltage that reflect specific neurocognitive processes that summed together form the measured waveform), as the peaks do not map onto distinct underlying components in a simple one-to-one manner. It is the underlying components rather than the peaks that directly reflect the neural and psychological processes of interest. The neural activity associated with each distinct mental process may last tens or hundreds of milliseconds, which means that the signature of one process will most likely overlap with that of other subsequent or simultaneous processes. Even if these neural processes occur in separate regions of the brain, the ERP waveform at any given scalp electrode will be the weighted sum of all the underlying component waveforms, and therefore the recorded peaks will represent the electrical interaction of several separate components. This weighting is because the propagation of voltage from a single component generator site to a particular electrode site

depends on the position and orientation of the component source with respect to the electrode, along with the conductance of the brain, skull, and scalp. Therefore, the relationship between each electrode site and each underlying component is represented by a different weighting factor.

Additionally, although the ERP waveform at a particular instant reflects synaptic activity at that moment, it does not reflect only the neural activity that began at that particular instant. It might also represent previous neural activations that are still active. As a result, multiple components, and thus corresponding equivalent current dipoles, are usually active simultaneously. In fact, source localization studies have shown that as many as 10 separate equivalent current dipoles may be active within a given 150 ms period [67, 68]. A formal definition of ERP component that has been established is the following [69, 46]: "An ERP component is a scalp-recorded neural signal that is generated in a specific neuroanatomical module when a specific computational operation is performed". Consequently, a component may occur at different times depending on the experimental conditions, but to be considered the same component it must originate from the same module and must represent the same neural process. According to this definition, many well-known macro ERP components shouldn't be considered individual components as they reflect different computations carried out by multiple brain areas.

In general, ERP analyses focus on onset, duration and temporal evolution of underlying processes rather than their peak. Whereas it is relatively easy to characterize a scalp ERP waveform based on its peaks, it is particularly challenging to precisely isolate and localize the true internal underlying components purely based on the signals recorded on the scalp because of the superposition problem (i.e., the superimposition of many underlying components that forms the recorded scalp waveform makes it is difficult to decompose the recorded signal to isolate the individual components). The problem of overlapping components makes it difficult to ascertain whether a change in a peak is due to a change in one or multiple components [61]. More generally, it is difficult to determine if an experimental manipulation has modulated the strength or timing of a specific component, or rather has produced a change in the subject behavior that has affected some other overlapping components. On the other hand, considerable information about the structure of the underlying component can often be obtained by examining the waveforms (especially difference waves) from multiple electrode sites,




Figure 2.7: Artificial representation of an ERP response (red) resulting from the interaction of three components which differ in peak activation amplitude, magnitude, and timing. The electrical scalp recordings can exhibit reductions, amplifications, or even cancellations of relevant peaks, as well as deformations in latency and topography. The resulting response (red) presents amplitude reductions and temporal shifts of all three peaks compared to the corresponding underlying components.

because different components will be weighted differently at each electrode.

The identification of the underlying components from the recorded scalp waveforms is called inverse problem and it is complex, if not impossible, to solve with 100% accuracy because it is an ill-posed (underdetermined) problem. Indeed, there are infinite possible combinations of arbitrary underlying components that summed together result in the measured scalp recording [70, 50]. In general, some of these combinations are inadmissible from a physical point of view, whereas others are more physiologically reasonable. In any case, there is no way to tell with certainty which one is actually responsible for producing the observed voltage distribution. Even the number of underlying components is usually unknown. There are many different methods that attempt to solve the inverse problem, but all of them are based on assumptions that are hardly verifiable. This problem becomes even worse considering the generally low signal-to-noise ratio (SNR) of EEG recordings. In many experiments, the number of dipoles could be very large, and even a relatively low level of noise would make the dipole localization impossible.

Some commonly used procedures allow to constrain the number of dipoles [71] or their location [72, 73]. As one might expect, they often provide quite different solutions, making it difficult to verify if one is actually correct.

Difference waves are often used to gather more reliable estimates about the scalp distribution, temporal evolution, and the number of the underlying components. They consist in the difference at each time point between the ERP waveforms associated with two different experimental condition. Although conceptually very simple, difference waves help making the time course of experimental effects clearer, which, in some cases, is even more important than precisely identifying all the involved underlying components. It is not guaranteed that the difference wave will represent only a single component, however, there is a good chance that it will if there is only a slight difference between the two conditions. In general, given that ERP waveforms at different scalp sites reflect the same components but scaled by different weighting factors (the underlying components have exactly the same time course at every electrode site because the voltage propagates instantaneously to all electrodes), the combination of an inspection of difference waves at different electrodes and a source localization analysis seems to be the best approach to identify the structure of the underlying components. This is because a well-constructed difference wave (i.e., obtained from slightly different experimental conditions) contains fewer components than the original scalp waveforms, making it easier to disentangle them. If two conditions differ in some source components and not in others, then the difference wave will eliminate the common components leaving those that differ. For instance, if the scalp distribution of the effect is the same throughout the entire time course of interest, it could be a hint that it is produced by a single component [46].

The high temporal resolution of ERPs makes them an excellent tool for determining the time course of a neural or psychological process and therefore suitable for: 1) determining which neural processes differ across conditions (e.g., perception of stimuli characteristics, attention, etc.) or across groups; 2) determining whether and when some event-related brain processes are completed; and 3) covert monitoring of processing in situations in which overt behavior is difficult to measure or interpret (e.g., coma, infancy), or even undesirable (monitoring processes of unattended stimuli). There are also situations in which a person might voluntarily avoid making a valid behavioral response, such as a suspect criminal, and in these cases, ERPs

have been used as part of a polygraph to assess whether the person has knowledge of an event that he or she is not admitting [74, 75].

Regardless the usage, in cognitive neuroscience research it is advisable to follow established guidelines [64] and, if possible, to focus on ERP components that are large compared to the background activity (e.g., P3) and to design experimental paradigms such that only one or two ERP components differ across conditions. Then, as already mentioned, it is often advisable to compute difference waveforms between conditions or between electrode sites taking into consideration also the scalp distribution to isolate the specific ERP components affected by the experimental protocol. This approach allows identifying the time point at which the waveforms associated with the two conditions diverge. For instance, ERPs have been used to determine when, after the onset of a stimulus, processing differs between emotional and neutral stimuli such as words, facial expressions, and images [76, 77, 78, 79, 80, 81, 82, 83, 84, 85, 86, 87, 88, 89, 90, 91]. This method does not require isolating a specific component or linking a component to a specific process, and therefore it is sounder as it avoids making the previously discussed weak assumptions needed to isolate or work with ERP components. Of course, this method provides an upper bound on the timing of an effect. Since many processes may be invisible in scalp recordings, the brain might have made a distinction between two stimuli long before a difference is noticeable in the scalp-recorded signals. Even more complicated is the investigation of brain processes whose result might not reach awareness or trigger a behavioral response. By using ERPs it is possible to estimate the amount of information that has been extracted from a stimulus that does not reach awareness compared to a similar one that does.

2.4 ERP components

ERP components can be divided in three main categories: exogenous sensory components that are induced by external stimuli, endogenous components that reflect task-dependent neural processes, and motor components that materialize during preparation and execution of motor actions. The focus of this paragraph is on exogenous components.




Figure 2.8: Stereotypical representation an auditory evoked potential (AEP) which illustrates the four main auditory component. The first component is associated with the P1 peak, which is normally measured around 100 ms after the sound onset. The second, which is usually more informative when cognitive acoustic processing is concerned, is the N1, and its peak is usually observed between 120 and 200 ms from the onset. The following is the P2, which is the one normally exhibiting the greatest amplitude. It is the second positive peak and is usually found around 300 ms. Finally, the long-latency N2 component peaks around 350-400 ms from the sound onset. Source [2].

2.4.1 P1-N1-P2 complex

The P1, N1 and P2 constitute a complex of exogenous components that are present both in visual and auditory sensory evoked responses. Depending on the nature of the stimuli, they may vary in spatial distribution ad latency.

The visual P1 component is a positive-going component sensitive to variations in visual stimuli parameters whose peak is observed around 80-130ms [92] over the lateral occipital scalp, approximately right over the ventrolateral prestriate cortex, contralateral to the visual field in which the stimuli is presented [93]. Some studies suggest it be modulated by selective attention

[94, 95] and by the subject's state of arousal [96]. Concerning the attention dimension, the P1 is proposed to reflect some sort of "cost of attention" [97]. When a subject is paying attention to a particular area and the target stimulus is presented outside that area, there is a decrement in the P1 amplitude [98, 99]. This decrement (or suppression) of the P1 might represent the cost of having to stop attending to one area and shift the attention to the place where the target stimulus is located [97]. An opposite pattern is associated to the N1 component which exhibits an increment in amplitude when a subject is attending to a certain area and the stimulus is shown in that area [97].

The P1 wave is followed by the N1 wave. It is the result of several visual N1 subcomponents that are not necessarily functionally related but contribute to the same visually salient deflection in the waveform. The earliest N1 subcomponent peaks between 100 and 150 ms after the onset at anterior electrode sites, then there appear to be at least two posterior N1 components that peak between 150 and 200 ms after the onset, one arising from parietal cortex and another arising from lateral occipital cortex. Many studies have shown all three subcomponents to be influenced by spatial attention [92, 94]. The latter subcomponent appears to be larger when subjects are performing active discrimination tasks than when they are simply detecting the presented stimuli, which has led to the proposal that this subcomponent reflects some sort of discriminative processing [100, 96, 101].

The P1 and N1 components also represent cortical activity resulting from sound stimuli [102, 103, 104, 105, 106, 107, 108], form part of the bottom-up auditory pathway [109]. The N1 component plays a role in the initial discrimination of acoustic stimuli [110, 111] and may represent the activation of the planum temporale [112].

The auditory N1 deflection appears with negative polarity over the fronto-central scalp, typically peaking between 100 and 120 ms from stimulus onset (Figures 2.8 and 2.9). N1 is elicited by sudden changes in sound energy, such as sound onset or an abrupt change in the spectral make-up of a continuous sound [113]. In short, the auditory N1 is elicited by acoustic change. A large part of the auditory N1 is generated bilaterally within primary auditory cortical areas. However, the auditory N1 is not a single component as it has multiple generators both within and outside the auditory cortex, which are differentially affected by stimulus parameters [106, 114]. Increasing the inter-stimulus interval increases the N1 amplitude up to at least 10 s and the auditory N1 is sensitive to most sound features. These findings suggest

that the neuronal generators of N1 are involved in the temporary storage of auditory information. However, the N1 is not sensitive to combinations of auditory stimulus features. Therefore, the neural generators of auditory N1 cannot implement an integrated memory representation of a sound [115]. Some of the exogenous ERP responses (P1, N1, P2) may reflect the emergence of new auditory streams. These responses are sensitive to large changes in stimulus energy, which is a prime cue for the activation of a new sound source.

Like the visual N1 wave, the auditory N1 wave is composed of multiple distinct subcomponents [106]. The most evident ones are: 1) a component that peaks around 75 ms after the stimulus onset that appears to be generated in the auditory cortex on the dorsal surface of the temporal lobe, 2) a component that peaks around 100 ms on the vertex (Cz) whose origin is unknown, and 3) a more laterally distributed component that peaks around 150 ms whose source appears to be in the superior temporal gyrus. Moreover, also the auditory N1 wave is sensitive to attention [116].

A distinct P2 wave follows the N1 wave peaking at anterior and central scalp sites (see Figure 2.9). Larger P2 peaks are measured in response to target stimuli, and this effect is even stronger when the targets are relatively infrequent [97]. Although both P2 and P3 are larger when infrequent target stimuli appear (in oddball paradigm for instance), the P2 effect occurs only when the target is easily and quickly discriminable, whereas the P3 effect can occur for arbitrarily complex target categories. In general, little more is known about the posterior P2 wave because it is often undistinguishable from the overlapping N1, N2, and P3 waves.

The N1 and P2 responses are also influenced by increases in the acoustical features such as sound intensity and spectral flux, which are commonly used to locate the onset times of syllables in speech and the onsets of tones in music [117, 118, 119]. Additionally, their peak amplitudes are influenced by inter-trial interval following a somehow linear correlation: the greater the interval between the stimuli, the larger it is the amplitude of the two peaks [120, 121, 106]. It was shown that the maximum amplitude is observed with inter-trial intervals in the range between 6 and 10 s [122, 123]. This effect seems to be associated with a refraction effect which is reflected in lower amplitudes when the neurons do not have enough time to return to baseline levels when the intervals between subsequent stimuli are too short [3, 61].

Source localization analyses performed in previous studies related to nat-




Figure 2.9: Electrical and topographical representations of the two main acoustic evoked components varying the inter-stimulus interval. As can be seen, both the N1 and the P2 component are modulated by the temporal separation dimension: the more temporally isolated are the sounds, the larger are the amplitudes of both vertex components. Source [3]

uralistic sounds showed that the neural generators of the P2 responses to sound intensity variations originate from the primary auditory cortex and the temporal pole [124, 125] whereas the generators of the P2 to the spectral flux variations originate from the primary and secondary auditory cortex [126, 127].

The P2 auditory component has been shown to reflect sound classification




Figure 2.10: Representation of the human auditory cortex. It is both anatomically and functionally subdivided in primary and secondary auditory cortex. Closely linked to the to this cerebral region are the temporal pole on one side (front) and the planum temporale on the other (rear).

and to be associated with interference prevention mechanisms [128].

Also the late N2 and P3 components are influenced by external events, indeed they are easily identified when the oddball paradigm is used but seem to be associated with supra-modal auditory factors [129, 130]. In particular, they are considered endogenous as they are more influenced by cognitive processing and reactions to the stimuli rather than their characteristics [131, 69].

In the acoustical context, the N1-P2 complex, also known as "vertex potential", primarily reflects sensory and perceptual processes at the initial stages of auditory processing [132]. For instance, the amplitude of N1-P2 is apparently determined within about 30 msec after the sound onset [133]. Indeed, the two components are thought to be generated in the auditory cortex [134, 135]. Furthermore, several studies associated the N1-P2 complex with improved acoustic cues detection and encoding [136, 137, 138, 139, 140, 141, 106]. On the other hand, late components, namely those occurring later than 200 ms after the sound onset, have rather been associated with endogenous and cognitive processes [142]. In particular,

the N2 component seems to be involved in conscious auditory categorization, [143, 100, 144, 145, 146] and to lexical content extrapolation [147], while the N400 component has been linked to semantic categorization [148], memory functions [149] and pitch labeling processes [134, 146] (even though absolute pitch has also been associated with the N1 component [150, 4]).

A similar separation has been proposed for emotional speech processing, with early components involved in sensory processing and late components implicated in meaning extrapolation and integration [151]. Also in this context, the N1-P2 is thought to reflect decoding and aggregation of acoustic features such as tonal frequencies, intensity, and inter-stimulus interval [136, 152, 153, 154, 155], while late components are suggested to be linked to more complex ("meaning-related") emotion and semantic processing [156, 157, 158] and to be strongly influenced by arousal [159].

Often the N2 and N400 peaks are present together [4, 160, 161, 133] even though no conclusive evidence of similar underlying origin or direct interaction has emerged (see Figure 2.11 for the corresponding topographies). On the contrary, the two components seem to reflect different processes, the former more related to object identification/recognition (pre-semantic perceptual processes) [162] and the latter to semantic elaboration [163, 4]. In the acoustic context, this view about the N2 component is supported by another study suggesting it to be associated with an initial shift of auditory spatial attention towards the target direction, regardless of whether the spatial information is relevant for the task or not [164].

The acoustic N2 component, more precisely the N2b component, is suggested to be related to the orienting reflex (OR), which is an immediate response/reaction to a change in the environment associated with significant stimuli [165, 166]. Due to its very nature, it occurs whether the stimuli are attended or not [167] and is affected by habituation or refractoriness [168, 5] (see Figure 2.12). As previously mentioned, the fact that the N2 and P3 components have been recorded in significant absences of stimuli, suggests that they could be related to the meaning attributed to the stimuli rather than to their physical characteristics, and thus have been considered endogenous.

2.4.2 Mismatch negativity (MMN)

From a general point of view, the N2 deflection is also elicited by repetitive nontarget stimuli [169]. In particular, if deviant stimuli are occasionally




Figure 2.11: Representation of both early (N1 & P2) and late (N2 & N4) auditory components, along with the corresponding topographies. The figure on the left shows the classical fronto-central topography of the N1 and P2 components, whereas the figure on the right reveals more frontal topographies for the N2 and N4 components. Source [4]




Figure 2.12: EEG trace resulting from the average of twenty-four 16-second-long responses displaying the classical P1-N1-P2 complex in evoked by 8 impulsive sounds. Unsurprisingly, the onset response exhibits significantly larger amplitudes both in the N1 and P2 peaks with respect to the subsequent responses. Additionally, a habituation behavior is visible in the decreasing peak amplitudes trend, especially in the first evoked responses. Source [5]

presented within the repetitive train (e.g., in an oddball paradigm), a larger amplitude is observed. Evidence suggests that the N2 component is the results of at least three subcomponents [144, 170] which vary depending on attention, and stimulation modality. One of its subcomponents is the previously mentioned N2b but, in this case, an earlier component, namely the N2a, is also evoked. It is a relatively automatic effect that occurs for auditory mismatches, even if they are task irrelevant. This effect is commonly known as mismatch negativity (MMN) and is characterized by a peak between 160 and 220 ms exhibiting a frontocentral midline scalp maximum. As a matter of fact, also a third component located in the prefrontal cortex which is involved in shifting attention to the deviant sound is thought to contribute to the MMN effect [170].

The deviant sound can differ from the standards in one or more perceptual features such as pitch, duration, or loudness. The MMN is usually evoked by either a change in frequency, intensity, duration or real or apparent spatial locus of origin [171].The MMN can be elicited regardless of whether the subject is paying attention to the sequence [172]. Indeed, even if a person is reading or watching a silent movie during the experiment, the appearance of deviant stimuli still produces a clear MMN.

Task-irrelevant visual mismatches can also elicit a negative-going wave in the same latency range [173], but the early portion of this effect appears to reflect temporal rareness rather than mismatch detection per se [174]. Thus, the MMN appears to be a mainly auditory phenomenon.

The most widely accepted theory of the MMN proposes that it reflects the comparison of a short-lived memory trace of the standards with the current stimulus [170]. However, the MMN often overlaps with other components that are also involved in discriminative processing, especially if they are sensitive to habituation or refractoriness and that are therefore triggered by the standard/deviant contraposition. An example of such overlapping component is the N1. Indeed, its amplitude shrinks when the same stimulus is presented many times, as a result of a reduced responsiveness of the neurons tuned to the specific stimulus characteristics (e.g., pitch). Therefore, when deviant stimuli appear, two overlapping processes occur: on the one hand, the mismatch detection triggers the MMN (N2a), on the other, a new population of neurons with intact responsiveness is triggered producing a larger N1 response with respect to standard stimuli. The two components partially overlap both in the spatial and temporal domain and therefore contaminate

each other from the scalp measurement point of view.

Nevertheless, there is evidence that although possibly interleaved with other components as well involved in stimuli characterization and discrimination, at least part of the MMN reflects mismatch recognition, as it is elicited by tones occurring at an unexpectedly early time [175], as well as by the omission of a stimulus [176], and not just by changes in standard and deviant stimuli characteristics.

2.4.3 P3

The P3 wave is a late ERP component elicited along with cognitive processes of decision making. As previously anticipated, it is considered an endogenous component, as its occurrence is associated not only with the physical attributes of a stimulus but with e reaction to it. More specifically, the P3 is thought to reflect processes involved in stimulus evaluation or categorization [177]. It is usually elicited using the oddball paradigm (see Figure 2.13), in which rare target ("deviant") items are mixed with frequent non-target (or "standard") items, and consists in a positive deflection (if measured relative to a reference at the ear lobes or the mastoids) peaking in the parietocentral scalp region between 250 and 500 ms [178]. Various characteristics of the P3 peak, such as presence, magnitude, and latency are often used as metrics to describe event-related cognitive processes. Reproducibility, ubiquity, and magnitude of its peak made the P3 one of the most investigated ERP components both in clinical and laboratory tests [179], and to implement BCIs [180]. There are several distinguishable ERP components in the time range of the P3 wave [181]. The first major distinction was made [182], who distinguished between a frontally maximal P3a component and a parietally maximal P3b component. Both were elicited by unpredictable, infrequent changes in the stimuli, but the P3b component is present only when these changes are task-relevant, and this is indeed the component usually referred to as P3 [46, 182]. The P3a has a peak latency in the range between 250 and 280 ms and has been associated with attention (especially orienting attention, i.e., involuntary shifts of attention induced by changes in the environment) and novelty [183].

On the other hand, the P3b wave is strongly dependent on the task complexity and the individual subject response [178]. Generally speaking, improbable events will elicit a P3b, and the less probable the event, the larger

the P3b amplitude [184]. This was shown to be true both for the overall probability and for the local probability [185]. However, as anticipated, in order to elicit a P3b, the improbable event must be related to the task at hand in some way (for example, the improbable event could be an infrequent target picture of choice in a carousel of random uninteresting pictures). Given that amplitude and latency of the peak are affected by the processing workload, the P3b can also be used to measure how demanding a task is in terms of cognitive workload [184].

In particular, P3 amplitude is larger when subjects dedicate more effort to the task, leading to the hypothesis that P3 amplitude might be associated with resource allocation [186]. On the other hand, the amplitude shrinks when the subject is uncertain of whether a given stimulus was a target or non-target. Thus, if a task is made more difficult, this might simultaneously increase the amplitude since the subjects have to devote more effort to the task, and at the same time decrease the amplitude by making subjects less certain of the category of the stimuli.

Moreover, since the difference in amplitude of the P3 component between rare and frequent stimuli reflects some processing that cannot until the categorization of the stimuli has completed, anything that delays this stimulus categorization (e.g., increasing the time required for low-level sensory processing or higher-level stimuli categorization) will necessarily increase the onset time of the difference. As a result, if difference waves are used in this context, strong conclusions can be drawn about the effect of a given manipulation in influencing the amount of time required to categorize the stimuli.

Notably though, the P3 component does not directly arise from the categorization process itself. Rather, stimuli categorization must occur before the P3 can be elicited (or, more precisely, before the difference becomes evident deviating from zero). Consequently, the latency of the P3 can be used to assess the timing of processes that must have occurred prior to the time at which the waveforms diverge for the rare versus frequent stimuli. Another characteristic of the P3 component is that its latency is sensitive only to the time required to perceive and categorize the stimuli and not to the amount of time required to plan and execute an action once a stimulus has been categorized [187, 188].

Multiple studies have shown that an unexpected, unusual, or surprising task-irrelevant stimulus within an attended stimulus train elicits a frontal P3-like response [189, 190, 183] that is similar to the P3a component originally

described in [182]. Results in [191] have enforced this hypothesis providing evidence that this component is not related with the P3b component because the latter is observed only for targets that are expected or awaited, whereas it could be related to the frontal P3a wave since it is elicited by stimuli that are truly unexpected or surprising (novel). However, a definitive confirmation is still missing.

The main factor influencing the P3 amplitude and latency is the target probability [192, 193, 194, 195, 179, 181, 196, 187, 197]. In particular, as suggested in [181], the relevant factor is not the sequential probability of the stimulus category (i.e., the ratio between the number of stimuli in a particular category and the total number of stimuli), rather the temporal probability of the stimulus category (i.e., the ratio between the number of stimuli in a particular category and the time period). Indeed, if we take the standards out the stimulus train while preserving the timing of the targets, the P3 elicited by the targets is probably the same as it would be with the standards included, even though the sequential probability of the targets is now 100% [198, 199].

2.4.4 N400

The N400 is a negative-going wave that is usually largest over central and parietal electrode sites, with a slightly larger amplitude over the right hemisphere than the left hemisphere (see Figure 2.11). As previously mentioned, it has been associated to semantic processing [148]. In particular, it is typically seen in response to violations of semantic expectancies. For example, if a sentence is presented one word at a time on a screen, a large N400 will be elicited by the last word if it is perceived as semantically incongruent or unlikely with respect to the preceding sequence of words, possibly depending on previously established semantic context [200]. On the other hand, little N400 activity would be observed if the sentence had ended with one of the semantically correct most likely words. The same effects are observed if the words are presented in naturally delivered speech. It can also be observed in response to middle words or pairs of words if they are semantically unrelated to the preceding sequence of words, but this may rather reflect associative strength among words rather than semantic relationship per se [201]. Indeed, some N400 activity is generally elicited by any content word we read or hear, but relatively infrequent words elicit larger N400s than those elicited




Figure 2.13: Oddball paradigm representation (A) with the corresponding target (deviant) and non-target (standard) average evoked responses (B). Notably, the same outcome is measured if non-target stimuli are dropped but the temporal separation of target stimuli is preserved (C).

by relatively frequent words [200].

Some studies presented results indicating that the N400 component can also be elicited by non-linguistic stimuli such as line drawings [202] when inconsistencies with respect to the semantic context materialize. It was also found in late detection of multisensory emotional integration, in particular in the association of voice inflection to emotional facial expressions [161, 158].

Concerning its cerebral localization, the N400 appears to be generated primarily in the left temporal lobe. This view derives form studies of split-brain patients and lesion patients have [203, 204], and recordings from the cortical surface in neurosurgery patients [205].

2.4.5 Error-Related Negativity (ERN)

Several ERP studies observed a negative-going deflection at frontal and central electrode sites in the difference wave between correct and incorrect behavioral responses [206, 207, 208] (see Figure 2.14). This component, which has been named Error-Related Negativity (ERN), develops immediately after the responses and typically peaks in the range between 80 and 150 ms after the beginning of the erroneous response [209, 210]. It can be observed, for instance, in experiments involving speeded choice tasks that are so fast to occasionally induce trivial errors [207].

The ERN amplitude seems correlated with the magnitude of the error, in that fully incorrect trials are accompanied by a large ERN, whereas partial error trials are accompanied by a somewhat smaller ERN. Additionally, it seems to be sensitive to engagement and motivation. When subjects are instructed to strive for accuracy in their responses, observed amplitudes are typically larger than when subjects are instructed to be as quick as possible, and thus to be less concerned with errors [211].

Interestingly, the ERN is followed by a positive late deflection, peaking between 200 and 500 ms after the response, called error positivity (Pe), which is thought to reflect cognitive awareness of errors, in contrast with the ERN that is observed even with little or no awareness of the committed error [212, 213]. However, in the case of unconscious errors the amplitude is reduced [208, 214].

Many researchers suggested that the ERN may reflect the activity of a system that monitors responses, which is sensitive to conflicts between intended and actual responses, and that generates emotional reactions depending on the outcome [215, 216]. Evidence suggests that the ERN originates in the anterior cingulate cortex [217, 218], even though some studies have found ERN-like responses in multiple other cortical areas [219]. Thus, as it often the case with ERP components, it is likely that multiple neural sources contribute to the scalp ERN. Nevertheless, by studying the ERN, it is possible to learn something about the cause of the error and the brain processing after the detection of the error [206].




Figure 2.14: Electrical representation of the error-related negativity (ERN) and error positivity in terms of difference wave and topography. The ERN (blue) starts even slightly in advance with respect to the error time, and it exhibits the largest amplitude in the frontocentral region. Source [6]

2.5 Acoustic processing

The ability to perceive and accurately represent the acoustic environment is one of the most advanced features of the human brain. When we hear a sound, we immediately characterize it in terms of content and location in space. A peculiarity of this process is that, while the visual system maps the spatial information directly on the receptive sensory cortices (topographical maps), the tonotopic (frequency-based) organization of the auditory system does not allow it and requires to infer the spatial information through the integration of multiple auditory cues [220]. These cues derive from the interaction between the incoming sound wave and the head and the pinnae and can be categorized as binaural (based on the input differences between




Figure 2.15: Subcortical acoustic processing flow starting from the cochlea to the auditory cortex. The path includes the superior olivary nucleus, the inferior colliculus, and the medial geniculate body and consists of a parallel route with multiple integration points for the aggregation and enhancement of the monoaural and binaural cues. Source [7]

the two ears) or monoaural (spectral characteristics at each ear separately). The binaural cues, which are interaural time difference (ITD) and interaural level difference (ILD), are most informative for horizontal localization, while monoaural cues are most informative for estimating distance and elevation, as well as for disambiguating the front/rear cone of confusion [221, 222]. Nevertheless, a weighted combination of all auditory cues [223], including their temporal evolution produced by spontaneous or intentional head micro-movements [224, 225, 226, 227], is employed to encode both azimuth and elevation [228, 229, 230, 231, 232, 225], and reduce front/rear discrimination errors [233, 227, 224, 234, 235, 236].

Acoustic information propagates from the ears to the auditory cortex through subcortical pathways (shown in Figure 2.15) encompassing the auditory nerve, the superior olivary complex, the inferior colliculus and the medial geniculate body of the thalamus [237]. The encoding of the binaural cues occurs in the superior olivary complex [238, 239], whereas the monoaural cues are encoded in the dorsal cochlear nuclei [220].

Through this subcortical path, the auditory cues are refined and aggre-

gated prior to reaching the primary auditory cortex (PAC) where a complete acoustic representation starts to be shaped [18, 19]. In particular, the spatial representation is entirely inferred in the cortex from the aggregation of the low-level auditory cues, since no explicit spatial representation is available in the sensory receptors and the primary sensory cortices [238]. Spatial acoustic maps are learned and continuously adjusted from the experience of the correspondence between the auditory cues and the corresponding spatial context (sound source position and motion dynamics, head shape and orientation, sound characteristics, etc.) [221, 240, 241, 242, 243]. As one could imagine, this process takes great advantage of the integration of the visual cues provided by the visual system [244].

From the PAC, the acoustic processing splits into two functionally specialized cortical pathways in what is known as the auditory dual-pathways model [15, 16, 8, 17]: a ventral "what" pathway involved in acoustic content identification, and a dorsal "where" pathway dedicated to spatial processing [20, 8, 21, 15, 22]. This parallel hierarchical acoustic processing was initially investigated after evidence of a similar organization in the visual system [245, 246, 247], and has been confirmed by multiple studies, even though shared processing has also been evidenced in the inferior parietal cortex [8, 23], as can be seen in Figure 2.16.

In practice, the ventral stream propagates to the inferior frontal cortex (IFC) where most of the identification processing is performed, whereas the dorsal stream propagates through the posterior (secondary) auditory cortex and the planum temporale (PT), the inferior parietal lobule (IPL), the premotor cortex (PMC), and finally ends in the dorsolateral prefrontal cortex (dlPFC) [248, 249, 250, 9, 19, 10, 251, 252, 253, 254, 255, 256, 257, 258, 259] (see Figure 2.17).

The dorsal "where" pathway starts with low-level sensory processing in the PAC which propagates in the subsequent stages to build incrementally refined higher-order acoustic representations of sound source location and motion dynamics [18, 260, 256, 251, 258]. The core of this processing takes place in the IPL and the posterior parietal cortex [261, 8]. Another key region is the PT [262, 19], even though the posterior temporal region is not always activated when spatial localization is involved [8]. From this point of view, it has been hypothesized that the PT acts as a conjunction point where spatial information is disambiguated from content information [263]. Additionally, IPL and PT have been identified as focal areas for acoustic motion perception,




Figure 2.16: Areas involved in the "what" (red) and "where" (blue) acoustic processing activity resulting from a meta-analysis of 38 PET and fMRI studies. It is clearly visible the dual pathway consisting in the red ventral "what" pathway that spans from the PAC to the IFC, and the blue "where" pathway mainly involving the PT, the IPL, and the PMC. Some areas are shared between the two pathways, in particular, the posterior auditory cortex and the IPL. Adapted from [8]

both in the radial and tangential directions [264, 262, 265, 256].

Concerning the spatial processing propagation, a MEG study of passive listening to sounds from different locations has confirmed a processing sequence exhibiting peak activations in the N1 component timeframe starting in the PAC (139 ms after sound onset), then moving to the PT (156 ms), and subsequently reaching the IPL (162 ms) [10] (see Figure 2.18). Moreover, it has been shown a decreasing trend of the peak activation amplitude in the three mentioned regions along with this propagation, confirming the source of the N1 component to be in the Heschl's gyrus (where the PAC is located). This multiplicity of N1 response sources agrees with other studies showing various anterior and posterior auditory cortex sources associated with different sound features changes [266, 267, 268]. In accordance with other studies, the right hemisphere has shown a stronger involvement than the left one in sound localization, especially in passive listening conditions [269, 270, 261, 271, 11].

The key cerebral regions and the specific processing flow of the hierarchical dorsal spatial stream have been confirmed both in passive listening [10, 251, 272], and in active, goal-oriented, listening tasks [273, 274, 252, 270],




Figure 2.17: Representation of the dual-stream model, consisting of the ventral "what" pathway (green) and the dorsal "where" pathway (red). Source [9]

with an apparent additional feedback propagation from the dlPFC towards the PAC and consequently stronger involvement of the latter in the active case [19, 275, 276]. Additionally, active sound source localization engagement seems to increase the functional connection between the two auditory cortices, resulting in shared neural representations of sound location within the two hemispheres, in contrast to the separated complementary representations exhibited in the passive listening condition [273].

Concerning the temporal differences between the acoustic identification performed in the ventral pathway and the spatial processing performed in the dorsal pathway, several EEG studies based on the elicitation of ERPs showed significant differences already in the N1 component timeframe localized in the PT and the IPL (dorsal "where" stream) [277, 278, 21, 279]. The same behavior has been reported in another study that investigated feature-specific attention to either sound content or location [252]. The main finding has been a significantly earlier activation of the posterior "where" stream compared to the anterior "what" stream (30 ms), also in this case associated with the N1 timeframe. Additionally, in reference to the N1 amplitude, it has been demonstrated that feature-specific attention modulates, in a top-down fashion, the low-level selectivity of neuronal populations in the human non-primary auditory cortex tuned to the corresponding pathway (i.e., the




Figure 2.18: The top section shows the flow of source activation identified in a passive spatial listening experiment [10]. The PAC is activated first (violet region shown in panel a), then the PT (green region shown in panel b), and finally the IPL (teal region shown in panel c). The bottom section presents the results of a MEG study from an active sound localization task that highlights an activation flow similar to the top one, but exhibiting slightly earlier regional activations than reported by [10]. Both flows exhibit a bilateral activation with a stronger involvement of the right hemisphere. Adapted from [10, 11]

posterior N1 activity is enhanced by spatial attention and the anterior N1 activity is enhanced by content attention).

Chapter 3

State of the art

3.1 Sound location classification

Several studies have gone beyond the characterization of the human cortical acoustic processing and tried to decode the cerebral signals to infer the location of sound sources. Statistically significant single-trial, participant-specific, classification accuracies associated to an active localization setting have been reported in an 8-direction study employing short (400 ms) white noise stimuli played from physical loudspeakers [26] considering all possible binary comparisons between the EEG responses to the reference frontal direction and those to the remaining 7 directions individually (average accuracy over 5 subjects and 7 comparisons equal to 76.5%). The discrimination was based on spectral features computed for each channel using a discrete wavelet transform (DWT), and notably achieved a mean accuracy of 76.3% in the "front vs rear" configuration.

Similarly, another EEG study [27] involving 3 subjects and 4 directions (front, rear, left and right) reported mean aggregated, participant-specific, classification accuracies (averages of 40 trials) of 94% in the binary "left vs right" configuration, and of 72% in the full quaternary configuration. In this

case, the adopted stimuli were 3 kHz pure tones and they were played through headphones simulating the different directions by filtering the signals using general HRTFs. The discrimination was still based on spectral features but computed using a continuous wavelet transform (CWT).

Robust mean aggregated, participant-specific classification accuracies (averages of 10 trials) have been presented also in another EEG study [28] which involved 6 subjects and the same 4 main directions considered in [27]. This study consisted on a passive listening and employed extremely short (50 ms) white noise bursts played from physical loudspeakers. The discrimination was based on raw EEG time series without applying any feature extraction procedures and achieved an accuracy of 60.7% in the binary "front vs rear" configuration, 73.6% in the binary "left vs right" configuration, and 53.7% in the full quaternary configuration. Notably, lateral directions (left and right) were more easily discriminable than longitudinal directions (front and rear) and, interestingly, the successful classification appears to be predominantly based on information extracted from the N1 and P2 ERP components respectively. Moreover, different topographical patterns are reported for lateral (left and right) and longitudinal (front and rear) configurations with significantly stable within-configuration similarities (similar responses to left and right, and similar responses to front and rear). This result seems in agreement with other studies highlighting significant differences mainly between centric (longitudinal) and eccentric (lateral) directions [24, 25].

Also blood oxygen level-dependent (BOLD) features obtained from fMRI measurements have been used to discriminate the directions in the lateral and longitudinal directions. In the study [280], which involved 8 subjects performing an active localization task, participant-specific multivariate pattern analysis (MVPA) of the BOLD features, mainly computed over the superior temporal lobe, allowed to achieve 66.7% of average accuracy in the "left vs right" configuration and 57.4% in the "front vs rear" one. This study reproduced through headphones realistic spatial band-passed noise bursts previously recorded at the inner ears of each individual participant when naturally played through speakers.

Most of these studies reported a slight contralateral tuning of the two hemispheres with respect to the sound directions, and this seems in accordance with a bias toward the contralateral stimulation reported in other studies [281, 282]. Moreover, a third population of neurons, bilaterally tuned to azimuthal space around the midline, has been reported [283, 284], and

this seems reflected in the more symmetric topographies associated with the longitudinal directions.

3.2 EEG application in the automotive industry

EEG has long been seen as a suitable technology for improving some of the safety needs of the automotive industry given its predisposition to passively capture the drivers' state of mind, their perception, and their intentions, in some cases even before the execution of the associated actions. The human-vehicle interaction and the associated safety could be greatly improved by adopting portable EEG-based infrastructures able to reliably interpret the drivers' intentions or the reactions to events in real-time while driving. Indeed, multiple studies have investigated the adoption of EEG signals to make certain aspects of ADAS (Advanced Driving Assistance Systems) more driver-centric. EEG signals have been largely analyzed for drowsiness, stress, and fatigue detection [285, 286, 287, 288, 289, 290, 291, 292, 293, 294, 295, 296] and for workload and attention/alertness estimation [297, 298, 299]. Multiple studies reported fatigue detection accuracies greater than 90% [300, 301, 295]. Other studies have attempted to use EEG signals to detect emergency braking intentions [302, 303, 304, 305], mismatches between autonomous steering actuations and drivers' intentions [306], obstacle avoidance intentions [307, 308], and even classify driving style or experience [309, 310, 311, 312, 313, 314]. Additionally, analysis of EEG signals has been performed to characterize the effects of different sounds on the mental state while driving [315] for instance to relief driving fatigue [316], and to assess audio/video distraction and perception when involved in multiple tasks [317, 318, 319, 320, 299, 314]. More ambitious studies have attempted to achieve synchronous or even asynchronous control of the vehicle, including braking, acceleration, and steering intentions [321]. Promising results have been reported with live demos, in some cases achieving even anticipatory results [322].

Notably, though, most of these studies were performed in simulated driving conditions, and only a few studies have investigated the applicability of EEG in real-life scenarios such as while driving a real vehicle [285, 301, 303, 296], while cycling or walking [323, 324, 325, 326], or when piloting a real airplane [327]. This aspect is certainly due to the complexity in setting up such experiments both from an infrastructural and a safety point

of view, but also because of the low signal-to-noise ratio of the EEG signals that dramatically worsens in moving conditions. In this regard, the main issues in real-life scenarios are the voluntary and involuntary head movements necessary to monitor the environment and the external vibrations, which result in electrodes displacement and electrical signal contamination due to muscular activity [328, 329].

Chapter 4

Infrastructure

In this chapter, we tackle the design and the validation of a portable infrastructure to be used for data acquisition and real-time processing in all the experiments of this doctoral work and in future in-vehicle applications. In Section 4.1 we introduce the background behind the need of a custom infrastructure for this thesis purposes and in Section 4.2 we present the proposed solution. Then, we describe the experiment we conducted to validate both hardware and software components of the infrastructure (Section 4.3) and the corresponding results (Section 4.4). Finally, we highlight the limitations (Section 4.5) and draw the conclusions (Section 4.6). The material presented in this chapter refers to [330] presented at the IEEE International Conference on Systems, Man and Cybernetics (SMC) in 2019, and [331], published in the special issue Advances in Design and Integration of Wearable Sensors for Ergonomics of the Sensors journal in 2021.

Research objective 1: *Implement a portable infrastructure allowing acquisition, investigation and joint real-time processing of multiple biosignals (EEG above all), vehicle telemetry, and contextual information, suitable for*

complex real-world in-vehicle automotive applications.

4.1 Introduction

The recent technological advances in mobile biosensing systems concerning comfort, portability and reliability are favoring the adoption of the technology in real-life scenarios aiming to objectively characterize human feelings, perception and emotions conditioned by the environmental context. The psychophysiological sources of information that are commonly investigated are Electroencephalography (EEG), Electromyography (EMG), Electrocardiography (ECG), and Galvanic Skin Response (GSR) and they are usually measured and jointly analyzed along with some sort of representation of the environment to contextualize the measurements. These signals are the most objective source of information about human feelings that we can access in a non-invasive way but, being them simple electrical measurements, are highly subject to electromechanical noise.

Nevertheless, several studies have achieved promising results employing them outside the laboratory while involved in real-life tasks despite the degradation of available information due to the poorer signal quality.

Concerning the specific usage of brain signals for subjective perception and intention identification purposes, a mobile EEG cap with dry electrodes has been successfully used to detect hazardous piloting maneuvers in real flight conditions [332], an active wet EEG system has been employed to characterize AEPs while outdoor cycling [323], while other studies have adopted the EEG technology in real-world driving conditions to detect, for instance, emergency breaking intentions [303] or mismatches between autonomous steering actuation and driver's intention [306]. One issue of these and many other studies of this kind is the employment of bulky, project-specific, infrastructures.

Considering these automotive applications of BCIs it is clear how the human-vehicle interaction could be greatly enhanced employing portable infrastructures able to reliably interpret the drivers' intentions or reactions while driving, and this not only from the acoustical point of view. Accordingly, there is an increasing number of car manufacturers working on more context-aware driving assistants to be integrated in their ADAS (Advanced Driving Assistance System), for instance for drowsiness detection or lane-change assistance [333, 334, 335]. However, one issues of existing studies

is the employment of bulky, project-specific, infrastructures. In the specific case of this doctoral thesis, we aim to assess the real-world applicability of a methodology allowing to objectively decode single-trial neurophysiological temporal dynamics associated with aspects of spatial sound perception such as sound direction and sound motion speed.




Figure 4.1: Artifact removal: statistical reconstruction of noisy time intervals based on prior knowledge about channels correlation in clean conditions. In red the original noisy signals (two eye blinks highlighted in pink), in blue the resulting clean signals. As a preliminary step, entire channels identified as noisy due to their excessively large and irregular variance (see green box) are discarded and reconstructed interpolating the clean neighboring channels.

The main issue of real-world adoption of the mentioned biosignals, and EEG above all, is the poor signal-to-noise ratio (SNR), especially when measured in uncontrolled scenarios such as while driving a real vehicle (see Figure 4.1 for a representation of the issue and an approach to tackle it). An additional problem is related to the intrinsic complexity (non-stationarity and low interpretability) of the measured brain signals, especially when analyzed in a single-trial fashion (see Figure 4.2 to appreciate the difficulty in visually classifying even just one channel of a single-trial ERP response as either target or non-target).

The first step is to build a robust and portable infrastructure allowing to easily measure and process these signals in real-time, fully synchronized with vehicle telemetry and contextual information, while guaranteeing the lowest possible level of noise even in challenging conditions. A fundamental need for such infrastructure is, therefore, the ability to be used also in the vehicle




Figure 4.2: Characteristic shape of Event-Related Potential (ERP). It is the average response measured in terms of electrical activity (EEG) in specific areas of the brain when an infrequent attended event (target) takes place, being it visual, auditory, or tactile. ERPs are characterised by known peaks, such as the P1, N2 and P3, that are named after deflection orientation (either Negative or Positive) and latency with respect to the onset of the event. The average shape of target and non-target responses is generally different and this allows, provided a sufficiently large number of repetitions, to discriminate between attended and unattended events. The bottom two plots show the great variability of the single-trial responses in the two conditions and the respective mean value (which are plotted together in the top plot for an easier comparison).

while driving, both for data acquisition and testing. Moreover, despite being portable, it must allow the offline training of the machine learning models and must have real-time inference capabilities both for inference and continuous learning.

Despite being portable, it must allow the offline training of the machine learning models and allow real-time processing for classification and actuation. Moreover, to allow the continuous refinement of the trained models to limit the non-stationarity nature of EEG signals it must allow the deployment of continuous learning solutions.

From the software point of view, the infrastructure must integrate a pool of preprocessing pipelines for data cleaning and signal correction (an example is shown in Figure 4.1), features extraction routines and scripts to easily train different classification models both on raw EEG signals and on aggregated features. Additionally, it must provide standardized methods to quickly run statistical investigations and visualizations of the physiological signals. This because even simple parameters such as filter type and cutoff frequencies, or whether to apply signal re-referencing and what kind of technique to use, play a huge role in the classification results.

The proposed infrastructure was validated implementing a BCI to control the infotainment menu of a car which was based on the presentation of the menu icons (6 in the considered implementation) one after another following an oddball-like paradigm, relying on the discrimination of the ERPs elicited by the appearance of the desired (target) menu item from those associated with the other (non-target) icons to identify the action to activate (see Figure 4.2 for a representation of target and non-target ERP responses). The system was trained and evaluated collecting data from 10 participants both in laboratory and real driving conditions, and then its general model performance was re-evaluated on 5 totally new participants.

The research questions associated with this validation activity are the following:

1. *Is the signal quality provided by the infrastructure in real driving conditions statistically different from that obtained in standard static laboratory conditions, or the signal quality remains comparable?*

2. *Can we extract meaningful subjective information from the EEG signals collected while driving? Can we build a BCI that leverages this*

information to provide feedback to the user based on the decoded information?

3. *Are we able to go beyond single-participant models and train a single comparably performing general model?*

4.2 Proposed solution

To address the described needs, this study proposes a custom embedded infrastructure that can be used both for multi-stream acquisition and real-time processing of a wide range of biosignals fully synchronized with contextual information and vehicle telemetry (see Figure 4.3). It is built around three main components: one or more OpenBCI for biosignal acquisition, one or more battery-powered NVIDIA Jetson TX2[1] modules (NVIDIA, Santa Clara, CA, USA) for instantiating the local network, data processing and storage, and the Lab Streaming Layer [2]) (LSL) framework for the wireless synchronization.

The LSL framework together with custom middleware software guarantee a high modularity, allowing to support a variable number of processing nodes, input sources, and devices. The streams can be heterogeneous in data format (number of channels, data type and sampling rate) since the inter-module synchronization and the data reorganization is handled by LSL itself. The master node, in our case the Jetson TX2, runs a custom version of the LabRecorder [3] software that, while recording the raw data streams coming from different modules and devices, exchanges out-of-band NTP-like clock synchronization information with each involved stream source to estimate the relative clock offsets. This information can be used either online or in postprocessing to remap all data streams onto a common time axis (that of the master machine). The running correction factor of each stream is computed by fitting a linear model on the history of estimated clock offsets.

To measure the EEG signals, the proposed infrastructure integrates a custom multi-purpose, lightweight prototype EEG helmet composed of a net of adjustable elastic bands to hold the dry Neuroelectrics[4] EEG electrodes,

[1] `www.nvidia.com`
[2] `https://github.com/sccn/labstreaminglayer`
[3] `https://github.com/labstreaminglayer/App-LabRecorder`
[4] `https://www.neuroelectrics.com/`




Figure 4.3: Schema of the proposed embedded infrastructure. It allows to acquire and process in real-time a fully synchronized flexible combination of psychophysiological signals (EEG, EMG, EKG, GSR, etc.), contextual information and vehicle telemetry (CAN, GPS, CAMERAS, etc.). Additionally, it optionally allows to provide visual, acoustic or tactile feedback to the users and to record their interaction with auxiliary devices such as smartphones and buttons. One of the key components is the EEG helmet prototype which is based on an OpenBCI that, thanks to a physical decoupling between sensors and electronics, ensures the smallest possible sensors motion and thus the smallest possible electromechanical noise.

one OpenBCI[5] Cyton Board with OpenBCI Wifi Shield for measurement and data transmission and a set of headphones to hold electronics and battery. This solution allows to provide ergonomic head fit and adequate pressure to ensure good contact with the skin, while being comfortable to wear for long stretches of time. Its main strengths are the flexibility, in the sense that it allows multiple channel configurations based on the task under investigation, and the high signal quality (reduced motion artifacts) due to the smallest possible amount of moving parts obtained mechanically decoupling the EEG electrodes from the electronics. The adopted OpenBCI WiFi configuration allows to stream up to 16 ExG channels at 500Hz and the inertial measurements of the internal IMU.

For more rigorous and less exploratory investigations it is guaranteed also the compatibility with wireless commercial medical-grade EEG headsets such as Enobio 20 (Neuroelectrics, Barcelona, Spain) and g.Nautilus (g.tec medical engineering [6], Shiedlberg, Austria). In this case additional non-linux PCs running proprietary software are required to acquire the signals and relay them onto an LSL stream. The schematic representation of the setup is shown on the Figure 4.4.

The proposed solution allows to simultaneously and synchronously record a set of biopotentials such as EMG, ECG, and EEG, behavioral signals through eye-tracking devices, and other signals that can be extracted from a custom Android application running on a modern smartphone (e.g., GPS, inertial data and video stream). The mentioned application allows to also interface via Bluetooth with up to 5 external MetaMotion-R [7] wireless IMUs (Mbientlab, San Francisco, CA, USA) to record inertial signals from body or vehicle parts, and the interaction with multiple push buttons, useful to allow user control. Additionally, it allows to collect telemetry data via CAN bus and video recordings from vehicle cameras. Another fundamental feature of the infrastructure is that it can be used as a programmable interface for stimuli presentation, with the additional possibility to control online the stimuli delivery based on the contextual signals. Given these characteristics and the computational power of the Jetson TX2 embedded system (including the on-board GPU), it is suitable for running online end-to-end data analyses, which are paramount to investigate human perception in ecological real-life

[5] `https://openbci.com/`
[6] `https://www.gtec.at/`
[7] `https://mbientlab.com/`

scenarios (e.g., driving).

Indeed, as will be shown in the following sections (Figure 4.7 in particular), the signals recorded in the validation experiments have shown no statistically significant difference and comparable classification performances between laboratory and driving conditions, confirming the reliability of the infrastructure.

4.3 Experimental validation

The proposed bio-sensing infrastructure was empirically validated implementing a Brain-Computer Interface (BCI) to control the infotainment menu of the car. It exploited the visually evoked Event-Related Potential (ERP) [9] induced with an oddball paradigm in which the 6 icons of the menu were randomly presented one after another (3 repetitions per icon). In particular, it leveraged the difference, on average, between the ERPs evoked by the appearance of the desired icon (target) and those evoked by the appearance of undesired icons (non-target). This difference can be appreciated in the top panel of Figure 4.7. The experiment was performed both in standard laboratory conditions and while driving on a closed private track, with the main goal of evaluating the effective signal quality obtained using the infrastructure in the more demanding driving conditions. Regarding the actual control of the menu while driving, the single-trial recognition of the target icon was performed by a simple Convolutional Neural Network (CNN) architecture called Deep4Net [10] that was trained to discriminate between brain responses to target icons and brain responses to icons that were not intended as target for each of the 10 recruited individuals separately. This task was performed to assess the ability to extract meaningful subjective information from the EEG signals collected while driving. Furthermore, to assess the informativeness of the data collected in the different configurations, three training dataset compositions were evaluated: using only laboratory data, using a mix of laboratory data and car data, and using only car data. Finally, to investigate the fundamental generalization capability of the proposed CNN architecture, we trained a single general model on the data of all participants together (hybrid configuration) and tested it both offline on test trials of the same participants and online with 5 totally new participants.

4.3.1 Experiment description

Ten volunteers (9 male and 1 female, age 37.8 ± 7.42) participated in the validation experiment, taking part to both the laboratory and the driving sessions. None of the involved participants were professional drivers, but all had valid driving licenses and driving experience. All participants had normal or corrected-to-normal vision, did not report any known neurological or psychiatric diseases at the time of the experiments and provided written informed consent for participation.

All parts of the BCI were implemented using the described infrastructure. In particular, stimulus delivery, data acquisition, model training, and online prediction computation and feedback delivery were performed by the small, battery powered, embedded system. A schematic representation of the setup is shown in Figure 4.4.




Figure 4.4: Schema of the recording system employed in the experimental setup.

Considering the specific application based on visually evoked ERPs, we decided to reduce the montage of the prototype EEG helmet to 3 channels only (Cz, Pz, and Fp1). The reason behind this choice was twofold: 1) it is well established that VEP, and in particular the P3 component, peak in centro-parietal regions (covered by Cz and Pz) [336]; 2) given the in-vehicle usage while driving, we wanted the helmet to be as comfortable as possible and as easy to put on as possible (also to guarantee the highest possible signal quality), therefore we reduced the number of channels to the minimum. The Fp1 channel was included to detect eye-related artifact (e.g., blinks) rejection/removal purposes, being it one of the closest channels to the eyes. The designed prototype, and in particular the chosen configuration, proved to be effective in providing an ergonomic head fit and adequate pressure, ensuring a good connection with the skin while being also comfortable to wear for long periods of time.

The OpenBCI collected the raw EEG signals from the EEG electrodes and transmitted them at a sampling frequency of 500 Hz via WiFi to the Jetson TX2, which relayed them onto LSL. Based on the sample number provided by the OpenBCI along with the EEG signals, and a pinging procedure, we additionally included two easily accessible streams to monitor the number of lost packets and possible temporary connection losses. For each session, all streams were saved onto the Jetson TX2 in a single XDF file by the custom LabRecorder software.

During both laboratory and driving sessions, visual stimuli were presented on a 5-inch LCD touch screen with 800 x 480 resolution (later referred to as "small screen"), connected to the Jetson TX2 via HDMI cable (see Figure 4.4 and 4.5). The script for presenting the stimuli was written using the Python library PsychoPy, which can generate precise and reliable visual stimuli with negligible delays [337]. In a separate set of experiments we tested the system's synchronization, comparing the stimulus delivery timing (streamed as LSL markers) with the actual appearance of the stimuli on the screen detected by a photoresistor [337] connected to one of the streamed EEG channels (thus acting as a feedback). The resulted delay was 30 ms with a very narrow distribution (jitter of 2.7 ms) that remained consistent between the recordings.

4.3.2 Experimental settings in the laboratory

The first set of experiments was performed in a standard laboratory environment. Participants were seated 1 m in front of a 24-inch computer monitor with 1920 x 1080 resolution and completed a visual oddball-like task similar to [338] and [339], mentally focusing on one randomly-chosen icon (target) from a set of 6 icons, that were appearing one by one in a random order for 700 ms with an inter-stimulus interval of 100 ms. Icons represented possible menu items in a car infotainment menu and were shown on a small screen positioned in front of the monitor, on the periphery of the participant's visual field (to simulate a vehicle's screen or head-up display). Meanwhile, the computer monitor showed a driving video recorded from a first-person perspective (to simulate driving condition) as shown in panel A of Figure 4.5. The participants were requested not to look at the small screen and the icons directly, but focus on them with their peripheral vision, keeping the eyes in the central part of the computer monitor. Moreover, they were asked

to refrain from moving their head and body, and to avoid excessive blinking and strong eye movements.

The schematic representation of the laboratory session layout is shown in panel A of Figure 4.5. Each experimental session consisted of 6 runs of the visual oddball task, with 30 s breaks between subsequent runs. In each run, the icons were flashed 60 times: each of the 6 icons was presented 10 times in block-randomized order, so within every 6 presentations each icon appeared 1 time. This to allow us to later compute the optimal number of repetitions to use in real driving conditions, based on the tradeoff between performance and time needed to get the feedback. All icons had the same size (600 x 600 pixel) but different shape and color to facilitate the discrimination [340]. Colors were randomly selected among 6 options - black, green, yellow, magenta, red, blue - at the beginning of every session and were kept constant for all the runs in the session.

All ten participants completed 6 in-lab sessions subdivided in 2 days (with the interval of 4.25 $\pm$ 2.33 days). Participants s001 and s005 completed one additional day of in-lab recordings (3 sessions) because of technical issues in one of the first recording days.

Based on the collected data, an individualized classification model was built for each participant to detect, on a single-trial basis, if a particular trial was target or non-target. For the details on the classification model see the corresponding section below.

4.3.3 Experimental settings on the proving ground

The real car experiments were performed by the same participants while driving a hybrid Toyota Prius in controlled conditions on Toyota's closed private proving ground (1.2 Km flat oval track). During the experiments, the drivers kept the speed between 45 and 55 Km/h and activated the system (initiated the runs) autonomously when ready, by pressing the button of one wireless MetaMotion-R IMU placed onto the steering wheel.

The stimuli of the carousel were presented on the same small screen used for the laboratory experiments, placed near the car screen in front of the driver just on the right of the steering wheel, as in panel B of Figure 4.5. The driving experiments consisted of 3 driving sessions for each participant, and each session was completed on a separate day with an average inter-session interval of 3.5 $\pm$ 5.86 days. The driving session layout was modified




Figure 4.5: Experimental session design. A, laboratory protocol: one session comprised 6 runs (each having 60 trials; each icon repeating 10 times) of visual oddball task, with 30 s rest periods in between. B, driving protocol: one session included around 50 runs (each having 18 trials; each icon repeating 3 times) that were self-initiated by the participant. In both conditions the colors for the items were randomly chosen in the beginning of the session and remained constant within the session; items in a run were block-randomized on each repetition of a 6-item block.

in comparison with the laboratory one to avoid long periods of heavy mental load and to allow the user to self-initiate every trial when ready and not distracted, as it normally happens when manually interacting with the infotainment of the car. The outline of the driving session layout is shown in panel B of Figure 4.5. Each driving session lasted approximately 1 hour, including preparation time. During the session, participants were free to self-initiate each run when ready. At this preliminary stage of the study we used a button to activate the system, instead of another advanced hand-free means, because it was out of the research scope. Additionally, runs were shortened compared to the laboratory settings and comprised 18 trials (3 presentations for each icon, block-randomized as in laboratory sessions). EEG signals belonging to one run were buffered and then classified by the participant's individualized model that was previously trained on all their previously recorded laboratory data. The output of this model was used to provide the driver with an online feedback before enabling the initiation of

the subsequent run. This feedback step of the protocol was not mandatory, but we decided to include it to increase engagement and attention of the participants during the session, but also to give them an online, usually exciting, feeling of the system performance.

4.3.4 Data acquisition and analysis

As mentioned in the introduction of this section, with ease-of-use and portability in mind, EEG signals were recorded from 3 electrode locations (Cz, Pz, Fp1, according to the 10-20 system) referenced to the left earlobe. The choice for the electrode positions was made in accordance with the centro-parietal distribution of the P3 ERP component to rare target stimuli [336], which was expected as a major outcome of the oddball experiments; channel Fp1 was used for ocular artifacts detection. The raw EEG signals were acquired by the OpenBCI with a sampling rate of 500 Hz and saved as LSL streams along with the experimental event markers. EEG signals were then band-pass filtered between 0.1 and 30 Hz to increase reliability and signal to noise ratio while preserving the relevant physiological information [341, 342]. EEG data for each trial were extracted using Python MNE[8] library in the time window between -0.1 s and 0.7 with respect to the onset of experimental events for all recorded channels, using the first 0.1 s (from -0.1 s to stimulus onset set to 0,0 s) for baseline correction.

Rejection of bad trials was automatically performed in two subsequent steps. Due to rare imperfections in wireless data transmission, inevitable minor data losses occurred in some trials, which were removed from the analysis if more than 20 consecutive samples were lost (step 1). Then, a threshold-based artifact rejection algorithm was implemented to remove from the subsequent analysis those trials having signals exceeding a $\pm 100\mu$V threshold in any of the three analyzed channels (step 2). The rejection rates were calculated as percentage of all rejected trials with respect to the total number of trials for each participant, and then averaged across all participants. After preprocessing, the no more useful Fp1 channels was dropped and the extracted trials were used to train the different classification models, to evaluate their performance, and to run a physiological analysis of the ERPs to target and non-target stimuli. For the latter, we analyzed the extracted EEG signals in the time window between 250 to 530 ms after the stimulus

[8] `https://mne.tools/dev/index.html`

onset for each trial and calculated peak ERP amplitude (maximum in the window), peak-to-peak amplitude (the difference between the minimum and the maximum) and ERP peak latency (in ms from stimulus onset) for each trial of channels Cz and Pz. The window was manually chosen in order to include the P3 ERP component that appears in response to the target stimuli in the oddball paradigm, with a peak latency which is known to vary depending on the adopted experimental protocol [338, 339]. Signals from the two channels were averaged with the median operator for to obtain grand averages representative of all recruited participants. The differences between target and non-target responses, and between target responses in different the different experimental configurations (laboratory and driving) were assessed using a pairwise comparison with Welch's t-test for unequal variances with a Bonferroni correction for multiple comparisons. The average number of trials per participant that were analyzed is 1930 ± 448 for laboratory sessions, and 2385 ± 153 for driving sessions, with a 1:5 target/non-target ratio. To estimate the amount of noise on single trials, we calculated root mean square (RMS) scores, randomly selecting 200 trials for each participant from laboratory and driving sessions, performing 1000 permutations. RMS scores were averaged first for channels, than for subjects, and finally the grand averages between participants were computed for each condition [342]. Power spectral density (PSD) was calculated for all EEG trial segments in the 0.1-30 Hz window for the two channels separately and for each individual participant using Welch method (computed using the Python scipy package considering 256-sample segments, 200-sample overlap and 1024 points for the Fast Fourier Transform); the results were then averaged among participants with the median operator to compute the grand averages for laboratory and driving conditions.

4.3.5 Classification models

To build the individualized classification models we took inspiration from the convolutional architectures presented in [343], which demonstrated to be effective in a Motor Imagery (MI) classification task outperforming the golden standard FBCSP (Filter Bank Common Spatial Pattern) approach. Being a flexible architectures performing classical time/space convolutions, we hypothesized that these CNNs would work also for ERP-related task. We trained both the original deep (Deep4Net) and shallow (ShallowNet)

networks adopting the default parameters presented in the paper and implemented in the original Braindecode[9] library. For fitting and evaluating the CNNs, we used EEG segments in the whole 0.0-0.7 s interval with respect of stimulus onset. To compare the performances obtained with the CNN approaches with a more classical feature-based classification approach, we trained a Random Forest classifier with a combination of features extracted with the Windowed Means (WM) paradigm described in [344] and the 17 morphological features listed in [345]. In particular, for each channel separately we extracted 5 windows in the time interval between 0.2 s and 0.7 s and computed the morphological features, obtaining 44 features in total. Based on the cross-validation results, the depth and number of trees for the Random Forest were set to 12 and 1000 respectively. Figure 4.6 shows the ranked importance of the first features provided by the classifier demonstrating that P3-related features like positive peak latency, peak-to-peak time window and windowed means after the P3 peak (Windowed Mean 3 and Windowed Mean 4) were the most relevant for the classification. For all the evaluated approaches, to account for the imbalance in the dataset (1:5 ratio of target and non-target trials), we forced a class re-weighting in the fitting phase by applying a five-fold increase to the weight of the target trials. To be consistent with the target driving sessions characteristics, the prediction of the correct icon was always computed by grouping 18 consecutive trials (3 repetitions of each presented stimulus) based on the icon type, averaging the predicted single-trial probabilities of each icon group separately and provid-

[9] `https://braindecode.org/`




Figure 4.6: Ranking of the most important subset of features provided by the random forest classifier, averaged across training sets and subjects. Considering that the window of interest spans between 0.2 s and 0.7 s, and that it is subdivided in 5 subwindows, each WM feature corresponds to the average over 100 ms. In particular, the features WM3 & WM4 correspond to the late subwindows between 0.5 s and 0.6 s, and 0.6 s and 0.7 s respectively.

ing the highest as output. To find the optimal participant-specific number of training epochs for each individual deep learning model, we implemented a 5-fold stratified cross-validation procedure using the averaged balanced classification accuracy obtained on the different validation sets as metric.

Once we identified the optimal hyperparameters (number of training epochs for deep learning approaches, and number of windowed means, depth and number of trees for the classical feature-based approach), we re-trained on the whole combination of training and validation set and evaluated the performance of the models on the held-out test set. Since we were mostly interested in applying and evaluating the models in a real-life driving conditions, we saved each participant's last driving session as a test set (average number of trials for each participant was 881 $\pm$ 58).

To evaluate the differences between the data from the laboratory and driving sessions, and determining how these different recording modes could affect the final classification scores, we repeated the training procedure with three different dataset compositions. The first one consisted of all and only the laboratory trials for each participant (1930 $\pm$ 448 trials), the second one included only the first two driving sessions (1581 $\pm$ 143 trials), and the last one was the combination of the former two (3512 $\pm$ 457 trials). To account for the imbalance of trials of the hybrid training set with respect to the other two, we performed the training of each different machine learning approach 5 times sub-sampling from the hybrid set only half of the shuffled trials in a stratified manner (thus preserving the proportions of the classes). This resulted in 1756 $\pm$ 228 trials that were actually used for individual training, and subsequent testing on the usual held out test set. The results of the hybrid set that are presented in the following sections correspond to the average of the 5 individual performances.

Prior to training the models, we examined the ERP responses to target and non-target stimuli for each participant and each training dataset configuration. For each participant, average peak ERP amplitudes and peak-to-peak amplitudes of target responses, independently calculated for all three training dataset configurations, were significantly different from the non-target ones (Welch's t-test, $p < 0.05$). We also compared the peak responses of the different training sets, averaging the values for all participants to compute the grand averages. The resulting values were equal to 8.7 $\pm$ 4.2 μV, 9.8 $\pm$ 5.6 μV and 8.6 $\pm$ 4.1 μV for laboratory, driving and hybrid sets, respectively, with no statistically significant difference between pairs of groups (Welch's

t-test, p = 0.6, 0.58 and 0.96).

4.4 Results

4.4.1 Signal quality: laboratory and driving settings

To investigate the effect of the stressing driving conditions on the quality of the EEG recordings, we compared the data collected in this condition with the data acquired in the laboratory sessions, evaluating several parameters that reflect the noise level of EEG signals. In particular, we focused on trial rejection rates, ERP RMS and ERP PSD [342]. The two-steps trial rejection process described in Section 4.3.4 eliminated on average less than 10 % of the trials from the analysis for each participant, with no significant difference between the grand average rejection rates in the two conditions (Table 4.1); 10.5±4.94 % in laboratory and 8.7±5.24 % driving conditions; p = 0.39, Welch's t-test). Both in laboratory and driving conditions the artifact rejections (Step 2) originated mostly from high-amplitude activity in channel Fp1 and therefore were most probably due to the eye-related movements. Indeed, removing channel Fp1 from the rejection analyses significantly decreased the percentage of total eliminated trials (Table 4.1; p = 0.0001, Welch's t-test).

Table 4.1: Trials rejection rates

LAB: Trials rejection rates; median±std, %			
	Step 1: Due to data loss	Step 2: Due to artifacts	Total
Cz, Pz, Fp1	4.2±3.8	6.05±4.8	10.5±4.94
Cz, Pz	4.2±3.8	0.6±1.9	6.62±5.1
CAR: Trials rejection rates; median±std, %			
	Step 1: Due to data loss	Step 2: Due to artifacts	Total
Cz, Pz, Fp1	0.81±0.39	7.8±5.32	8.7±5.24
Cz, Pz	0.81±0.39	1.18±1.47	2.09±1.38

To estimate the level of noise in individual trials we calculated average RMS scores for each trial (band-pass filtered from 0.1 to 30 Hz): first, for the baseline period (0.1 s prior to stimulus onset) and second, for the whole EEG segment of interest (0.0 - 0.7 s with respect to stimulus onset). For each participant, RMS scores were computed on the two channels separately




Figure 4.7: EEG signals collected in laboratory and driving conditions. A, Grand average RMS values (channels Cz and Pz combined) of baseline and whole ERP trial for the two conditions; individual subjects' data are shown as black dots within the box plots. B, Grand average PSD values of channel Pz. Shaded areas show standard deviation across participants, gray area indicates statistical significant differences between the two conditions conditions ($p < 0.05$). C, Median grand averaged EEG responses for target and non-target trials; shaded area represents the standard error.

and then averaged. The results presented in panel A of Figure 4.7 show comparable RMS values for laboratory and driving conditions both for baseline and ERP segments. No statistically significant differences were found in the baseline values, while the RMS scores of the ERP segments collected in driving conditions were statistically higher than the laboratory counterparts ($p = 0.01$, Welch's t-test for unequal variances), indicating higher variability of the responses, which could either reflect the increased mental load of real-driving scenario or a higher noise.

Grand average PSD values were computed in the usual 0.1-30 Hz range for laboratory and driving conditions. The spectra showed statistically significant differences between the two recording conditions in the 3-6.3 Hz frequency band for both channels Pz and Cz ($p < 0.05$, t-test with Bonferroni correction in the 0-20 Hz window) with no difference between channels ($p > 0.05$, t-test with Bonferroni correction; panel B of Figure 4.7 shows the values of channel Pz). Notably, PSD spectra for the laboratory recordings had a noticeable peak in the alpha band, suggesting a possibly more relaxing condition. The comparison between the grand average responses to target and non-target stimuli in laboratory and driving scenarios shows

almost identical P3 ERP amplitudes and shapes for the two conditions, with clear P3 ERP component appearing around 0.4-0.5 s after stimulus onset in both channel Pz and Cz (panel C of Figure 4.7, illustration of channel Pz). For both conditions and both channels, target responses were statistically different from the non-target ones in the 0.4-0.5 s window ($p < 0.05$, t-test with Bonferroni correction), wit no difference between target responses in different conditions.

Based on the GPS trace that we recorded together with the EEG signals, we investigated the rejection rates conditioned on the characteristics of the different sections of the proving ground to which the rejections belonged. We did so to understand whether there was a correlation between section complexity and number of rejections. The rejection rates of the different sections are shown in the top panel of Figure 4.8. Even though it suggests that the greatest rejection rates were experienced in the corners and the regions immediately before them (straightaways: $8.4\% \pm 5.7\%$, corners: $10.8\% \pm 6.9\%$, $p > 0.05$), we did not find any statistically significant differences. The greater rejection rates experienced in the corners and the regions immediately before them are likely due to the presence of merging lanes requiring the drivers to turn their heads checking for the presence of other cars. Nonetheless, the peak rejection rates remained below 20 % (17 % to be precise), which is a satisfactory result.

4.4.2 Classification results

Models comparison Table 4.2 shows the single-participant classification accuracies achieved by the different models trained on the three training sets configurations (laboratory, hybrid, and driving) and evaluated on the last driving session of the corresponding participant, held out as test set. All performances are above chance level, which is equal to 16 % for the 6-class task. Regarding the performance of different classification models, 4 groups one-way ANOVA with a Turkey post hog test showed statistically significant difference only between Deep4Net and ShallowNet ($p < 0.05$). Considering the mean performance, Deep4Net provides the best scores (54 % mean classification accuracy), followed by the Random Forest classifier (43 %), and the worst which is ShallowNet (34 %). The results, although already in the Deep4Net favor, fail to highlight a key advantage of the deep learning approach, which is its flexibility compared to a classical feature-based




Figure 4.8: Trial rejection rates in the different sections of the proving ground. The sections are color-coded based on the magnitude of the corresponding rejection rates. The arrow on the top-left corner indicates the driving direction, and the dashed markers highlight the lane-merging sections. The bottom aerial picture shows the real proportions of the proving ground.

algorithms. While the classical feature-based approach requires a carefully constructed pull of relevant features, based on extensive prior knowledge of the analyzed data, the Deep4Net architecture alone proved to achieve state-of-the-art performance in different tasks, such as the ERP task, described in

the present study, and the MI task described in the original work [343]. On the other hand, the classical feature-based approach is less computationally demanding and, in this particular task, shows only slightly inferior performances compared to the best deep network.

Impact of training configurations Multiple BCI settings and training configurations were evaluated trying to optimize the BCI accuracy in classifying the ERP responses as target or non-target. Firstly, three different training dataset configurations were investigated: only laboratory data, only driving data, and a hybrid obtained combining the former two. There were no statistically significant differences among the classification accuracies achieved with the three different training configurations (one-way ANOVA p-values for all models were > 0.05), although the hybrid version tended to perform slightly better than the other two. Secondly, the impact of number of repetitions and EEG electrodes configuration on classification performance was investigated. Figure 4.9 shows all the evaluated combinations and the corresponding average classification accuracy among the 10 participants. As expected, we observed a better performance when increasing the number of repetitions and adopting more channels (54% of accuracy in the best configuration against 16% of the six-class random-chance level). Overall, the combination of 3 channels and 3 repetitions proved to be a viable trade-off between comfort, system response time, and performance.




Figure 4.9: Average participant-specific classification accuracy varying EEG channels configuration and the number of repetitions of the menu icons.

Table 4.2: Performance rates achieved by the different classification models varying the training configuration

Lab											
	s001	s002	s003	s004	s005	s006	s007	s008	s009	s010	Average
Random Forest	49%	31%	33%	37%	49%	51%	58%	37%	55%	60%	46%
Shallow Net	36%	25%	**43%**	18%	25%	43%	42%	24%	35%	58%	35%
Deep Net	53%	41%	37%	33%	45%	61%	**71%**	39%	**59%**	68%	51%

Hybrid											
	s001	s002	s003	s004	s005	s006	s007	s008	s009	s010	Average
Random Forest	59%	38%	33%	35%	45%	66%	55%	37%	52%	59%	48%
Shallow Net	45%	31%	**43%**	20%	27%	43%	44%	25%	33%	40%	35%
Deep Net	55%	45%	35%	37%	**53%**	69%	69%	45%	**59%**	**70%**	**54%**

Car											
	s001	s002	s003	s004	s005	s006	s007	s008	s009	s010	Average
Random Forest	60%	41%	31%	**41%**	35%	69%	56%	43%	47%	60%	48%
Shallow Net	45%	27%	31%	18%	24%	51%	42%	25%	35%	30%	33%
Deep Net	**62%**	**51%**	35%	33%	37%	**75%**	65%	**49%**	51%	**70%**	53%

Figure 4.10 shows the performance of the best performing model (Deep4Net). The fact that the individualized models trained on exclusively laboratory (in-lab) data did not, on average, show a noticeable decrease in performance compared to the other two training scenarios is promising: it suggests that for the proposed BCI, the initial classification model could be built and pre-trained in a controlled laboratory environment, without a need for collecting training data in real driving conditions, which are more dangerous and less controllable.

Information transfer rate We evaluated the system also in terms of Information Transfer Rate (ITR), which is a common metric to quantify the communication performance of a BCI [346, 347, 348]. It is based on Shannon's theory and incorporates both speed and accuracy according to the underlying concept of Bitrate (B), computed as

$$B = \log_2 N + P \log_2 P + (1 - P) \log_2 \frac{1 - P}{N - 1} \tag{4.1}$$

with N representing the number of possible selections (in our case N=6




Figure 4.10: Subject-specific performance achieved on the test session by the Deep4Net architecture varying the training dataset configuration. In-lab and in-car models are trained only on trials recorded in laboratory and in driving sessions respectively, whereas hybrid models are trained on the combination of the former two.

as the selectable menu items are 6), and P being the probability of correct classification. The ITR (bits/min) is then computed as

$$ITR = \frac{B}{T} \tag{4.2}$$

with T representing the average time required to select a single item. We evaluated the performance of the system varying the number of repetitions (as shown in Figure 4.11) which affected both classification performance (P) and selection time (T). Considering that each icon was shown for 0.7 s and that we adopted a fixed 0.1 s inter-stimulus interval, the stimulation time of a complete sequence of 6 icons (one repetition) lasted 4.8 s (0.8 * 6). The resulting ITR for the three configurations is the following: 2.17 for the 3-repetition case (accuracy equal to 54%), 2.23 for the 2-repetition case (accuracy equal to 47%), and 1.6 for the 1-repetition case (accuracy equal to

34%). Surprisingly, the 2-repetition configuration showed the best result in optimizing the tradeoff between accuracy and selection time.

Generalization In addition to the individualized models, we trained a single general model of the same Deep4Net architecture by combining the data of the 10 participants. The performance on the separate last driving session test set, consisting of the combination of the original 10 test sets, remained three times higher than random chance (52%), confirming the identification of common patterns across multiple participants despite the complex dual-task (icon selection while driving) and the narrow area covered by the adopted 2-channels montage. The general model was then evaluated in the laboratory condition on five new participants, whose signals were not considered in the training phase, and the performance remained as high as 49% ± 17%. Notably, participant s015 represents an outlier for the model performance. Indeed, we run a separate experiment with this participant employing the same infrastructure, but adopting a full 32-channel EEG montage, and we managed to achieve single-trial accuracies greater than 90%. A physiological analysis confirmed that the ERP was simply more lateral than that of the other considered participants, and therefore was not captured by the original 2-channel montage. Of course, a similar performance improvement was experienced with all other participants, but this at the expense of comfort and usability.

All in all, the same architecture, trained on the signals of all participants together, has achieved a classification accuracy similar to the average of the individualised models, both with already seen and totally new participants (Table 4.3). This represents a promising result in terms of generalization, which is a paramount condition to achieve the overall objectification goal of the present work, as the results need to be representative for a large population despite the strong differences among the individual brain responses (see Figure 4.11 to appreciate this difference).

Table 4.3: Classification performance achieved by the single general model with totally new subjects

	s011	s012	s013	s014	s015	**Average**
Performance	62%	48%	67%	50%	18%	**49%**



Figure 4.11: Average responses to the target of all the 15 available participants (channel Pz) and classification performance achieved by the general model on the corresponding test set. The general model was trained on both laboratory and car data (hybrid training configuration) of the original 10 participants and tested on the last driving session that was kept as separate test set. On the bar plot, the classification performance of the five new participants is highlighted (light blue dashed box) as well as the random chance (black dashed line, 16.6%) and the overall mean accuracy (magenta dashed line, 49%). Higher performances are associated with a larger P3 component and a smaller variability among the single trials (not visible in this plot).

4.5 Limitations

The present study represents a first evaluation of the proposed infrastructure for running EEG-based experiments in driving scenarios. Although effective in implementing a simple working BCI to control the infotainment menu of a car, the current state of the system still has limitations that we plan to be address in the continuation of the doctoral research, to improve performances and reliability.

As expected, the more challenging environment resulted in slightly noisier recordings (Figure 4.7): while the RMS scores of the baseline period did not differ significantly between conditions, the ERP RMS was higher. Accordingly, the main drawback is a relatively high ratio of rejected trials, originating from two main sources: loss of data during the wireless transmission and the artifacts present in the recorded EEG signals (see Table 4.1). The first issue could be solved by integrating a more professional wireless connectivity module in the electronics of the prototype EEG helmet or, when possible, to adopt other certified medical-grade devices. In general, the proposed headset is still a prototype and we plan to refine it integrating cable and sensor shielding solutions and active sensors amplification (like the one of the g.Nautilus PRO).

Concerning the rejections associated to the presence of artifacts in the signals, the majority originated from channel Fp1, and therefore are most probably due to non-cerebral, eye-related, activity. To mitigate this issue we plan to implement two solutions: 1) integrate an eye-tracker to automatically identify eye blinks, allowing to take advantage of ad-hoc removal procedures, such as removal of eye-related ICA components pre-computed in previous calibration phases, and 2) when the conditions allow it, adopt an high-density EEG helmet with full montage to allow artifact removal procedures like Artifact Subspace Reconstruction (ASR) that are based on channels interpolation. This last solution would also guarantee greater classification performances thanks to the additional information, as hinted in Section 4.4.2.

Also classification performance and the generalization ability of the adopted machine learning models should be improved. Although we achieved performances 3 times higher than the random chance baseline using a single general model, the absolute accuracy (around 50 % for the 6-class problem under consideration) is still not suitable for real usage, especially because it is achieved not in a single trial fashion but rather aggregating three repetitions.

4.6 Conclusions

In this chapter we presented a custom embedded infrastructure specifically designed to allow the acquisition and real-time processing of high-quality psychophysiological signals in driving conditions contextualized by telemetry data and environment sensing solutions such as the GPS trace. The pro-

posed infrastructure was validated implementing a BCI allowing to select the intended item of the infotainment menu of the car while driving, without any manual interventions, just leveraging the driver's cognitive brain responses. More precisely, the BCI relied on an oddball-like stimulus presentation carousel to elicit ERPs time-locked to the icon appearances. A preliminary assessment of the synchronization ability of the infrastructure confirmed an average misalignment of 30 ms elapsing between stimulus delivery and EEG signals sensing, with a small jitter of 5 ms, stable across multiple sessions. Although satisfactory, this result could be improved by implementing automatic calibration procedures to characterize the mean unsolvable latency of each involved device featuring part of the communication outside of the LSL control (e.g., Bluetooth communication).

The system was operated both in simple laboratory conditions and more demanding driving sessions. Signals and classification performances associated with the two conditions were compared to assess the signal quality provided by the infrastructure. Results did not show any statistically significant differences among the two conditions, confirming the reliability of the proposed solution. Nevertheless, the trial rejection rates caused by casual wireless communication instabilities and presence of artifacts in the signal, are still not satisfactory and suggest the integration of more advanced solutions (see Section 4.5 for a non-exhaustive list).

Overall, the trained model achieved promising individualized classification performances. Furthermore, the same deep learning architecture that was used as base for the individualized models, achieved comparable generalisation results when trained an the data of all the participants together, even when tested on totally new people never seen during the training phase. Considering the different subjective characteristics of the ERP responses, this promising result represents a step forward in the generalization direction as it suggests that the Deep4Net architecture succeeded in learning robust population-invariant patterns allowing to recognize the target P3 ERP component. We speculate that the same deep learning architecture can therefore be successfully used in similar population-wide ERP-based problems, such as the general investigation of sound localization within the ERPs evoked by impulsive warning sounds.

In conclusion, although improvable and extensible, the proposed infrastructure demonstrated to be effective and complete for investigating subjective intentions and feelings, even in online settings requiring human interac-

tion, thus more ecological and realistic. It was used not only to acquire the physiological signals and provide online feedback, but also for the whole data analysis and model training phases, leveraging the integrated pipelines for data preprocessing, signal quality evaluation, statistical analysis, and model training (both deep learning and classical feature-based).

Chapter 5

Sound localization

In this chapter, we present our main contribution in investigating the horizontal sound localization component of the human spatial sound perception. After an initial introduction (Section 5.1), where we present some prior studies on the topic and the hypotheses behind this study, we describe the methodology adopted in a preliminary pilot study and the corresponding results (Section 5.2), which refer to a large extent to [349]. Then we describe the main experiment and present the obtained results (Section 5.3), and finally, we conclude with a discussion on the emerged insights (Section 5.4).

Research objective 2: *Investigate whether patterns associated with horizontal sound localization are accessible in EEG signals and determine whether machine learning classifiers leveraging these patterns can be used in the automotive industry to jointly design and select the best spatial warning sound, based on its induced behavioral outcomes and its discriminability, and to perpetually monitor the actual perception once the selected sound is deployed in the vehicle.*

5.1 Introduction

The mechanisms underlying the human ability to localize sounds in complex acoustic environments, such as in a vehicle while driving, dependent on sound characteristics and behavioral goals are not entirely understood. Previous empirical studies on sound localization have mainly adopted simple artificial sounds, such as white-noise or pure tone bursts, even though it has been shown that, in some cases natural sounds produce richer and stronger responses [350], and often considered only the frontal hemispace, ignoring rear sources that are hugely relevant in driving conditions. Moreover, a large body of studies implemented oddball-like paradigms to study the cerebral responses associated with sound localization, thus investigating conditions where specific directions were attended, which is not a realistic situation for warning sounds evaluation.

More generally, as thoroughly discussed in Chapter 3, auditory processing in the human auditory cortex has been largely investigated from a physiological point of view using various recording techniques [228, 229, 230, 231, 232, 225, 233, 227, 224, 234, 235, 236, 238, 221, 240, 241, 242, 243, 248, 249, 250, 9, 19, 10, 251, 252, 253, 254, 255, 256, 257, 258, 259]. A large body of literature suggested a cortical dual-pathways system involved in auditory processing [351, 352, 353, 354, 355, 356, 15, 16, 17], with anterior areas largely engaged in decoding the content of a sound ('what'), and posterior temporal and parietal areas playing a crucial role in the processing of spatial information ('where') [20, 8, 21, 15, 22, 18, 260, 256, 251, 258, 261, 8, 262, 19] .

Previous research showed distinct cortical patterns when listeners were presented with sounds from various directions, demonstrating that non-invasive neural recordings such as electroencephalography (EEG) are sensitive to auditory spatial processing [24, 272]. Three studies have attempted to classify the direction of a sound source from the corresponding EEG responses in pseudo-realistic non-oddball-like settings [26, 27, 28]. Promising classification results were achieved in all these preliminary studies, but none of them involved enough participants to be able to evaluate the generality of the findings. Additionally, apart from [26], they approached the classification task in a simplified manner averaging multiple brain responses rather than single trials. On the other hand, in [26] only binary configurations between

various directions and a frontal reference direction were evaluated, therefore only the front-rear configuration resulted relevant to our scope.

Nevertheless, the methodology and the insights originating from the proposed results suggested to investigate the same subject more in depth with more participants and sound repetitions, as it is still unclear how accurately spatial auditory signals can be decoded and whether any generality in the suggested patterns exists. In this work we aim to go a step further in this direction.

The research questions behind this study were originally the following:

1. *Is it possible to discriminate the direction of a sound source emitting a natural or pseudo-natural sound in a single-trial fashion from the associated EEG responses? To what extent? Are there general patterns that are invariant among a population despite the individual anatomical and functional differences?*

2. *Are the results of the other studies replicable and generalizable?*

3. *Do posterior sounds, given the lack of the associated visual information, elicit different and characteristic brain responses? Do they help in discriminating this direction against the others?*

To evaluate the methodology, test the experimental protocol and try to replicate the literature results we run a similar pilot study with five participants performing an active localization task while listening to a short natural wood-cracking sound from eight source positions on the horizontal plane. The combination of a natural sound, real speakers, and a pure listening task (rather than a decision task like in a P300-based paradigm) was chosen to evaluate the classification performance in a simulated realistic scenario.

The single-participant results obtained classifying the single-trial ERPs were statistically significant, compared to a random baseline, in all evaluated configurations, but presented the largest physiological differences and the consequent highest classification performances in the "left vs right" and "lateral vs longitudinal" (centric vs eccentric) configurations. This latter result confirmed prior evidence about principal diverging processing patterns in the "centric vs eccentric" configuration presented in [24, 25].

The results of this pilot study have been used to determine the population size of the main experiment. Moreover, they suggested some small

modifications to the experimental paradigm and the formulation of additional hypotheses. Although all evaluated configurations presented statistically significant classification accuracies, we decided to concentrate on the ones that showed the greatest discriminability, and therefore reduced the scope of the experiment to the four main directions also considered in two of the reference studies (front, rear, left and right). This choice of reducing the considered directions derived also from the need of a greater number of sound repetitions to produce statistically valid results, especially in forecast of the population-wide analyses of the main experiment, and to allow the training of more complex machine learning models like deep neural networks to improve the single-trial classification performances. In this light, to reduce the inter-trial interval and thus to increase the number of repetitions but also to consider a more natural context, we also decided to switch to a fully passive listening without any active localization task. The only active localization task was performed at the beginning of every session playing the same trains of four hand claps but statically positioned either at the nearest or the farthest extreme of the sound motion route. to evaluate the individual sound localization ability and to allow the participants to familiarize with the sounds. Moreover, this data was purposely collected to allow a comparison with the moving sounds of the protocol, especially at the fourth impulse where motion perception was evident.

Concerning the protocol, we changed the stimulus and used trains of four hand claps that were processed with advanced spatial audio techniques to simulate motion either toward or away from the participants, with the objective of investigating whether an approaching sound has a stronger effect than a receding or static one, and whether this effect is measurable in the EEG responses. The research questions formulated after the pilot study are the following:

1. *Are the classification performances achieved in the best configurations of the pilot study ("left vs right" and "lateral vs longitudinal") confirmed (or even improved thanks to the larger number of repetitions and the possibility to train more data-eager deep learning models) with a larger population?*

2. *Is the addition of sound motion perceived compared to static sounds? Does it have any measurable effect in the EEG responses? Does it help to improve the classification accuracy?*

3. *Does having a sound composed of multiple impulses improve the classification accuracy? Is there any adaptation effect hindering this outcome?*

5.2 Pilot study

This preliminary investigation was designed to assess the possibility of decoding the location of a natural sound source on the horizontal plane from the associated EEG responses in a pseudo-realistic scenario. The main goal was the definition of a suitable experimental protocol and its empirical evaluation with a restricted number of people to properly estimate the appropriate population size for the main experiment. Additionally, the intention was to take inspiration and replicate the results of similar studies [26, 27, 28, 280] by partially implementing their protocols and leveraging their resulting considerations relevant to our goal.

In particular, the present study involved five participants performing an active localization task while listening to a short (0.58 s) natural wood-cracking sound from eight source positions on the horizontal plane. The combination of a natural sound and real speakers was chosen to evaluate the classification performance in a more realistic scenario, whereas the active localization task was retained to preliminarily quantify the participants' localization ability in the selected experimental environment.

The within-participant single-trial classification results, albeit drawn from a small pilot dataset, demonstrated the effectiveness of the methodology. All four considered participants (one was excluded for acquisition issues) achieved statistically significant classification accuracies in all evaluated configurations, with peaks in the localization configurations involving aggregations of directions (three directions on the left vs three directions on the right, and longitudinal vs lateral directions, i.e., front and rear vs left and right). This result, although effective in confirming the existence of EEG patterns associated to spatially related directions, encouraged the implementation of modifications to the experimental protocol allowing to acquire more trials per direction to succeed in improving classification accuracy. Moreover, the employed wood-cracking sound included two prominent clicks at 250 ms distance that induced two distinct but overlapping ERPs that complicated the analyses due to the erroneously unforeseen impossibility to isolate the component responsible for the localization. As a result, after the pilot study we decided to use a single-impulse hand clap as natural stimulation sound.




Figure 5.1: Experimental setup. A) The natural wood-cracking sound was reproduced from 8 evenly separated loudspeakers positioned on the horizontal plane at a distance of 1.3 m from the center of the participants' head, where the listening level had been adjusted to peak values of 80 dB(A). B) Characteristics of the adopted wood-cracking sound (raw signal in the top panel and spectrogram in the bottom one).

5.2.1 Experiment description

Five healthy volunteers (1 female, one left-handed, mean age 32.2 years ranging between 29 and 39 years) participated in the pilot study. All of them provided voluntary information consent and reported to have normal hearing abilities and no known neurological or psychiatric diseases. Each participant took part to four acquisition sessions distributed across four different days for robustness against baseline mental state and helmet positioning. One participant was not considered in the analyses due to the impossibility to complete all four acquisition sessions due to technical issues.

The EEG signals were recorded from the participants at a sampling rate of 500 Hz using a g.Nautilus PRO system (gtec, Austria) equipped with 32 active dry electrodes (g.SAHARA) positioned according to the 10-20 system. Reference and ground were placed at the two mastoids.

The acquisitions were performed in four different days in the dimly lit, acoustically treated, listening room of the electroacoustic laboratory of *Casa del Suono* (Parma, Italy) where the participants sat in a comfortable chair surrounded by eight loudspeakers evenly spaced every 45° (+0°, -45°, -90°, -180°, +135°, +90° and +45°) at ear height and 1.3 meters from the sweet spot as shown in panel A of Figure 5.1.




Figure 5.2: Experimental paradigm. Each recording session was composed of two runs consisting of 80 trials. Each trial consisted of the presentation of the sound from a given direction. The randomized sequence of 80 directions within a run was balanced (10 repetitions for each of the 8 directions). A subjective feedback was provided after each trial through a custom mobile application. After the feedback, a random inter-trial time interval between 1 and 1.5 s was implemented to avoid inter-trial phase-locking effects.

The loudspeakers were controlled by Max 8 (Cycling '74) hosted on a Windows 7 computer and driven through a dedicated soundcard (details about room and setup can be found in [357]). The speakers were equalized using inverse filters of the impulse response computed applying the Kirkeby regularization [358]. As suggested in [359], the listening level at the sweet spot was calibrated to peak values of 80 dBA, which corresponds to the ideal subjective level.

The experiment consisted in an active sound localization task where the participants were asked to confirm the perceived direction of a short (0.58 s) natural wood-cracking sound randomly played from one of the eight loudspeakers. Panel B of Figure 5.1 shows the characteristics of the employed sound, in particular two main impulsive components at the beginning and at 250 ms. After each sound, the participants were asked to provide their feedback through a custom mobile application running on a smartphone that they were holding on their hands throughout the whole experiment.

All sessions started with a short training in which the direction of the immediately following sounds were indicated in advance, thus allowing the

subjects to familiarize the different sound characteristics before the actual data acquisition. The main part after the training consisted of two runs for a total of 160 sounds (80 trials per run consisting of 10 random repetitions per direction). These two runs were interleaved by a 5-minute break. The sound directions of each run were defined by a different random sequence and the time evolution of each trial followed the protocol depicted in Figure 5.2. During the sound reproduction and for the subsequent 0.5 s the interaction with the mobile application was disabled to avoid undesired movements near the time window of interest. Once enabled, the participants could confirm their perceived direction without any timing constraints. A random inter-trial time interval (between 1 and 1.5 s) between the feedback confirmation and the beginning of the following sound reproduction was implemented to avoid artificially induced phase-locking in the epochs.

5.2.2 Data preprocessing

Preprocessing was performed offline in MATLAB (EEGLAB, version 14.1.1b) and custom Python code. At first, EEG recordings were visually inspected to reject noisy channels and time intervals. As a result, the rearmost channel Oz was excluded from the analysis due to the abnormal fluctuations present in most of the sessions.

After this preliminary step, raw EEG signals were preprocessed with the Artifact Subspace Reconstruction (ASR) algorithm to increase the signal-to-noise ratio (SNR) [360, 361]. Specifically, signals were high-pass filtered using the default filter (non-causal FIR filter, Kaiser window, 0.25 Hz - 0.75 Hz transition band, 80 dB attenuation) and the clean calibration data was automatically extracted from the recordings. This calibration data is needed by the algorithm to estimate the channels covariance used both to identify and to interpolate noisy intervals.

All parameters of the ASR method were set to the default values, with the exception of a more relaxed channel correlation criterion (minimum channel correlation allowed equal to 0.75 compared to the default of 0.85), a less constraining participant-specific standard deviation threshold ranging from 7 to 12 (compared to the default of 5) to remove only particularly large artifacts, and a more aggressive criterion for bad channels identification (maximum tolerated fraction with respect to the total recording duration




Figure 5.3: Average response to the sound onset from lateral (red) and longitudinal (blue) directions (configuration S in Table 5.3). Panel A shows the ERP in the representative channel Cp1, highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). The same information is highlighted in the spatio-temporal domain in Panel B with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference among the two conditions.

set to 0.2 compared to the default of 0.5). The channels identified as bad by

ASR were replaced by a spherical interpolation of all the remaining channels using the FieldTrip[1] standard 10-5 channel locations.

After the artifact removal phase, cleaned signals were band-pass filtered (one-pass, zero-phase, non-causal FIR filter, Hamming window with 0.0194 pass-band ripple and 53 dB stop-band attenuation, 3 Hz - 35 Hz) and then epoched retaining the 0.58 after the acoustic stimulus onset. This window clearly showed a pair of ERPs time-locked to the wood-cracking impulsive components (both N1 and P2 ERP components were present as expected from the literature). At this stage, an artifact rejection step was implemented by spherically interpolating all channels of any single trial exceeding a $\pm$ 45 μV threshold, thus considered abnormal. Additionally, if after this interpolation step any of the single channel signals of a trial were still exceeding the threshold, meaning that the cleaning procedure failed, the trial was rejected. The percentage of epochs exceeding the threshold for the four subjects was 4.7% $\pm$ 4.3%, and the single channel signals interpolation successfully corrected 91.6% $\pm$ 13.9% of them.

Finally, the Denoising Source Separation (DSS) approach [362] was used to increase the discriminability from EEG signals. DSS rotates the data into a component space that maximizes the separability among the classes and therefore it facilitates the subsequent data analysis by reducing the within-class and increasing the between-class variability. Prior to applying DSS we discarded the high-amplitude frontal channels Fp1 and Fp2 (the channels most affected by eye-related activity) since this method strongly dependent on the average of all the channels. The optimal number of DSS components to retain was selected through cross-validation in the data analysis phase for each participant and each localization configuration. In most of the cases the best value found was in the range between 20 and 25 components out of 29, thus rejecting from 4 to 9 components.

5.2.3 Data analysis

After preprocessing, the extracted epochs were used to search for statistically significant patterns and to train participant-specific classification models for different localization configurations (shown in Table 5.1, 5.2, and 5.3).

[1] `https://www.fieldtriptoolbox.org/`




Figure 5.4: Average response to the sound onset from left (orange) and right (violet) directions (configuration 5 in Table 5.3). Panel A shows the ERP in the representative channel Cp1, highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). The same information is highlighted in the spatio-temporal domain in Panel B with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference among the two conditions.

5.2.4 Physiological responses

Figure 5.3 and Figure 5.4 show the population average ERP response of a representative channel (panel A) and the whole spatio-temporal evolution of the difference wave (panel B) for the two localization configurations exhibiting the greatest discriminability.

The trial window used for the classification is highlighted in the ERP plots by the two black dashed vertical lines. In the same plots, the green areas indicate time windows where the ERPs of the two conditions were statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). The same information, considering all electrodes, is shown in the spatiotemporal plot, where statistically significant regions of interest are highlighted with a crosses (X). The fact that both configurations present blobs of statistically significant difference between the configuration directions, and that those blobs last (evolving) for a prolonged period of time around known ERP peaks like N1, P2 and N2 (see the scalp topographies shown in the Figure 5.3 and Figure 5.4), suggests the presence of invariant physiologically plausible patterns exploitable for classification.

Notably, the ERP representations also show a qualitative difference between the responses to the first and second sound click. Apart from the fact that the beginning of the second ERP that starts at a negative amplitude because it overlaps with the ongoing first ERP, the second P2 component lasts longer. This phenomenon could not be explained using the adopted experimental paradigm and made it difficult to precisely identify unique ERP patterns allowing to classify the sound direction. As a consequence, although interesting, this observation suggested to backtrack to a simpler single-impulse natural sound for the main experiment.

5.2.5 Classification

PREPARATORY ANALYSIS Behavioral assessment of the participants' localization ability demonstrated 98.9% of average accuracy. The strong localization ability shared among all participants suggested avoiding the collection of subjective feedback to implement a shorter experimental protocol allowing the collection of a higher number of trials and thus focus on the main goal of localization-relate physiological pattern identification.

Concerning the classification task, considering the limited number of

epochs per class at our disposal, we used the simple Random Forest (RF) ensemble method to leverage its bagging characteristic to reduce model variance. Additionally, to increase the number of epochs per class, hypothesizing common patterns in the brain responses associated with spatially related directions, we experimented with localization configurations involving aggregations of directions (see first three columns of Table 5.3).

The classifiers' hyperparameters were optimized through a grid search in a 5-fold cross-validation fashion splitting the data according to a 70% train, 20% validation and 10% test subdivision.





To build the feature vector for classification we followed the *windowed means* approach [344], thus for each channel we partitioned this trial in sub-windows and we used the average value within each sub-window as features. The size of the sub-windows was selected through the same cross-validation procedure used to select the number of DSS components and in most cases, it was found to be 3 samples, resulting in a feature vector length of 2407 (29 channels x 83 sub-windows).

The other hyperparameters tuned through cross-validation were number and depth of the trees or the Random Forest classifier, eventually set to 1000 and 12 respectively and, as discussed in Section 5.2.2, the number of components to retain in the DSS denoising phase. This parameter was tuned separately for each of the classification analyses (i.e. for each participant and localization configuration) and its optimal value was generally between 20 and 25 components out of 29.

RESULTS The presented classification performances of the participant-specific models on the test set are the result of 20 executions of a train-validation-test procedure with different shuffling patterns (to avoid overfitting the test set). Table 5.1, 5.2, and 5.3 show the single-trial accuracy results (computed as the number of correctly classified trials divided by the total number of trials).

Each column of a table represents a different localization configuration and we divided them in three groups based on the arity (i.e. the number of elements in a set) of the classification problem and the size of the classes in terms of directions.

Table 5.1 reports the results of the binary classifications involving couples

	A) 	B) 	C) 	D) 
Subject 1	61.2 ± 11.8	60.9 ± 9.6	56.9 ± 12.0	62.5 ± 12.0
Subject 2	57.8 ± 9.4	61.9 ± 13.2	53.1 ± 13.3	57.5 ± 11.8
Subject 3	53.1 ± 10.2	63.7 ± 9.2	61.6 ± 8.2	58.7 ± 10.5
Subject 4	60.9 ± 10.4	60.3 ± 10.7	55.6 ± 13.7	58.4 ± 11.6
Average	58.3 ± 10.5	**61.7 ± 10.7**	56.8 ± 11.8	59.3 ± 11.5





	E) 	F) 	G) 	H) 
Subject 1	58.4 ± 15.1	56.9 ± 9.9	59.4 ± 16.9	63.1 ± 12.2
Subject 2	41.2 ± 13.5	47.2 ± 12.4	54.1 ± 12.5	63.1 ± 11.7
Subject 3	49.4 ± 11.2	53.1 ± 8.3	64.1 ± 11.8	62.5 ± 10.4
Subject 4	53.7 ± 9.1	62.5 ± 9.0	64.7 ± 12.4	60.3 ± 11.6
Average	50.7 ± 12.2	54.9 ± 9.9	60.5 ± 13.4	**62.3 ± 11.5**





Table 5.1: Single-trial classification performance achieved in binary localization configuration (single individual directions). Bold values indicate the configurations where the average performance among the subjects minus the standard deviation is greater than the chance level (50%).

of individual directions, Table 5.2 the results of the ternary classifications, and Table 5.3 the results of the quaternary, quinary and octonary classifications (T, U, V, W, and X) and the results of binary classifications involving groups of aggregated directions (Q, R, and S).

Some configurations were modeled better than others with the selected approach (bold values in Table 5.1, 5.2, and 5.3). These configurations are highlighted if the average of the participant-specific performance minus the standard deviation is greater than the chance level.

The mathematical chance level (defined by the number of classes involved in the classification) was validated empirically by means of a permutation test based on random shuffling. As expected, given that the number of trials per class was almost balanced after trial rejection, the empirical baseline matched the mathematical one.

The results of the localization configurations involving aggregations of directions based on their spatial distribution are slightly higher and present

	I) 	J) 	K) 	L) 
Subject 1	49.2 ± 8.1	49.2 ± 8.6	45.8 ± 8.9	45.6 ± 8.9
Subject 2	37.3 ± 9.4	39.4 ± 10.0	42.5 ± 11.1	43.1 ± 9.3
Subject 3	41.4 ± 9.4	45.2 ± 8.0	48.1 ± 9.4	50.6 ± 10.6
Subject 4	46.9 ± 10.3	51.7 ± 10.5	52.3 ± 11.2	43.3 ± 12.4
Average	**43.7 ± 9.3**	**46.3 ± 9.3**	**47.2 ± 10.1**	**45.7 ± 10.3**





	M) 	N) 	O) 	P) 
Subject 1	42.9 ± 8.5	40.8 ± 10.9	37.7 ± 11.3	41.0 ± 9.4
Subject 2	38.9 ± 9.2	32.3 ± 8.2	36.2 ± 8.9	37.7 ± 8.2
Subject 3	42.1 ± 8.0	38.7 ± 11.5	43.7 ± 9.1	39.2 ± 10.2
Subject 4	47.9 ± 9.9	35.4 ± 10.0	36.9 ± 6.3	47.7 ± 10.5
Average	**43.0 ± 8.9**	36.8 ± 10.1	38.6 ± 8.9	41.4 ± 9.6

Table 5.2: Single-trial classification performance achieved in ternary localization configurations (single individual directions). Chance level is 33%.

a lower variance with respect to counterparts involving single directions (hypothetically due to the greater number of trials available for training and validation). Considering the obtained results, we decided to refine the experimental protocol towards the main experiment in such a way to focus on the localization configurations providing the highest discriminability.

5.2.6 Population size computation

To estimate the needed sample size (number of participants) for the main experiment we referred to the general considerations and the realistic Monte Carlo simulation presented in [363]. This was possible because the experiment details, the adopted statistical test and the analysis parameters precisely matched. According to the results of this pilot study, we are facing conditions with a small effect size (d) in the order 0.2 (left vs right, $|m1 - m2| = 1.5\ \mu V$, $std = 7.5\mu V$) and 0.4 (eccentricity, $|m1 - m2| = 3\mu V$, $std = 7.5\mu V$), comparable with the lateralized readiness potentials (LRPs) case presented in the study. Additionally, we also intend to perform within-group analyses and aim at a 0.05 statistically significant effect. According to Figure 6b, with at least 12 participants and 30 trials per condition, it is already possible to









	Q) 	R) 	S) 	T) 
Subject 1	63.8 ± 6.2	64.8 ± 7.6	65.6 ± 9.0	37.8 ± 6.0
Subject 2	55.4 ± 8.0	62.4 ± 5.3	55.1 ± 6.6	32.0 ± 7.0
Subject 3	56.0 ± 4.7	67.3 ± 6.9	62.5 ± 7.6	37.8 ± 8.2
Subject 4	57.9 ± 5.3	62.1 ± 5.1	68.1 ± 7.9	40.3 ± 9.8
Average	$\mathbf{58.3 \pm 6.1}$	$\mathbf{64.1 \pm 6.2}$	$\mathbf{62.8 \pm 7.8}$	$\mathbf{37.0 \pm 7.7}$
	U) 	V) 	W) 	X) 
Subject 1	33.0 ± 6.4	28.7 ± 4.6	27.7 ± 6.1	18.0 ± 4.2
Subject 2	28.1 ± 8.4	23.4 ± 6.8	25.6 ± 6.0	14.8 ± 4.7
Subject 3	33.6 ± 6.2	23.9 ± 5.4	25.7 ± 8.2	18.3 ± 4.8
Subject 4	34.7 ± 5.7	27.9 ± 5.3	32.2 ± 8.2	19.1 ± 4.9
Average	$\mathbf{32.3 \pm 6.7}$	$\mathbf{26.0 \pm 5.5}$	$\mathbf{27.8 \pm 7.1}$	$\mathbf{17.6 \pm 4.7}$

Table 5.3: Single-trial classification performance achieved in binary localization configurations (aggregated directions), and quaternary, quinary and octonary localization configurations (single individual directions). Chance levels are 50%, 25%, 20%, and 12.5% respectively.

detect a statistically significant ERP effect (statistical power greater than 0.8). Similarly, considering a within-group analysis, with a 1.5μV between-conditions difference and at least 45 trials per condition, 20 participants are enough to obtain a 0.8 statistical power (see Figure 8a). This result is in line with most of the ERP studies present in the literature, and therefore is the target of valid participants we set for the main experiment. Accordingly, considering the 20% participants rejection rate we faced in the pilot study and the uncertainty related to the ongoing SARS-CoV-2 pandemic we decided to recruit 10 additional buffer participants. Moreover, a greater number of participants would help in estimating the generalization of the trained machine learning models, especially in the leave-one-participant-out validation procedure.

Concerning the number of trials, even though the above estimate suggested that 45 trials would be enough to obtain statistically significant results, considering the data dependence of deep learning models and the hints provided by the pilot study, we decided to collect at least twice as many trials

per class of the pilot study, resulting in at least 160 trials per class.

5.2.7 Conclusions

The single-trial classification results, albeit drawn from a small dataset, demonstrate the effectiveness of the approach to investigate EEG patterns associated with the localization of a natural sound. In fact, the trained participant-specific models achieved statistically significant classification accuracies in all configurations under consideration, in particular in those involving aggregations of directions. We hypothesize this to be due to the greater number of trials per class available in those configurations, therefore, considering the extremely high localization scores seen in this pilot, we opted to avoid the collection of subjective feedback and to focus solely on the most discriminable localization configurations to increase the number of trials in the main experiment.

We also decided to change the sound into a single-impulse natural sound like a hand clap to be able to more precisely isolate the ERP components involved in the horizontal sound localization processing.

To increase the classification accuracy towards more reliable performances, we decided to investigate the possible influence of sound motion by simulating approaching and receding sounds in place of the static one used in this pilot, hoping the approaching sounds to induce more discriminable brain responses.

5.3 Main experiment

Based on the insights gathered from the pilot study and the updated research questions, we refined the protocol to run the main experiment. In particular, the new protocol, which is described in Section 5.3.1, aimed at improving the individualized single-trial classification accuracy achieved in the pilot study in the two main localization configurations ("left vs right" and "lateral vs longitudinal") by using trains of impulsive natural hand clap sounds simulating radial motion (either approaching or receding). Sound motion was simulated by means of advanced sound spatialization techniques and was included in the experiment to investigate whether moving sounds could be discriminated from stationary sounds and, more importantly, whether approaching sounds would induce any measurable effect in the EEG responses that could help

the sound direction classification. Other two key differences with respect to the pilot study were the shift towards a passive listening condition and the limitation of the number of sound source directions to the main four ones (front, rear, left and right). Combined, these two modifications allowed to collect a greater number of trials, necessary for the adoption of complex deep learning architectures such as CNNs and Transformers, that we trained in comparison with models like the other studies (time-frequency features extracted with CWT and DWT techniques, in particular). The main goal of these complex models was the research of general, population-wide, patterns. Moreover, given the multi-impulse trial nature (all four impulses of a sound trial came from the same direction), we could at the same time investigate the emergence of adaptation mechanisms and experiment with the Multi-Instance Learning (MIL) paradigm to investigate whether classifying multiple semantically related impulsive sounds together would improve the spatial discrimination accuracy.

As for the pilot study, the data analysis was subdivided in a physiological signals' investigation performing temporal and spatio-temporal statistical analyses among the different classes of a localization configuration, and model training and classification. In both cases, thanks to the sophisticated experimental design we could approach multiple perception problems, not only the main one concerning the horizontal localization per se. Indeed, we were also able to evaluate brain responses associated to "approaching vs receding" sounds, which is very much associated to sound intensity perception and, thanks to an additional experimental section involving only stationary sounds, also the more interesting "moving vs stationary" sounds configuration. This last analysis was one of the reasons of the 4-impulse sound trains used in the main experiment in place of the pilot single wood cracking sound, as we could compare the brain responses to impulses other than the onset one which is too short to provide a clear cognitive sound motion feeling. In this case, we compared the responses to the fourth impulse of the approaching sound with those of the close stationary sound, and those of the receding sound with those of the far stationary sound because they were perceived at the same distance. The only difference was the accumulated perception of motion in the approaching and receding cases.




Figure 5.5: Characteristics of the simulated moving sounds adopted for the main sections of the experiment. They are constituted by a burst of four hand claps separated by 0.5 s (raw signal in the top panel and spectrogram in the bottom one), processed with Ambisonics [12] to give the impression of approaching (panel A) or receding (panel B) sounds.

5.3.1 Experiment description

PARTICIPANTS Thirty healthy volunteers (10 female, mean age 32 ranging between 26 and 39 years) participated in the experiment, after having provided voluntary informed consent. All participants reported to have normal hearing abilities and no known neurological or psychiatric diseases. Each participant underwent two acquisition sessions in two different days and two participants were discarded from the analyses due to excessive amount of noise in the recordings. Approval for the study was obtained from the local Ethical Committee ("Comitato etico Unico per la provincia di Parma").

ACQUISITION SETUP The EEG signals were recorded with the same equipment used in the pilot study and also the experiment location and the sound system remained the same (listening room of the electroacoustic laboratory of *Casa del Suono*). To overcome the slight misalignment issue of the pilot study associated with the additional acoustic equipment not directly integrated in our infrastructure, we added a microphone feedback loop recording and streaming via LSL the exact listened sounds (microphone placed on top of the participants' head) to achieve the best possible synchronization with the EEG signals.




Figure 5.6: Characteristics of the simulated stationary sounds adopted for the training section of the experiment. Just as the moving sounds, they are constituted by a burst of four hand claps separated by 0.5 s (raw signal in the top panel and spectrogram in the bottom one), processed with Ambisonics [12] to give the impression of close (panel A) or far (panel B) stationary sounds (at the same extreme distances of the moving ones to allow fair comparisons).

SOUNDS PREPARATION AND REPRODUCTION Given the intention of simulating approaching or receding motion in a realistic and perceivable manner, we moved from the single wood-cracking sound of the pilot study reproduced as point source from individual loudspeakers, to a burst of four hand claps processed by means of the High Order Ambisonics (HOA) [12] technique and rendered through the 16 loudspeakers of the available spherical arrangement of the listening room. Realistic impulse responses representing the real acoustic path between sound source and receiver were measured at four different distances (0.5 m, 1 m, 2 m and 4 m) using a multichannel HOA microphone and used to process the target sounds (a pool of hand claps slightly differing from one another to reduce the sensation of artificially crafted sounds) though convolution to render the different distances. The resulting sound were then rotated in the four target directions and grouped in bursts of four impulses according to approaching or receding trajectories (see Appendix 1 for a detailed description of the processing and Figure 5.5 for the spectrogram of the resulting approaching and receding sounds). This complex processing, thanks to the 16-channel HOA reproduction, provided a significantly more realistic feeling of motion than the basic counterpart purely acting on sound intensity.

TRAINING SECTION Each session started with a short training section (12 randomized repetitions per direction) in which the participants were asked to confirm the perceived direction of each sound. In this section we presented the participants with stationary sounds, either at close or far distance, simulating the same final distance of the two kinds of moving sound (see Figure 5.6 for the spectrogram of the stationary sounds). This choice served three purposes: firstly, it allowed the participants to get accustomed with the sound characteristics in relation to the adopted virtual spatialization technique, as the sounds were not reproduced as point sources by individual loudspeakers as was done in the pilot, secondly, it allowed to quantify the individual and overall localization ability of the participants, and lastly, it allowed the collection of EEG responses to stationary bursts needed to make a comparison with the moving ones used in the main sections.

MAIN SECTIONS After the initial training section, the participants underwent two consecutive runs, each composed of 256 bursts fully randomized in terms of azimuth and motion direction. This corresponds to 64 sounds per direction, 32 approaching and 32 receding. In total, considering the 4 runs, distributed across two sessions, we collected 256 EEG responses per direction. The randomization sequence was different for each of the four runs and all participants were presented the same sequence in the same order. The 4 hand claps composing one burst sound were separated by a constant 0.5 s interval and the different sounds were interleaved by a random inter-trial time interval (between 1.5 s and 2.5 s).
Considering the decision to not perform any active localization task during the experiment, to retain the participants' attention, we introduced an additional 5% of deviant sounds (low intensity cracking background sounds from any direction) which they were asked to acknowledge by pressing a button. These trials were excluded from the data analysis.

5.3.2 Behavioral results

A preliminary assessment of the adopted sound reproduction technique took place before the acquisition campaign with six volunteers not considered for the experiment. Both sound localizability and motion perception were investigated adopting the same training procedure of the experiment. The participants correctly localized the sound sources 97.9% of the times and five




Figure 5.7: Direction independent individual ERP responses to sound onset (average of the responses to the four sound directions). Apart from minor differences in peak amplitude and latency, the overall shape is robust across participants. The onset response exhibits significantly larger responses than the following three responses which, in turn, show similar amplitudes.

of them reported a clear perception of motion (the sixth perceived only a variation of intensity, apart from the close sound that was actually perceived within 50 cm). All participants reported a confirmed the perception of the high-intensity sound being within 70 cm, and five participants perceiving motion reported a distance range comparable to the intended one (0.5 m to 4 m), in two cases just slightly shorter (3 m), and in one case larger (10m). Together, these results confirmed that the designed sonic environment successfully delivered the intended sensations.

The behavioral assessment of the participants' localization ability indicated, on average, a 94.9% correct identification of the sound directions. Only three participants performed worse than 90% and six participants obtained a perfect score and, in general, zero errors were made with lateral (left or right) sounds. We argue that the overall slightly lower performance compared to the pilot study (94.9% vs 98.9%) and the increased difficulties experienced in the front-rear cone of confusion could be due to the spatial virtualization

technique we adopted to deliver the feeling of sound motion (all 16 speakers were active at any given time), in place of the point sources (only one speaker at a time was activated) used in the pilot study.
After the end of the second session, without prior disclosure of the experiment details, we asked the participants to fill a questionnaire about their subjective perception. Among the thirty original participants, eighteen clearly perceived the sound motion (only one of them reported that the feeling artificial due to the employed sounds and the known environment configuration), and eight of them reported a compressed (<2m) distance range (almost contained within the loudspeakers distance of 1.3 m). The remaining twelve participants reported only a steady variation of intensity at speakers distance, and seven of them did not even perceive the high-intensity sound being particularly close. Overall, fifteen participants confirmed a strong feeling produced by the sounds featuring a high-intensity first impulse (either close stationary or receding sounds), especially from the rear direction, and ten participants spontaneously indicated that they felt a much stronger confidence in localizing the long-lasting, softer, distractor sounds.

5.3.3 Data preprocessing and classification methods

DATA PREPROCESSING Based on the minor classification improvements provided by the ASR and DSS methods in the pilot study and some preliminary investigations with the present data, we decided to keep the processing as simple and as general as possible we avoided to apply them. This was possible also thanks to the higher overall signal quality despite the 6 times larger population size. Accordingly, we did not perform any manual data rejections.
The signals were band-pass filtered between 3 Hz and 35 Hz with the same filter of the pilot study (one-pass, zero-phase, non-causal FIR filter, Hamming window with 0.0194 pass-band ripple and 53 dB stop-band attenuation), epoched retaining the 2 s after the sound onset (first impulse of the burst), and then passed through the artifact removal/rejection step. At this stage, all channels of an trial exceeding a predefined threshold of $\pm$ 60 μV (softer than the $\pm$ 45 μV used in the pilot) were spherically interpolated considering only the clean channels and, if after this interpolation, any trial channel still exceeded the threshold we rejected the trial. Contrarily to the pilot study in which we performed manual rejection, here we automatically interpolated

any flat trial channels and any trial channels exhibiting a standard deviation at least 3 times larger than the mean standard deviation of all the channels. Finally, we re-referenced the signals to Common-Average Reference (CAR) [52] to reduce the effects of possible localized noise.

CLASSIFICATION METHODS After preprocessing, the extracted trials were used to train different classification models in a single-trial fashion for different localization configurations. Considering the four available directions, we addressed four localization configurations: "left vs right", "front vs rear", "lateral vs longitudinal" and "front vs rear vs left vs right". For each configuration we trained an individualized model for each of the 28 participants subdividing the dataset into a stratified train-validation-test splitting. For sake of robustness, these models were trained and evaluated 20 times with different trial shuffling seeds (to avoid overfitting the test set). Additionally, we trained a single general model adopting a leave-one-participant-out procedure. For both training configurations we investigated multiple machine learning approaches, both deep learning and feature based.
Firstly, in addition to the *windowed means* [344] features extraction method used in the pilot, we investigated other two techniques presented in other similar studies [26, 27] to experiment with time-frequency representations. These two additional methods are the Continuous Wavelet Transform (CWT) [364] and the Discrete Wavelet Transform (DWT) [365]. As for the *windowed means* (WM) we computed the features for each channel individually and then concatenated them to construct the feature vector. With all three feature types we used a *Random Forest* (RF) classifier whose hyperparameters were kept fixed according to the pilot results (1000 trees of depth 12). Also the sub-window size of the *windowed means* approach remained equal to 3 samples as selected in the pilot, whereas we searched for the optimal parameters of the two new features extraction methods through a grid search in the classical 5-fold cross-validation with 70% train, 20% validation and 10% test splitting. The hyperparameters of the CWT method were the *number of scales* and the *mother wavelet* and their values were set to 32 and "morlet" respectively after the cross-validation procedure based on a majority voting metric across the different classification configuration we tackled. In the same way, we tuned the hyperparameters of the DWT method, setting the *level of decomposition* to 7 and the *number of coefficients* to 6. To specifically address the generalization across participants, we also investigated the




Figure 5.8: Average population-wide responses to front (blue) and rear (magenta) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference.

potential of Riemannian geometry [366, 367, 368, 369]. This technique uses covariance matrices as features for the classification, and a Riemannian metric to manipulate them [370, 371, 372, 373, 374, 375]. We experimented with

multiple configurations suggested in the corresponding Python implementation (PyRiemann [2]) and the best results with a pipeline composed of a xDAWN [376, 377] spatial filter, a covariance matrix estimation with projection in the Riemannian tangent space, and a Logistic Regression classifier. Secondly, in addition to the classical approach of manually crafting a feature vector and using a classifier such as a RF, we experimented with two additional automatic methods. The first is Rocket [378, 379], a computationally efficient state-of-the-art classification approach for EEG that is based on random convolution kernels. The second is the Deep4Net CNN architecture used to implement the BCI presented in Chapter 4, which demonstrated effective in achieving significant individualized and generalization accuracies. In this latter case we used the default values of the Braindecode library implementation, whereas we tuned the number of kernels and the classifier and its parameters for the Rocket approach in the classical cross-validation manner. The final selected configuration consisted in 5000 kernels and a Ridge Regression classifier (which provided slightly better accuracies than a Random Forest classifier).

5.3.4 Data analysis

The experimental protocol was specifically designed to allow a variety of analyses, starting with the obvious discrimination of different localization configuration. In addition, leveraging the availability of stationary, approaching and receding sounds composed of multiple, well separated, impulses, we were able to investigate the differences between approaching and receding sounds, the differences between stationary and moving sounds, and possible adaptation effects due to the multiplicity of semantically related impulses composing a sound. All these configurations were statistically analyzed from the physiological point of view both in the temporal and spatio-temporal domain, and from the single-trial classification point of view.

5.3.4.1 Physiological responses

Figure 5.7 shows the general responses (average of the four sound directions) of the individual participants. It can be appreciated that, despite some expected differences in peak latencies and amplitudes, the overall shape is stable across participants, showing some sign of variability mainly in

[2] `https://pyriemann.readthedocs.io/`




Figure 5.9: Average population-wide responses to left (blue) and rear (red) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference. Panel E and F show the ERP in channels T7 and T8 respectively, to give an idea of the contralaterality of the pattern.

the late onset response (from 0.3 to 0.6 s). Moreover, the onset response showed significantly larger peak amplitudes compared to the following three responses ($p < 0.05$ for each pairwise Welch's t-test for unequal variances between onset and subsequent responses) which, in turn, did not show any statistically significant differences ($p < 0.05$ for each pairwise Welch's t-test for unequal variances between them).

In this section we summarize the results of the statistical analyses that have been performed on the average EEG responses of the population in the mentioned configurations of interest. The goal was to identify relevant (statistically significant) spatio-temporal EEG patterns correlated with the processing of different sound characteristics. For each configuration, we run a series of channel-wise t-tests in the temporal domain (shown for the representative vertex channel Cz in panel A of each Figure), and series of temporal t-tests in the spatial domain (shown in panel B of each Figure). All analyses considered an α of 0.05 and have been corrected for multiple comparisons with the Bonferroni correction. The statistically significant regions were highlighted by green boxes in the time series plots of panel A and with crosses (X) in the spatio-temporal plots of panel B.
Contrarily to the hypotheses, all the identified statistically significant patterns have been found in the onset response, suggesting the lack of a motion- or direction-related perception effect in the EEG responses at later stages.

5.3.4.1.1 Localization configurations

In this section we show the temporal and spatio-temporal differences between the classes of the three main binary localization configurations, which are "front vs rear", "left vs right", and the aggregated "lateral vs longitudinal" (i.e., front and rear together vs left and right together).

FRONT vs REAR As can be seen in Figure 5.8 (panel A), this configuration shows almost zero statistically significant differences between responses to the two directions (only a tiny difference concentrated in channel Cz at 0.3 s, around the N2 peak, which is not even identified as statistically significant in the spatio-temporal domain shown in panel D, given the lack of a X the corresponding location). Indeed, as will be shown in Section 5.3.4.2, the "front vs rear" configuration was almost impossible to discriminated in a




Figure 5.10: Average population-wide responses to lateral (orange) and longitudinal (violet) sounds (independently from motion direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel C represents the legend of the configuration, and panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference.

single-trial fashion regardless the adopted classification method (best average result of 0.523 ± 0.063 obtained with the Rocket classifier). This result is in contrast with the results achieved in the pilot study (average classification




Figure 5.11: Average population-wide responses to approaching (pink) and receding (dark cyan) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference.

accuracy of 0.583±0.105) and with [26], where average single-trial classification results of 0.763±0.029 have been reported for this configuration using the DWT feature extraction technique which we also tested.›main

LEFT vs RIGHT As can be seen in Figure 5.9 (panel B and C), this localization configuration presents broader and more prolonged statistically significant lateralized differences in the rising edge between the N1 and P2 peaks (from 0.14 to 0.2 s) mainly measured in the temporal lobes (channels T7 and T8 which exhibit a contralateral pattern, consistent with the literature [24]). Although better performances have been obtained tackling this classification problem leveraging this stronger discriminating pattern (best average result of 0.576±0.064 obtained with the CWT + RF model), the results are lower than those of the pilot study in the same localization configuration (0.617±0.107). Nonetheless, a similar above chance result has been obtained in the general leave-one-participant-out evaluation, corroborating the identification of a general (population-wide) pattern.

LATERAL vs LONGITUDINAL This aggregated configuration shows the most evident statistically significant differences, which encompass the three main ERP components N1-P2-N2 as well as later cognitive stages taking from 0.4 onwards (see Figure 5.10, panel A and B). As can be seen in panel B, three main topographically distinct patterns differentiate the processing of this sound characteristic related to "eccentricity" (possibly due to the inherently relevant difference between monoaural and binaural cues). This result confirms the pattern identified in the pilot study, which had already been summarily described in [24, 25], involving a significantly larger population. These differences allowed a more robust single-trial classification than the previous two configurations. A best average result of 0.627±0.045 has been achieved training individualized models and 0.586±0.040 evaluating the leave-one-participant-out case. In this case, the performance is comparable, if not better (given the smaller variance), to the pilot study (0.628±0.078). Similar results have been obtained both with CWT + RF and WM + RF approaches.

5.3.4.1.2 Motion perception

In this section we show the physiological differences between distinct sound motion condition, regardless of the sound direction. Initially, we compare the ERP responses to approaching and receding sounds, which is strongly correlated with the intensity of these sounds at the different simulated distances, depending on the motion direction. Then we compare the ERP responses to




Figure 5.12: Average population-wide responses to approaching (gold) and close stationary (brown) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference.

the last impulse of the approaching sounds and the close stationary sounds (they exhibit the same intensity, and therefore the only variable is the perception of the immediately antecedent sound evolution) to determine whether

the accumulated motion perception has any effects on the ERP response. The same analysis is then performed on the opposite condition, namely receding sounds compared to far stationary sounds. Together, these three analyses should allow the identification of EEG patterns related to sound motion perception, if any.

APPROACHING vs RECEDING As expected, the main and only relevant differences are concentrated in the first and last ERP responses, which is where the difference in sound intensity is largest due to the largest distance. Although the onset response is larger than the last response as usual, a swap of peak amplitude reflecting sound intensity is clearly visible in panel A of Figure 5.11. Although no evidence of a motion-related perception can be isolated from this configuration alone, it is important to show that cerebral tracking of certain acoustic characteristics is present in the EEG responses also at times later than the onset.

APPROACHING vs CLOSE STATIONARY SOUNDS In this analysis, we compare the responses to the approaching sounds collected during the main sections of the experiment against the responses to the close stationary sounds collected during the initial trainings. Contrarily to the hypothesis, no statistically significant differences are found in the last ERP response (see panel A of Figure 5.12). This result rejects any hypotheses of identifiability of sound motion perception patterns independent from sound intensity within EEG signals. As usual, the only statistically significant differences are found in the onset response due to the maximum sound intensity difference, as in the "approaching vs receding" condition, but this does not provide any interesting information. Notably, though, the spatio-temporal pattern (which is almost identical to that of the "approaching vs receding" configuration, see panel B of Figure 5.12 and 5.11) is different from those seen with other configurations, suggesting a distinct processing of sound intensity.

RECEDING vs FAR STATIONARY SOUNDS Confirming the result of the previous "approaching vs close stationary sounds" analysis, also in this case no statistically significant differences are found in the ERP response evoked by the last impulse (see panel A of Figure 5.13).




Figure 5.13: Average population-wide responses to receding (brown) and far stationary (gold) sounds (independently from sound direction). Panel A shows the ERP in the representative channel Cz (panel B shows its location), highlighting in green the regions where the difference between the responses to the two directions is statistically significant ($p < 0.05$, Welch's t-test with Bonferroni correction). Panel D shows the differences among the two conditions in the spatio-temporal domain, highlighting with crosses (X) superimposed on the statistically significant channel locations at statistically significant times. The colors of the topographies represent the magnitude of the difference.

5.3.4.1.3 Habituation

Based on the results presented so far, especially the lack of statistically significant differences in responses to impulses rather than the onset, we decided




Figure 5.14: Population-wide direction-dependent difference waves representing "long" (between semantically unrelated trials, panel A) and "short" (between semantically related onset and subsequent response, panel B) habituation effects. Consistently with Figure 5.7, the great amplitude difference between onset response and subsequent ones results in greater differences than between subsequent semantically unrelated trials. A clear difference between lateral and longitudinal sounds is visible in both conditions, with a larger effect in the "short" case (panel B). Violet=Front, Cyan=Right, Gold=Rear and Red=Left.

to investigate possible habituation effects. Given that the protocol did not prevent the presence of consecutive sound bursts originating from the same direction, we divided the dataset into two mutually exclusive sets independently from the motion direction: one composed of all and only the trials in which the sound direction was the same of the previous sound, and the other comprising all and only the trials in which the direction was different from that of the previous sound. Here we present the comparison between these two sets for the four individual directions, which aims at identifying possible direction dependent long (semantically independent) habituation differences between onset responses to sounds coming from the same direction of the previous one and onset responses to sounds that varied direction (both conditions experiencing a 2 ± 0.5 s inter-trial interval between last impulse of the previous sound and onset of the following one). Similarly, we present the direction dependent short (semantically dependent) habituation differences between onset responses and second impulse responses. In this case, given the different amplitudes, a direct comparison between the two conditions (shown in panel C and D) is not as informative as the previous case and therefore we resort to the difference wave (shown in Figure 5.14 in panel A for the “long” habituation and in panel B the “short” habituation).




Figure 5.15: Habituation effects related to the frontal direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the absence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B).

(between semantically unrelated trials) direction-dependent habituation effects, we discovered that lateral sounds, and not longitudinal ones, elicit statistically significant differences in the ERP responses to consecutive sounds coming from the same direction and sounds coming from different directions. Also in case of “short” (between semantically related onset and subsequent response) direction-dependent habituation effects we found a different population-wide pattern between lateral and longitudinal sounds.

As can be seen from the difference wave shown in Figure 5.14 and the direct comparisons shown in Figures 5.15, 5.17, 5.16 and 5.18, both “long” and “short” habituation-related effects have been identified in lateral configurations and not in longitudinal configurations (see presence/absence of statistically significant differences in panel A & B, and larger differences in the statistically significant regions of panel C & D). This late finding requires further investigation with more appropriate multivariate statistical analyses and explicit effect quantification, in addition to further experiments to precisely isolate the origin of the pattern.




Figure 5.16: Habituation effects related to the rear direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the absence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B).

5.3.4.2 Classification

Considering the results of the physiological investigation showing statistically significant differences in the onset response, for the classification task we focused on the first 0.7 s after the stimulus onset. Moreover, to train sound intensity independent models while using the greatest amount of data available, we considered both approaching and receding sounds together.
In the following paragraph, we present the single-trial classification accuracies obtained averaging the 20 randomized training repetitions tackling the four localization configurations. For each configuration we trained 6 different models (WM + RF, CWT + RF, DWT + RF, Deep4Net, Rocket and a Riemannian geometry-based approach) both on individual data and on a leave-one-participant-out setting. As can be seen comparing the different tables, apart from the “front vs rear” case which we have already marked as unreliable given the chance-level-like performances, a clear pattern is highlighted: the CWT + RF model achieves the best performances in the individ-








Figure 5.17: Habituation effects related to the right direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the presence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B).

ualized setting whereas the Riemannian geometry-based approach achieves the best across-participants general results. This latter result adds evidence to the peculiar transfer-learning and generalization abilities of Riemannian geometry.

5.3.4.2.1 Localization configurations

Table 5.4: Windowed Means + Random Forest (WM + RF)

				
Individualized	**51.9±6.5** (51.1±6.3)	55.7±6.7 (50.4±6.3)	62.3±4.5 (49.7±4.5)	33.4±4.2 (24.5±4.1)
Leave-one-out	51.9±6.5 (50.3±2.3)	56.7±3.5 (50.0±2.6)	58.6±4.1 (50.3±1.6)	31.7±2.8 (25.2±1.4)








Figure 5.18: Habituation effects related to the left direction. Panel A and B show ERP and spatio-temporal differences of the "long" (between semantically unrelated trials) effect, whereas panel C and D show ERP and spatio-temporal differences of the "short" (between semantically related onset and subsequent response) effect. Note the presence of statistically significant differences in panel A and B (green regions in panel A and crosses (X) in panel B).

Table 5.5: Continuous Wavelet Transform + Random Forest (CWT + RF)

				
Individualized	52.1±6.3 (51.1±6.3)	**55.7±6.7** (50.4±6.3)	**62.7±4.5** (49.7±4.5)	**34.3±4.2** (24.5±4.1)
Leave-one-out	52.8±3.4 (50.3±2.3)	56.8±3.2 (50.0±2.6)	58.6±4.0 (50.3±1.6)	31.4±2.9 (25.2±1.4)

5.3.4.2.2 Auxiliary configurations

To validate the choice of using approaching and receding onset trials together, we trained the fast WM + RF model on the two configurations separately, and the accuracies achieved in the two cases failed to show statistically significant differences (McNemar's test, $\alpha = 0.05$). Moreover, the two reduced configurations resulted in poorer performances compared to the combination

Table 5.6: Discrete Wavelet Transform + Random Forest (DWT + RF)





				
Individualized	50.8±6.4 (51.1±6.3)	53.5±6.3 (50.4±6.3)	60.6±4.6 (49.7±4.5)	31.0±4.2 (24.5±4.1)
Leave-one-out	51.0±3.0 (50.3±2.3)	55.8±2.7 (50.0±2.6)	58.7±4.0 (50.3±1.6)	31.1±3.3 (25.2±1.4)

Table 5.7: Deep4Net





				
Individualized	51.5±5.0 (51.1±6.3)	55.4±5.7 (50.4±6.3)	56.6±4.5 (49.7±4.5)	33.0±4.1 (24.5±4.1)
Leave-one-out	51.5±2.7 (50.3±2.3)	56.4±3.1 (50.0±2.6)	58.6±3.8 (50.3±1.6)	30.1±2.2 (25.2±1.4)

Table 5.8: Rocket









				
Individualized	52.3±6.3 (51.1±6.3)	55.4±6.2 (50.4±6.3)	60.3±4.4 (49.7±4.5)	33.0±4.2 (24.5±4.1)
Leave-one-out	**53.3±2.6** (50.3±2.3)	55.8±2.9 (50.0±2.6)	**59.1±3.8** (50.3±1.6)	32.1±2.6 (25.2±1.4)

Table 5.9: Riemannian geometry

				
Individualized	51.0±6.3 (51.1±6.3)	56.6±6.6 (50.4±6.3)	61.5±4.5 (49.7±4.5)	31.8±4.2 (24.5±4.1)
Leave-one-out	52.1±2.6 (50.3±2.3)	**57.9±3.3** (50.0±2.6)	**59.1±3.8** (50.3±1.6)	**32.8±3.0** (25.2±1.4)

of the two, especially in the individualized setting where less data were available (see Table 5.4).
Additionally, to confirm the lack of any discriminable pattern related to sound direction in the last impulse, we trained the same WM + RF classifier on that portion of data. As can be seen in Table 5.12, the achieved performances are almost random.

Table 5.10: Approaching sounds only (WM + RF)





				
Individualized	52.5±9.2	55.1±8.7	60.2±5.9	33.3±6.1
Leave-one-out	51.7±3.9	55.8±3.6	58.3±4.2	31.3±2.9

Table 5.11: Receding sounds only (WM + RF)









				
Individualized	51.9±8.9	54.8±8.9	60.9±6.4	32.8±6.4
Leave-one-out	52.4±3.1	56.1±3.5	59.4±4.7	31.8±3.1





Table 5.12: Fourth response only (WM + RF)

				
Individualized	50.5±6.3 (51.1±6.3)	50.1±6.6 (50.4±6.3)	51.2±4.6 (49.7±4.5)	25.7±4.1 (24.5±4.1)
Leave-one-out	50.3±2.3 (50.3±2.3)	50.8±2.0 (50.0±2.6)	51.0±1.9 (50.3±1.6)	26.1±1.3 (25.2±1.4)

5.4 Conclusions

Based on the physiological investigation and the classification performances, we will draw in this section the conclusions concerning the research questions

Table 5.13: Onset responses to sounds that varied direction (WM + RF)

				
Individualized	51.4±7.2	56.5±7.2	63.0±5.0	34.3±4.9
Leave-one-out	52.5±3.5	57.5±3.5	63.0±5.0	32.8±3.5

at the origin of this study.

Although statistically significant patterns comparable to the ones identified in the pilot study have been confirmed also in the main experiment with a larger population, and despite the larger number of available trials and the adoption of state-of-the-art deep learning models, a decrease in classification accuracy has been experienced in all training conditions (varying localization configuration, dataset composition and machine learning model) apart the "lateral vs longitudinal" configuration. Unexpectedly large drops in the "front vs rear" and "left vs right" configurations have been observed. This result clashes with the hypotheses of replicability of the results achieved in the other benchmark studies, and with the hypotheses of any peculiarity of rear sounds resulting in characteristic EEG responses allowing a precise discrimination.

All in all, apart from the random "front vs rear", all localization configurations provided results greater than the random chance baseline, but the only configuration providing meaningful single-trial discrimination, although currently far from a usable in real world scenarios, has proved to be the "lateral vs longitudinal" one. Even more importantly, it exhibited statistically significant generalization power, independent from sound intensity, across participants of the considered population despite the obvious anatomical differences.

A clear (foreseen) limitation of the designed protocol is the lack of a sufficiently large number of trials requiring active sound localization, allowing to determine whether the drop of classification accuracy is due to the different engagement of the proposed task. To include both active and passive localization tasks in the protocol would either have to reduce the number of trials per direction, avoid the different motion patterns, or increase the acquisition duration (which was already at its acceptance limit). An investigation of this question is postponed to future experiments.

Concerning radial sound motion perception, no statistically significant effects have been identified in the ERP responses to the last impulse of the employed sound burst, namely where the largest accumulated perception of sound motion should be present, compared to static sounds presented at the same distance. Moreover, random accuracies have been obtained in classifying the sound direction based on this last ERP response. Together, these results reject the hypothesized any EEG pattern reflecting sound motion perception, at least in the currently investigated experimental setting.
In general, all statistically significant direction-related patterns have been identified in the larger onset responses since a clear drop of ERP peak amplitudes has been experienced in the subsequent three responses which, in turn, exhibited a stable and equal amplitude. This pattern suggests an underlying direction-related habituation process, which is evident also in the most discriminable localization configuration ("lateral vs longitudinal"). On the other hand, sound intensity is encoded also in EEG responses other than the onset (see Figure 5.11). Even though these subsequent responses are characterized by reduced amplitudes also in presence of intensity variations, statistically significant intensity-dependent differences are identified in subsequent responses. Based on these results, we speculate that the underlying habituation could influence spatial processing and not intensity perception. Indeed, investigating possible "long" (between semantically unrelated trials) direction-dependent habituation effects, we discovered that lateral sounds, and not longitudinal ones, elicit statistically significant differences in the ERP responses to consecutive sounds coming from the same direction and sounds coming from different directions. Also in case of "short" (between semantically related onset and subsequent response) direction-dependent habituation effects we found a different population-wide pattern between lateral and longitudinal sounds. In our opinion, although not relevant for the goal of discriminating sound directions from EEG signals, this effect seems worth further investigation.

Chapter 6

Conclusions and future work

In this Chapter, we draw the conclusions of this thesis. First we discuss the main results that have been achieved, highlighting novelty, impact and limitations (Section 6.1). Then, we draft future research directions (Section 6.2).

Overall research objectives: *The ultimate goal of this thesis was the identification of robust and general (population-wide) brain patterns allowing to classify the direction of a sound from single-trial EEG responses in realistic conditions. A complementary, preparatory, goal was the implementation of a portable hardware and software infrastructure allowing to investigate fully synchronized psychophysiological responses in real driving conditions. In particular, the infrastructure had to allow fully synchronized multi-source acquisitions as well as the effortless (automatic) deployment of the designed solutions for real-time inference.*

6.1 Main results

An accurate classification of the perceived sound direction would be strategic for several applications, in particular in the automotive industry. For

instance, interior and exterior artificial vehicle sounds, such as spatial warning sounds, could be optimally designed leveraging the objective insights of such classification without having to rely on subjective questionnaires. Moreover, the spatial perception of both drivers and pedestrians could be perpetually monitored to intervene avoiding accidents in case of misperceptions. To effectively investigate and deploy such solutions, a suitable infrastructure is of paramount importance but, unfortunately, no single general portable and reliable solution for in-vehicle EEG investigations is, to our knowledge, available. In this regards, a first relevant result is the successful in-vehicle validation of the designed infrastructure presented in Chapter 4. Not only the implemented infrastructure allowed to robustly collect high-quality signals and to use them to control a dummy menu application while driving, it also achieved statistically significant general results, even with totally unseen participants.

In its current version, the infrastructure is unavoidably affected by some limitations. The main ones are the poor wireless connectivity module which produces unsatisfactorily high trial rejection rates due to packet losses, and the need of external PCs in case medically certified EEG systems are to be used, wasting its portability strength.

The main thesis result though, is the identification and single-trial exploitation of a population-wide pattern underlying the discrimination between lateral and longitudinal sounds. Unfortunately we failed to identify EEG patterns allowing to classify individual directions with sufficient confidence, but the brain pattern associated with the "lateral vs longitudinal" condition represents a promising starting point, especially considering the single-trial across-participants classification performances that have been achieved. Unexpectedly, we identified also a complementary habituation effect associated to lateral and longitudinal sound directions consisting in the presence of statistically significant differences between subsequent sounds coming from the same direction and from different directions only in case of lateral sounds, and not in case of longitudinal sounds.

A key limitation of these results is the strong susceptibility of the underlying cerebral spatial processing to the context (e.g, engagement in an active sound localization task against passive listening), which has been highlighted by the discrepancies between pilot study and main experiment. Moreover, although statistically significant, the single-trial population-wide classification accuracies are still far from usable in the real life.

6.2 Future directions

This thesis constitutes a small step towards the decoding of spatial perception from EEG measurements. The proposed methodology is original, but is still affected by limitations that could be tackled in future studies. Infrastructure robustness and classification performances are evident examples.
Additionally, perception of sound motion speed could be investigated, adding a third discriminating variable to the protocol implemented in the main experiment. Then, a deeper investigation of the discovered habituation effect seems worth the effort.
Finally, a validation of the single-trial discrimination associated with the "lateral vs longitudinal" configuration confirming the achieved performances also in real driving condition would allow to properly conclude this thesis work according to the predefined real-world usability goals.

Bibliography

[1] J. Kropotov, *Quantitative EEG, Event-Related Potentials and Neurotherapy*, 01 2009.

[2] J. Wunderlich, B. Cone, and R. Shepherd, "Maturation of the cortical auditory evoked potential in infants and young children," *Hearing research*, vol. 212, pp. 185–202, 02 2006.

[3] D. R. Pereira, S. Cardoso, F. Ferreira-Santos, C. Fernandes, C. Cunha-Reis, T. O. Paiva, P. R. Almeida, C. Silveira, F. Barbosa, and J. Marques-Teixeira, "Effects of inter-stimulus interval (isi) duration on the n1 and p2 components of the auditory event-related potential," *International Journal of Psychophysiology*, vol. 94, no. 3, pp. 311–318, 2014.

[4] A. Burkhard, S. Elmer, and L. Jäncke, "Early tone categorization in absolute pitch musicians is subserved by the right-sided perisylvian brain," *Scientific reports*, vol. 9, no. 1, pp. 1–14, 2019.

[5] W. Ritter, H. G. Vaughan, and L. D. Costa, "Orienting and habituation to auditory stimuli: A study of short terms changes in average evoked responses," *Electroencephalography and Clinical Neurophysiology*, vol. 25, no. 6, pp. 550–556, 1968.

[6] H. R. Overbye K, Bøen R and T. C, "Learning from mistakes: How does the brain handle errors?," 2020.

[7] C. Valzolgher, *Active listening in sound localization: Multisensory and motor contributions to perceiving and re-learning the auditory space*, Ph.D. thesis, University of Trento, 2021.

[8] S. R. Arnott, M. A. Binns, C. L. Grady, and C. Alain, "Assessing the auditory dual-pathway model in humans," *NeuroImage*, vol. 22, no. 1, pp. 401–408, 2004.

[9] J. P. Rauschecker, "Where, when, and how: Are they all sensorimotor? towards a unified view of the dorsal pathway in vision and audition," *Cortex*, vol. 98, pp. 262–268, 2018.

[10] M. Brunetti, P. Belardinelli, M. Caulo, C. Del Gratta, S. Della Penna, A. Ferretti, G. Lucci, A. Moretti, V. Pizzella, A. Tartaro, K. Torquati, M. Olivetti Belardinelli, and G. Romani, "Human brain activation during passive listening to sounds from different locations: An fmri and meg study," *Human Brain Mapping*, vol. 26, no. 4, pp. 251–261, 2005.

[11] G. Rabini, *Hearing sounds in space: A neuro-cognitive investigation on the ability to associate auditory cues with external space*, Ph.D. thesis, University of Trento, 2019.

[12] M. A. Gerzon, "Ambisonics. part two: Studio techniques," *studio sound*, vol. 17, no. 8, pp. 24–26, 1975.

[13] R. Robart, E. Parizet, J.-C. CHAMARD, K. JANSSENS, F. Biancardi, J. Schlittenlacher, W. Ellermeier, P. Pondrom, J. Cockram, P. Speed-Andrews, and G. Hatton, "eVADER: A Perceptual Approach to Finding Minimum Warning Sound Requirements for Quiet Cars.," in *AIA-DAGA 2013 Conference on Acoustics*, Merano, Italy, 2013, p. 1.

[14] L. Chuen, D. Sears, and S. McAdams, "Psychophysiological responses to auditory change," *Psychophysiology*, vol. 53, no. 6, pp. 891–904, 2016.

[15] J. P. Rauschecker, "Parallel processing in the auditory cortex of primates," *Audiology and Neurotology*, vol. 3, no. 2-3, pp. 86–103, 1998.

[16] J. P. Rauschecker and B. Tian, "Mechanisms and streams for processing of "what" and "where" in auditory cortex," *Proceedings of the National Academy of Sciences*, vol. 97, no. 22, pp. 11800–11806, 2000.

[17] J. K. Bizley and Y. E. Cohen, "The what, where and how of auditory-object perception," *Nature Reviews Neuroscience*, vol. 14, no. 10, pp. 693–707, 2013.

[18] J. Ahveninen, N. Kopčo, and I. P. Jääskeläinen, "Psychophysics and neuronal bases of sound localization in humans," *Hearing Research*, vol. 307, pp. 86–97, 2014, Human Auditory NeuroImaging.

[19] K. van der Heijden, J. P. Rauschecker, B. de Gelder, and E. Formisano, "Cortical mechanisms of spatial hearing," *Nature Reviews Neuroscience*, vol. 20, no. 10, pp. 609–623, 2019.

[20] C. Alain, S. R. Arnott, S. Hevenor, S. Graham, and C. L. Grady, ""what" and "where" in the human auditory system," *Proceedings of the national academy of sciences*, vol. 98, no. 21, pp. 12301–12306, 2001.

[21] L. De Santis, S. Clarke, and M. M. Murray, "Automatic and intrinsic auditory "what" and "where" processing in humans revealed by electrical neuroimaging," *Cerebral Cortex*, vol. 17, no. 1, pp. 9–17, 2007.

[22] R. J. Zatorre, M. Bouffard, P. Ahad, and P. Belin, "Where is' where'in the human auditory cortex?," *Nature neuroscience*, vol. 5, no. 9, pp. 905–909, 2002.

[23] Y. E. Cohen and C. M. Wessinger, "Who goes there?," *Neuron*, vol. 24, no. 4, pp. 769–771, 1999.

[24] J. Lewald and S. Getzmann, "When and where of auditory spatial processing in cortex: a novel approach using electrotomography," *PLoS One*, vol. 6, no. 9, pp. e25146, 2011.

[25] Y. Liang, B. Liu, X. Li, P. Wang, and B. Wang, "Revealing the differences of the representations of sounds from different directions in the human brain using functional connectivity," *Neuroscience Letters*, vol. 718, pp. 134746, 2020.

[26] A. F. Cabrera and P. F. Hoffmann, "Single-trial classification of auditory event-related potentials elicited by stimuli from different spatial directions," in *2010 Annual International Conference of the IEEE Engineering in Medicine and Biology*, 2010, pp. 5807–5810.

[27] C. A. A. Moreno, V. Manian, D. Rodriguez, and J. Valera, "Auditory source localization by time frequency analysis and classification of electroencephalogram signals," *Biomedical Journal of Scientific Technical Research*, vol. 19, no. 5, pp. 14595–14606, 2019.

[28] A. Bednar, F. M. Boland, and E. C. Lalor, "Different spatio-temporal electroencephalography features drive the successful decoding of binaural and monaural cues for sound localization," *European Journal of Neuroscience*, vol. 45, no. 5, pp. 679–689, 2017.

[29] H. J. Team, "Human brain anatomy and function," Sep 2018.

[30] S. F. Witelson, "The brain connection: The corpus callosum is larger in left-handers," *Science*, vol. 229, no. 4714, pp. 665–668, 1985.

[31] S. Zhang, *Reading the brain's personality: using machine learning to investigate the relationships between EEG and depressivity*, Ph.D. thesis, University of Otago, 2020.

[32] J. Moini and P. Piran, "Chapter 6 - cerebral cortex," in *Functional and Clinical Neuroanatomy*, J. Moini and P. Piran, Eds., pp. 177–240. Academic Press, 2020.

[33] D. T. Stuss and D. F. Benson, "Neuropsychological studies of the frontal lobes.," 1984.

[34] D. T. Stuss, "Functions of the frontal lobes: Relation to executive functions," *Journal of the International Neuropsychological Society*, vol. 17, no. 5, pp. 759–765, 2011.

[35] D. Y. Kimberg and M. J. Farah, "A unified account of cognitive impairments following frontal lobe damage: the role of working memory in complex, organized behavior.," *Journal of experimental psychology. General*, vol. 122 4, pp. 411–28, 1993.

[36] S. Teitti, S. Määttä, L. Säisänen, M. Könönen, R. Vanninen, H. Hannula, E. Mervaala, and J. Karhu, "Non-primary motor areas in the human frontal lobe are connected directly to hand muscles," *NeuroImage*, vol. 40, pp. 1243–1250, 2008.

[37] L. Bianchi, "The functions of the frontal lobes," *Brain*, vol. 18, pp. 497–522, 1895.

[38] D. T. Stuss, C. Gow, and C. R. Hetherington, ""no longer gage": frontal lobe dysfunction and emotional changes.," *Journal of consulting and clinical psychology*, vol. 60 3, pp. 349–59, 1992.

[39] A. Dietrich, "The cognitive neuroscience of creativity," *Psychonomic Bulletin & Review*, vol. 11, pp. 1011–1026, 2004.

[40] A. Flinker, A. Korzeniewska, A. Y. Shestyuk, P. J. Franaszczuk, N. F. Dronkers, R. T. Knight, and N. E. Crone, "Redefining the role of broca's area in speech," *Proceedings of the National Academy of Sciences*, vol. 112, no. 9, pp. 2871–2875, 2015.

[41] D. Kimura, "Some effects of temporal-lobe damage on auditory perception.," *Canadian journal of psychology*, vol. 15, pp. 156–65, 1961.

[42] E. T. Rolls, "Functions of the primate temporal lobe cortical visual areas in invariant visual object and face recognition," *Neuron*, vol. 27, pp. 205–218, 2000.

[43] M. M. Haglund, M. S. Berger, M. Shamseldin, E. Lettich, and G. A. Ojemann, "Cortical localization of temporal lobe language sites in patients with gliomas.," *Neurosurgery*, vol. 34, pp. 567–576, 1994.

[44] R. Joseph, *The Occipital Lobe*, pp. 233–245, Springer US, Boston, MA, 1990.

[45] G. Buzsáki, C. Anastassiou, and C. Koch, "The origin of extracellular fields and currents—eeg, ecog, lfp and spikes," *Nature reviews. Neuroscience*, vol. 13, pp. 407–20, 05 2012.

[46] S. J. Luck, *An introduction to the event-related potential technique.*, MIT Press, Cambridge, MA, 2005.

[47] B. Fisch and R. Spehlmann, *Fisch and Spehlmann's EEG Primer: Basic Principles of Digital and Analog EEG*, Elsevier, 1999.

[48] D. Silverman, "The rationale and history of the 10-20 system of the international federation," *American Journal of EEG Technology*, vol. 3, no. 1, pp. 17–22, 1963.

[49] G. Schalk and J. Mellinger, *A Practical Guide to Brain-Computer Interfacing with BCI2000*, 01 2010.

[50] L. Greenfield, J. Geyer, and P. Carney, *Reading EEGs: A Practical Approach*, Wolters Kluwer Health, 2012.

[51] S. Beniczky and D. Schomer, "Electroencephalography: basic biophysical and technological aspects important for clinical applications," *Epileptic disorders : international epilepsy journal with videotape*, vol. 22, 12 2020.

[52] K. A. Ludwig, R. M. Miriani, N. B. Langhals, M. D. Joseph, D. J. Anderson, and D. R. Kipke, "Using a common average reference to improve cortical neuron recordings from microelectrode arrays," *Journal of neurophysiology*, vol. 101, no. 3, pp. 1679–1689, 2009.

[53] E. Basar, C. Basar-Eroglu, S. Karakas, and M. Schurmann, "Oscillatory brain theory: a new trend in neuroscience," *IEEE Engineering in Medicine and Biology Magazine*, vol. 18, no. 3, pp. 56–66, 1999.

[54] G. Buzsaki, *Rhythms of the Brain*, Oxford University Press, 2006.

[55] N. Kopell, M. A. Kramer, P. Malerba, and M. A. Whittington, "Are different rhythms good for different functions?," *Frontiers in human neuroscience*, vol. 4, pp. 187, 2010.

[56] X.-J. Wang, "Neurophysiological and computational principles of cortical rhythms in cognition," *Physiological reviews*, vol. 90, no. 3, pp. 1195–1268, 2010.

[57] G. Buzsáki and A. Draguhn, "Neuronal oscillations in cortical networks," *Science (New York, N.Y.)*, vol. 304, pp. 1926–9, 07 2004.

[58] B. Lega, J. Jacobs, and M. Kahana, "Human hippocampal theta oscillations and the formation of episodic memories," *Hippocampus*, vol. 22, pp. 748–61, 04 2012.

[59] P. Sauseng, J. Hoppe, W. Klimesch, C. Gerloff, and F. Hummel, "Dissociation of sustained attention from central executive functions: Local activity and interregional connectivity in the theta range," *The European journal of neuroscience*, vol. 25, pp. 587–93, 02 2007.

[60] P. Fries, "Neuronal gamma-band synchronization as a fundamental process in cortical computation," *Annual review of neuroscience*, vol. 32, pp. 209–24, 04 2009.

[61] M. G. WOLDORFF, "Distortion of erp averages due to overlap from temporally adjacent erps: Analysis and correction," *Psychophysiology*, vol. 30, no. 1, pp. 98–119, 1993.

[62] T. W. PICTON, "Human event-related potentials," *Handbook of Electroencephalography and Clinical Neurophysiology Revised Series*, vol. 3, 1988.

[63] J. I. Auñón, C. D. Mcgillem, and D. G. Childers, "Signal processing in evoked potential research: averaging and modeling.," *Critical reviews in bioengineering*, vol. 5 4, pp. 323–67, 1981.

[64] T. W. Picton, S. Bentin, P. Berg, E. Donchin, S. A. Hillyard, R. Johnson, G. A. Miller, W. Ritter, D. S. Ruchkin, M. Rugg, and M. J. Taylor, "Guidelines for using human event-related potentials to study cognition: recording standards and publication criteria.," *Psychophysiology*, vol. 37 2, pp. 127–52, 2000.

[65] G. F. Woodman, "A brief introduction to the use of event-related potentials in studies of perception and attention.," *Attention, perception & psychophysics*, vol. 72 8, pp. 2031–46, 2010.

[66] M. A. B. Brazier, "Evoked responses recorded from the depths of the human brain," *Annals of the New York Academy of Sciences*, vol. 112, 1964.

[67] F. D. Russo, A. Martínez, M. I. Sereno, S. Pitzalis, and S. A. Hillyard, "Cortical sources of the early components of the visual evoked potential," *Human Brain Mapping*, vol. 15, 2002.

[68] T. W. Picton, C. E. Alain, D. L. Woods, M. S. John, M. Scherg, P. A. Valdés-Sosa, J. Bosch-Bayard, and N. J. Trujillo, "Intracerebral sources of human auditory-evoked potentials," *Audiology and Neurotology*, vol. 4, pp. 64 – 79, 1999.

[69] E. DONCHIN, W. RITTER, and W. C. MCCALLUM, "Cognitive psychophysiology: The endogenous components of the erp," in *Event-Related Brain Potentials in Man*, E. Callaway, P. Tueting, and S. H. Koslow, Eds., pp. 349–411. Academic Press, 1978.

[70] S. Baillet, J. Mosher, and R. Leahy, "Electromagnetic brain mapping," *IEEE Signal Processing Magazine*, vol. 18, no. 6, pp. 14–30, 2001.

[71] M. Scherg et al., "Fundamentals of dipole source potential analysis," *Auditory evoked magnetic fields and electric potentials. Advances in audiology*, vol. 6, pp. 40–69, 1990.

[72] A. M. Dale and M. I. Sereno, "Improved localizadon of cortical activity by combining eeg and meg with mri cortical surface reconstruction: A linear approach," *Journal of Cognitive Neuroscience*, vol. 5, pp. 162–176, 1993.

[73] M. S. Hämäläinen, R. Hari, R. J. Ilmoniemi, J. Knuutila, and O. V. Lounasmaa, "Magnetoencephalography-theory, instrumentation, and applications to noninvasive studies of the working human brain," *Reviews of Modern Physics*, vol. 65, pp. 413–497, 1993.

[74] L. A. Farwell and E. Donchin, "The truth will out: Interrogative polygraphy ("lie detection") with event-related brain potentials," *Psychophysiology*, vol. 28, no. 5, pp. 531–547, 1991.

[75] V. Abootalebi, M. H. Moradi, and M. A. Khalilzadeh, "A new approach for eeg feature extraction in p300-based lie detection," *Computer Methods and Programs in Biomedicine*, vol. 94, no. 1, pp. 48–57, 2009.

[76] B. N. Cuthbert, H. T. Schupp, M. M. Bradley, N. Birbaumer, and P. J. Lang, "Brain potentials in affective picture processing: covariation with

autonomic arousal and affective report," *Biological Psychology*, vol. 52, no. 2, pp. 95–111, 2000.

[77] D. Foti, G. Hajcak, and J. Dien, "Differentiating neural responses to emotional pictures: Evidence from temporal-spatial pca," *Psychophysiology*, vol. 46, no. 3, pp. 521–530, 2009.

[78] A. Keil, M. M. Müller, T. Gruber, C. Wienbruch, M. Stolarova, and T. Elbert, "Effects of emotional arousal in the cerebral hemispheres: a study of oscillatory brain activity and event-related potentials," *Clinical Neurophysiology*, vol. 112, no. 11, pp. 2057–2068, 2001.

[79] A. KEIL, M. M. BRADLEY, O. HAUK, B. ROCKSTROH, T. ELBERT, and P. J. LANG, "Large-scale neural correlates of affective picture processing," *Psychophysiology*, vol. 39, no. 5, pp. 641–649, 2002.

[80] H. Schupp, B. Cuthbert, M. Bradley, C. Hillman, A. Hamm, and P. Lang, "Brain processes in emotional perception: Motivated attention," *Cognition and Emotion*, vol. 18, no. 5, pp. 593–611, 2004.

[81] J. K. Olofsson and J. Polich, "Affective visual event-related potentials: Arousal, repetition, and time-on-task," *Biological Psychology*, vol. 75, no. 1, pp. 101–108, 2007.

[82] S. Delplanque, M. E. Lavoie, P. Hot, L. Silvert, and H. Sequeira, "Modulation of cognitive processing by emotional valence studied through event-related potentials in humans," *Neuroscience Letters*, vol. 356, no. 1, pp. 1–4, 2004.

[83] A. Weinberg and G. Hajcak, "Beyond good and evil: the time-course of neural activity elicited by specific picture content.," *Emotion*, vol. 10 6, pp. 767–82, 2010.

[84] M. JUNGHÖFER, M. M. BRADLEY, T. R. ELBERT, and P. J. LANG, "Fleeting images: A new look at early emotion discrimination," *Psychophysiology*, vol. 38, no. 2, pp. 175–178, 2001.

[85] V. S. Johnston, D. R. Miller, and M. H. Burleson, "Multiple p3s to emotional stimuli and their theoretical significance," *Psychophysiology*, vol. 23, no. 6, pp. 684–694, 1986.

[86] D. Palomba, A. Angrilli, and A. Mini, "Visual evoked potentials, heart rate responses and memory to emotional pictorial stimuli," *International Journal of Psychophysiology*, vol. 27, no. 1, pp. 55–67, 1997.

[87] D. Foti and G. Hajcak, "Deconstructing Reappraisal: Descriptions Preceding Arousing Pictures Modulate the Subsequent Neural Response," *Journal of Cognitive Neuroscience*, vol. 20, no. 6, pp. 977–988, 06 2008.

[88] G. Hajcak, J. S. Moser, and R. F. Simons, "Attending to affect: appraisal strategies modulate the electrocortical response to arousing pictures.," *Emotion*, vol. 6 3, pp. 517–22, 2006.

[89] G. Hajcak, J. P. Dunning, and D. Foti, "Neural response to emotional pictures is unaffected by concurrent task difficulty: an event-related potential study.," *Behavioral neuroscience*, vol. 121 6, pp. 1156–62, 2007.

[90] G. Hajcak and D. M. Olvet, "The persistence of attention to emotion: brain potentials during and after picture presentation.," *Emotion*, vol. 8 2, pp. 250–5, 2008.

[91] K. E. Briggs and F. H. Martin, "Affective picture processing and motivational relevance: Arousal and valence effects on erps in an oddball task," *International Journal of Psychophysiology*, vol. 72, no. 3, pp. 299–306, 2009.

[92] G. R. Mangun, "Neural mechanisms of visual selective attention.," *Psychophysiology*, vol. 32 1, pp. 4–18, 1995.

[93] S. K. David E. Meyer, "Electrocortical Substrates of Visual Selective Attention," in *Attention and Performance XIV: Synergies in Experimental Psychology, Artificial Intelligence, and Cognitive Neuroscience*. The MIT Press, 04 1993.

[94] S. A. Hillyard, E. K. Vogel, and S. J. Luck, "Sensory gain control (amplification) as a mechanism of selective attention: electrophysiological and neuroimaging evidence.," *Philosophical transactions of the Royal Society of London. Series B, Biological sciences*, vol. 353 1373, pp. 1257–70, 1998.

[95] S. J. Luck, G. F. Woodman, and E. K. Vogel, "Event-related potential studies of attention," *Trends in Cognitive Sciences*, vol. 4, no. 11, pp. 432–440, 2000.

[96] E. K. VOGEL and S. J. LUCK, "The visual n1 component as an index of a discrimination process," *Psychophysiology*, vol. 37, no. 2, pp. 190–203, 2000.

[97] S. J. Luck, S. A. Hillyard, M. Mouloua, M. G. Woldorff, V. Clark, and H. L. Hawkins, "Effects of spatial cuing on luminance detectability: Psychophysical and electrophysiological evidence for early selection.," *Journal of Experimental Psychology: Human Perception and Performance*, vol. 20, pp. 887–904, 1994.

[98] G. R. Mangun and S. A. Hillyard, "Modulations of sensory-evoked brain potentials indicate changes in perceptual processing during visual-spatial priming.," *Journal of experimental psychology. Human perception and performance*, vol. 17 4, pp. 1057–74, 1991.

[99] S. V. Voorhis and S. A. Hillyard, "Visual evoked potentials and selective attention to points in space," *Perception & Psychophysics*, vol. 22, pp. 54–62, 1977.

[100] W. Ritter, R. Simson, H. G. Vaughan, and D. Friedman, "A brain event related to the making of a sensory discrimination," *Science*, vol. 203, no. 4387, pp. 1358–1361, 1979.

[101] J.-M. Hopf, E. Vogel, G. Woodman, H.-J. Heinze, and S. J. Luck, "Localizing visual discrimination processes in time and space," *Journal of Neurophysiology*, vol. 88, no. 4, pp. 2088–2095, 2002, PMID: 12364530.

[102] R. Burkard, J. Eggermont, and M. Don, *Auditory Evoked Potentials: Basic Principles and Clinical Application*, Point (Lippincott Williams and Wilkins) Series. Lippincott Williams & Wilkins, 2007.

[103] A. Kral and J. J. Eggermont, "What's to lose and what's to learn: development under auditory deprivation, cochlear implants and limits of cortical plasticity," *Brain Research Reviews*, vol. 56, no. 1, pp. 259–269, 2007.

[104] T. W. Picton, *Human Auditory Evoked Potentials*, Plural Publishing, 2010.

[105] N. T. Haumann, M. Lumaca, M. Kliuchko, J. L. Santacruz, P. Vuust, and E. Brattico, "Extracting human cortical responses to sound onsets and acoustic feature changes in real music, and their relation to event rate," *Brain Research*, vol. 1754, pp. 147248, 2021.

[106] R. Näätänen and T. Picton, "The n1 wave of the human electric and magnetic response to sound: a review and an analysis of the component structure," *Psychophysiology*, vol. 24, no. 4, pp. 375–425, 1987.

[107] B. Lütkenhöner and O. Steinsträter, "High-precision neuromagnetic study of the functional organization of the human auditory cortex," *Audiology and Neurotology*, vol. 3, pp. 191 – 213, 1998.

[108] B. Ross and K. Tremblay, "Stimulus experience modifies auditory neuromagnetic responses in young and older listeners," *Hearing Research*, vol. 248, pp. 48–59, 2009.

[109] T. S. Mattsson, O. Lind, T. Follestad, K. Grøndahl, W. Wilson, J. Nicholas, S. Nordgård, and S. Andersson, "Electrophysiological characteristics in children with listening difficulties, with or without auditory processing disorder," *International Journal of Audiology*, vol. 58, no. 11, pp. 704–716, 2019, PMID: 31154863.

[110] P. Kummer, M. Burger, M. Schuster, F. Rosanowski, U. Eysholdt, and U. Hoppe, "Cortical auditory evoked potentials to acoustic changes in speech stimuli in children," *Folia Phoniatrica et Logopaedica*, vol. 59, no. 5, pp. 273–280, 2007.

[111] J. M. Ostroff, B. A. Martin, and A. Boothroyd, "Cortical evoked response to acoustic change within a syllable," *Ear and hearing*, vol. 19, no. 4, pp. 290–297, 1998.

[112] C. Liegeois-Chauvel, A. Musolino, J. Badier, P. Marquis, and P. Chauvel, "Evoked potentials recorded from the auditory cortex in man: evaluation and topography of the middle latency components," *Electroencephalography and Clinical Neurophysiology/Evoked Potentials Section*, vol. 92, no. 3, pp. 204–214, 1994.

[113] D. L. Woods et al., "The component structure of the n 1 wave of the human auditory evoked potential," *Electroencephalography and Clinical Neurophysiology-Supplements Only*, vol. 44, pp. 102–109, 1995.

[114] I. Winkler, S. L. Denham, and I. Nelken, "Modeling the auditory scene: predictive regularity representations and perceptual objects," *Trends in Cognitive Sciences*, vol. 13, no. 12, pp. 532–540, 2009.

[115] R. Näätänen and I. Winkler, "The concept of auditory stimulus representation in cognitive neuroscience.," *Psychological bulletin*, vol. 125, no. 6, pp. 826, 1999.

[116] M. G. Woldorff, C. C. Gallen, S. A. Hampson, S. A. Hillyard, C. Pantev, D. Sobel, and F. E. Bloom, "Modulation of early sensory processing in human auditory cortex during auditory selective attention," *Proceedings of the National Academy of Sciences*, vol. 90, no. 18, pp. 8722–8726, 1993.

[117] F. Alías, J. C. Socoró, and X. Sevillano, "A review of physical and perceptual feature extraction techniques for speech, music and environmental sounds," *Applied Sciences*, vol. 6, no. 5, pp. 143, 2016.

[118] T. O. Paiva, P. R. Almeida, F. Ferreira-Santos, J. B. Vieira, C. Silveira, P. L. Chaves, F. Barbosa, and J. Marques-Teixeira, "Similar sound intensity dependence of the n1 and p2 components of the auditory erp: Averaged and single trial evidence," *Clinical Neurophysiology*, vol. 127, no. 1, pp. 499–508, 2016.

[119] W. Han, "P1-n1-p2 complex and acoustic change complex elicited by speech sounds: current research and applications," *Audiology and Speech Research*, vol. 6, no. 2, pp. 121–127, 2010.

[120] E. Sussman, M. Steinschneider, V. Gumenyuk, J. Grushko, and K. Lawson, "The maturation of human evoked brain potentials to sounds presented at different stimulus rates," *Hearing research*, vol. 236, no. 1-2, pp. 61–79, 2008.

[121] A. L. Wang, A. Mouraux, M. Liang, and G. D. Iannetti, "The enhancement of the n1 wave elicited by sensory stimuli presented at very short inter-stimulus intervals is a general feature across sensory systems," *PloS one*, vol. 3, no. 12, pp. e3929, 2008.

[122] H. Davis, T. Mast, N. Yoshie, and S. Zerlin, "The slow response of the human cortex to auditory stimuli: Recovery process," *Electroencephalography and Clinical Neurophysiology*, vol. 21, no. 2, pp. 105–113, 1966.

[123] D. A. Nelson and F. M. Lassman, "Effects of intersignal interval on the human auditory evoked response," *The Journal of the Acoustical Society of America*, vol. 44, no. 6, pp. 1529–1532, 1968.

[124] P. Belin, S. McAdams, B. Smith, S. Savel, L. Thivard, S. Samson, and Y. Samson, "The functional anatomy of sound intensity discrimination," *Journal of Neuroscience*, vol. 18, no. 16, pp. 6388–6394, 1998.

[125] L. Jäncke, N. J. Shah, S. Posse, M. Grosse-Ryuken, and H. W. Müller-Gärtner, "Intensity coding of auditory stimuli: an fmri study," *Neuropsychologia*, vol. 36, pp. 875–883, 1998.

[126] F. Mirz, T. Ovesen, K. Ishizu, P. Johannsen, S. Madsen, A. Gjedde, and C. B. Pedersen, "Stimulus-dependent central processing of auditory stimuli: a pet study," *Scandinavian Audiology*, vol. 28, no. 3, pp. 161–169, 1999.

[127] V. Menon, D. J. Levitin, B. K. Smith, A. Lembke, B. Krasnow, D. Glazer, G. H. Glover, and S. McAdams, "Neural correlates of timbre change in harmonic sounds," *Neuroimage*, vol. 17, no. 4, pp. 1742–1754, 2002.

[128] Y. Tong, R. D. Melara, and A. Rao, "P2 enhancement from auditory discrimination training is associated with improved reaction times," *Brain research*, vol. 1297, pp. 80–88, 2009.

[129] S. A. Hillyard and M. Kutas, "Electrophysiology of cognitive processing," *Annual Review of Psychology*, vol. 34, no. 1, pp. 33–61, 1983, PMID: 6338812.

[130] D. L. McPherson, *Late potentials of the auditory system*, Singular Publishing Group, 1996.

[131] S. Sutton, P. A. Tueting, J. Zubin, and E. R. John, "Information delivery and the sensory evoked potential," *Science*, vol. 155, pp. 1436 – 1439, 1967.

[132] A. Burkhard, S. Elmer, and L. Jäncke, "Early tone categorization in absolute pitch musicians is subserved by the right-sided perisylvian brain.," *Scientific Reports*, 02 2019.

[133] S. Onishi and H. Davis, "Effects of duration and rise time of tone bursts on evoked v potentials," *The Journal of the Acoustical Society of America*, vol. 44, no. 2, pp. 582–591, 1968.

[134] S. Elmer, S. Sollberger, M. Meyer, and L. Jäncke, "An empirical reevaluation of absolute pitch: behavioral and electrophysiological measurements," *Journal of cognitive neuroscience*, vol. 25, no. 10, pp. 1736–1753, 2013.

[135] H. G. Vaughan and W. Ritter, "The sources of auditory evoked responses recorded from the human scalp," *Electroencephalography and Clinical Neurophysiology*, vol. 28, no. 4, pp. 360–367, 1970.

[136] S. A. Hillyard and T. W. Picton, *Electrophysiology of Cognition*, pp. 519–584, John Wiley Sons, Ltd, 2011.

[137] S. Baumann, M. Meyer, and L. Jäncke, "Enhancement of auditory-evoked potentials in musicians reflects an influence of expertise but not selective attention," *Journal of cognitive neuroscience*, vol. 20, no. 12, pp. 2238–2249, 2008.

[138] M. Seppänen, J. Hämäläinen, A.-K. Pesonen, and M. Tervaniemi, "Music training enhances rapid neural plasticity of n1 and p2 source activation for unattended sounds," *Frontiers in Human Neuroscience*, vol. 6, pp. 43, 2012.

[139] A. Shahin, D. J. Bosnyak, L. J. Trainor, and L. E. Roberts, "Enhancement of neuroplastic p2 and n1c auditory evoked potentials in musicians," *Journal of Neuroscience*, vol. 23, no. 13, pp. 5545–5552, 2003.

[140] A. Shahin, L. E. Roberts, C. Pantev, L. J. Trainor, and B. Ross, "Modulation of p2 auditory-evoked responses by the spectral complexity of musical sounds," *Neuroreport*, vol. 16, no. 16, pp. 1781–1785, 2005.

[141] K. Tremblay, N. Kraus, T. McGee, C. Ponton, B. Otis, et al., "Central auditory plasticity: changes in the n1-p2 complex after speech-sound training," *Ear and hearing*, vol. 22, no. 2, pp. 79–90, 2001.

[142] M. Kutas and K. D. Federmeier, "Thirty years and counting: finding meaning in the n400 component of the event-related brain potential (erp)," *Annual review of psychology*, vol. 62, pp. 621–647, 2011.

[143] E. Dittinger, M. Barbaroux, M. d'Imperio, L. Jäncke, S. Elmer, and M. Besson, "Professional music training and novel word learning: From faster semantic encoding to longer-lasting word representations," *Journal of cognitive neuroscience*, vol. 28, no. 10, pp. 1584–1602, 2016.

[144] W. S. Pritchard, S. A. Shappell, and M. E. Brandt, "Psychophysiology of n200/n400: A review and classification scheme," in *Advances in Psychophysiology*, pp. 43–106. Jessica Kingsley, 1991.

[145] W. Ritter, P. Paavilainen, J. Lavikainen, K. Reinikainen, K. Alho, M. Sams, and R. Näätänen, "Event-related potentials to repetition and change of auditory stimuli," *Electroencephalography and Clinical Neurophysiology*, vol. 83, no. 5, pp. 306–321, 1992.

[146] M. Tervaniemi, V. Just, S. Koelsch, A. Widmann, and E. Schröger, "Pitch discrimination accuracy in musicians vs nonmusicians: an event-related potential and behavioral study," *Experimental brain research*, vol. 161, no. 1, pp. 1–10, 2005.

[147] D. van den Brink, C. M. Brown, and P. Hagoort, "Electrophysiological evidence for early contextual influences during spoken-word recognition: N200 versus n400 effects," *Journal of Cognitive Neuroscience*, vol. 13, pp. 967–985, 2001.

[148] M. Kutas and S. A. Hillyard, "Reading senseless sentences: Brain potentials reflect semantic incongruity," *Science*, vol. 207, no. 4427, pp. 203–205, 1980.

[149] M. Besson and M. Kutas, "The many facets of repetition: A cued-recall and event-related potential analysis of repeating words in same versus different sentence contexts.," *Journal of Experimental Psychology: Learning, Memory, and Cognition*, vol. 19, no. 5, pp. 1115, 1993.

[150] C. Wu, I. J. Kirk, J. P. Hamm, and V. K. Lim, "The neural networks involved in pitch labeling of absolute pitch musicians," *Neuroreport*, vol. 19, no. 8, pp. 851–854, 2008.

[151] A. Schirmer and S. A. Kotz, "Beyond the right hemisphere: brain mechanisms mediating vocal emotional processing," *Trends in Cognitive Sciences*, vol. 10, no. 1, pp. 24–30, 2006.

[152] S. Paulmann and S. A. Kotz, "Early emotional prosody perception based on different speaker voices," *Neuroreport*, vol. 19, no. 2, pp. 209–213, 2008.

[153] J. Chang, X. Zhang, Q. Zhang, and Y. Sun, "Investigating duration effects of emotional speech stimuli in a tonal language by using event-related potentials," *IEEE Access*, vol. 6, pp. 13541–13554, 2018.

[154] K. E. Crowley and I. M. Colrain, "A review of the evidence for p2 being an independent component process: age, sleep and modality," *Clinical Neurophysiology*, vol. 115, no. 4, pp. 732–744, 2004.

[155] H. Tiitinen, P. Sivonen, P. Alku, J. Virtanen, and R. Näätänen, "Electromagnetic recordings reveal latency differences in speech and tone processing in humans," *Cognitive Brain Research*, vol. 8, no. 3, pp. 355–363, 1999.

[156] I. J. Wambacq and J. F. Jerger, "Processing of affective prosody and lexical-semantics in spoken utterances as differentiated by event-related potentials," *Cognitive Brain Research*, vol. 20, no. 3, pp. 427–437, 2004.

[157] V. Bostanov and B. Kotchoubey, "Recognition of affective prosody: Continuous wavelet measures of event-related brain potentials to emotional exclamations," *Psychophysiology*, vol. 41, no. 2, pp. 259–268, 2004.

[158] S. Paulmann and M. D. Pell, "Contextual influences of emotional speech prosody on face processing: How much is enough?," *Cognitive, Affective, & Behavioral Neuroscience*, vol. 10, no. 2, pp. 230–242, 2010.

[159] S. Paulmann, M. Bleichner, and S. Kotz, "Valence, arousal, and task effects in emotional prosody processing," *Frontiers in Psychology*, vol. 4, pp. 345, 2013.

[160] L. Zhu, Q. Ma, X. Bai, and L. Hu, "Mechanisms behind hazard perception of warning signs: An eeg study," *Transportation Research Part F: Traffic Psychology and Behaviour*, vol. 69, pp. 362–374, 2020.

[161] J. Föcker and B. Röder, "Event-related potentials reveal evidence for late integration of emotional prosody and facial expression in dynamic stimuli: An erp study," *Multisensory research*, vol. 32, no. 6, pp. 473–497, 2019.

[162] A. Truman and L. Mudrik, "Are incongruent objects harder to identify? the functional significance of the n300 component," *Neuropsychologia*, vol. 117, pp. 222–232, 2018.

[163] J. P. Hamm, B. W. Johnson, and I. J. Kirk, "Comparison of the n300 and n400 erps to picture stimuli in congruent and incongruent contexts," *Clinical Neurophysiology*, vol. 113, no. 8, pp. 1339–1350, 2002.

[164] L.-I. Klatt, S. Getzmann, E. Wascher, and D. Schneider, "The contribution of selective spatial attention to sound detection and sound localization: Evidence from event-related potentials and lateralized alpha oscillations," *Biological Psychology*, vol. 138, pp. 133–145, 2018.

[165] R. Näätänen and A. Gaillard, "The orienting reflex and the n2 deflection of the event-related potential (erp)," in *Tutorials in Event Related Potential Research: Endogenous Components*, A. W. Gaillard and W. Ritter, Eds., vol. 10 of *Advances in Psychology*, pp. 119–141. North-Holland, 1983.

[166] E. Sokolov, "Orienting response," in *International Encyclopedia of the Social Behavioral Sciences*, N. J. Smelser and P. B. Baltes, Eds., pp. 10978–10981. Pergamon, Oxford, 2001.

[167] M. M. Bradley, "Natural selective attention: Orienting and emotion," *Psychophysiology*, vol. 46, no. 1, pp. 1–11, 2009.

[168] E. N. Sokolov, "A neuronal model of the stimulus in a reflex arc," *Soviet Psychology*, vol. 17, no. 2, pp. 3–22, 1978.

[169] R. Näätänen and T. W. Picton, "N2 and automatic versus controlled processes.," *Electroencephalography and clinical neurophysiology. Supplement*, vol. 38, pp. 169–86, 1986.

[170] "The mismatch negativity (mmn)," in *The Oxford Handbook of Event-Related Potential Components*, pp. 143–157. Oxford University Press, 2012.

[171] R. NÄÄTÄNEN, P. PAAVILAINEN, H. TITINEN, D. JIANG, and K. ALHO, "Attention and mismatch negativity," *Psychophysiology*, vol. 30, no. 5, pp. 436–450, 1993.

[172] E. Brattico, M. Tervaniemi, R. Näätänen, and I. Peretz, "Musical scale properties are automatically processed in the human auditory cortex," *Brain Research*, vol. 1117, no. 1, pp. 162–174, 2006.

[173] I. Czigler, L. Balázs, and I. Winkler, "Memory-based detection of task-irrelevant visual changes," *Psychophysiology*, vol. 39, no. 6, pp. 869–873, 2002.

[174] J. L. Kenemans, T. Grent, M. N. Verbaten, et al., "Detection of visual change: mismatch or rareness?," *Neuroreport*, vol. 14, no. 9, pp. 1239–1242, 2003.

[175] J. M. Ford and S. A. Hillyard, "Event-related potentials (erps) to interruptions of a steady rhythm," *Psychophysiology*, vol. 18, no. 3, pp. 322–330, 1981.

[176] J. Rüsseler, E. Altenmüller, W. Nager, C. Kohlmetz, and T. F. Münte, "Event-related brain potentials to sound omissions differ in musicians and non-musicians," *Neuroscience Letters*, vol. 308, no. 1, pp. 33–36, 2001.

[177] M. D. Comerchero and J. Polich, "P3a and p3b from typical auditory and visual stimuli," *Clinical Neurophysiology*, vol. 110, no. 1, pp. 24–30, 1999.

[178] J. Polich, "Updating p300: An integrative theory of p3a and p3b," *Clinical Neurophysiology*, vol. 118, no. 10, pp. 2128–2148, 2007.

[179] J. Polich, "Clinical application of the p300 event-related brain potential," *Physical Medicine and Rehabilitation Clinics*, vol. 15, no. 1, pp. 133–161, 2004.

[180] R. Fazel-Rezai, B. Z. Allison, C. Guger, E. W. Sellers, S. C. Kleih, and A. Kübler, "P300 brain computer interface: current challenges and emerging trends," *Frontiers in neuroengineering*, vol. 5, pp. 14, 2012.

[181] J. Polich, "Neuropsychology of p300," in *The Oxford handbook of event-related potential components*, pp. 159–188. Oxford University Press, 2012.

[182] N. K. Squires, K. C. Squires, and S. A. Hillyard, "Two varieties of long-latency positive waves evoked by unpredictable auditory stimuli in man," *Electroencephalography and clinical neurophysiology*, vol. 38, no. 4, pp. 387–401, 1975.

[183] J. Polich, "Theoretical overview of p3a and p3b," *Detection of change*, pp. 83–98, 2003.

[184] E. Donchin, "Surprise!... surprise?," *Psychophysiology*, vol. 18, no. 5, pp. 493–513, 1981.

[185] H. Levi-Aharoni, O. Shriki, and N. Tishby, "Surprise response as a probe for compressed memory states," *PLOS Computational Biology*, vol. 16, no. 2, pp. 1–21, 02 2020.

[186] J. B. Isreal, G. L. Chesney, C. D. Wickens, and E. Donchin, "P300 and tracking difficulty: Evidence for multiple resources in dual-task performance," *Psychophysiology*, vol. 17, no. 3, pp. 259–273, 1980.

[187] M. Kutas, G. McCarthy, and E. Donchin, "Augmenting mental chronometry: The p300 as a measure of stimulus evaluation time," *Science*, vol. 197, no. 4305, pp. 792–795, 1977.

[188] A. Magliero, T. R. Bashore, M. G. Coles, and E. Donchin, "On the dependence of p300 latency on stimulus evaluation processes," *Psychophysiology*, vol. 21, no. 2, pp. 171–186, 1984.

[189] E. Courchesne, S. A. Hillyard, and R. Galambos, "Stimulus novelty, task relevance and the visual evoked potential in man," *Electroencephalography and Clinical Neurophysiology*, vol. 39, no. 2, pp. 131–143, 1975.

[190] M. Soltani and R. T. Knight, "Neural origins of the p300," *Critical Reviewstrade; in Neurobiology*, vol. 14, no. 3-4, 2000.

[191] R. VERLEGER, P. JASKOWSKI, and B. WAUSCHKUHN, "Suspense and surprise: On the relationship between expectancies and p3," *Psychophysiology*, vol. 31, no. 4, pp. 359–369, 1994.

[192] W. S. Pritchard, "Psychophysiology of p300.," *Psychological bulletin*, vol. 89, no. 3, pp. 506, 1981.

[193] R. Johnson, "A triarchic model of p300 amplitude.," *Psychophysiology*, 1986.

[194] T. W. Picton, "The p300 wave of the human event-related potential," *Journal of Clinical Neurophysiology*, vol. 9, pp. 456–479, 1992.

[195] J. Polich and A. Kok, "Cognitive and biological determinants of p300: an integrative review," *Biological Psychology*, vol. 41, no. 2, pp. 103–146, 1995.

[196] C. C. Duncan-Johnson and E. Donchin, "On quantifying surprise: The variation of event-related potentials with subjective probability," *Psychophysiology*, vol. 14, no. 5, pp. 456–467, 1977.

[197] E. K. Vogel, S. J. Luck, and K. L. Shapiro, "Electrophysiological evidence for a postperceptual locus of suppression during the attentional blink.," *Journal of Experimental Psychology: Human Perception and Performance*, vol. 24, no. 6, pp. 1656, 1998.

[198] J. Polich, S. E. Eischen, and G. E. Collins, "P300 from a single auditory stimulus," *Electroencephalography and Clinical Neurophysiology/Evoked Potentials Section*, vol. 92, no. 3, pp. 253–261, 1994.

[199] J. Katayama and J. Polich, "P300 from one-, two-, and three-stimulus auditory paradigms," *International Journal of Psychophysiology*, vol. 23, no. 1, pp. 33–40, 1996.

[200] M. Kutas and K. D. Federmeier, "N400," *Scholarpedia*, vol. 4, no. 10, pp. 7790, 2009, revision #91546.

[201] S. M. Rhodes and D. I. Donaldson, "Association and not semantic relationships elicit the n400 effect: Electrophysiological evidence from an explicit language comprehension task," *Psychophysiology*, vol. 45, no. 1, pp. 50–59, 2008.

[202] P. J. Holcomb and W. B. Mcpherson, "Event-related brain potentials reflect semantic priming in an object decision task," *Brain and cognition*, vol. 24, no. 2, pp. 259–276, 1994.

[203] M. KUTAS, S. A. HILLYARD, and M. S. GAZZANIGA, "PROCESSING OF SEMANTIC ANOMALY BY RIGHT AND LEFT HEMISPHERES OF COMMISSUROTOMY PATIENTS: EVIDENCE FROM EVENT-RELATED BRAIN POTENTIALS," *Brain*, vol. 111, no. 3, pp. 553–576, 06 1988.

[204] P. Hagoort, C. M. Brown, and T. Y. Swaab, "Lexical—semantic event–related potential effects in patients with left hemisphere lesions and aphasia, and patients with right hemisphere lesions without aphasia," *Brain*, vol. 119, no. 2, pp. 627–649, 1996.

[205] G. McCarthy, A. C. Nobre, S. Bentin, and D. D. Spencer, "Language-related field potentials in the anterior-medial temporal lobe: I. intracranial distribution and neural generators," *Journal of neuroscience*, vol. 15, no. 2, pp. 1080–1089, 1995.

[206] W. Gehring, Y. Liu, J. Orr, and J. Carp, "The error-related negativity (ern/ne)," in *The Oxford handbook of event-related potential components*, pp. 231–292. Oxford University Press, 2012.

[207] W. J. Gehring, B. M. Goss, M. G. H. Coles, D. E. Meyer, and E. Donchin, "A neural system for error detection and compensation," *Psychological Science*, vol. 4, pp. 385 – 390, 1993.

[208] M. K. Scheffers and M. G. H. Coles, "Performance monitoring in a confusing world: error-related brain activity, judgments of response accuracy, and types of errors.," *Journal of experimental psychology. Human perception and performance*, vol. 26 1, pp. 141–151, 2000.

[209] M. Falkenstein, J. Hoormann, S. Christ, and J. Hohnsbein, "Erp components on reaction errors and their functional significance: a tutorial," *Biological Psychology*, vol. 51, no. 2, pp. 87–107, 2000.

[210] G. Hajcak, "What we've learned from mistakes: Insights from error-related brain activity," *Current Directions in Psychological Science*, vol. 21, no. 2, pp. 101–106, 2012.

[211] A. Gentsch, P. Ullsperger, and M. Ullsperger, "Dissociable medial frontal negativities from a common monitoring system for self- and externally caused failure of goal achievement," *NeuroImage*, vol. 47, pp. 2023–2030, 2009.

[212] T. Endrass, B. Reuter, and N. Kathmann, "Erp correlates of conscious error recognition: aware and unaware errors in an antisaccade task," *European Journal of Neuroscience*, vol. 26, no. 6, pp. 1714–1720, 2007.

[213] S. Nieuwenhuis, K. R. Ridderinkhof, J. Blom, G. P. Band, and A. Kok, "Error-related brain potentials are differentially related to awareness of response errors: evidence from an antisaccade task," *Psychophysiology*, vol. 38, no. 5, pp. 752–760, 2001.

[214] J. R. Wessel, "Error awareness and the error-related negativity: evaluating the first decade of evidence," *Frontiers in Human Neuroscience*, vol. 6, 2012.

[215] N. Yeung, "Relating cognitive and affective theories of the error-related negativity," in *Errors, conflicts, and the brain. Current opinions on performance monitoring*, pp. 63–70. MPI of Cognitive Neuroscience, 2004.

[216] M. Inzlicht and T. Al-Khindi, "Ern and the placebo: a misattribution approach to studying the arousal properties of the error-related negativity.," *Journal of Experimental Psychology: General*, vol. 141, no. 4, pp. 799, 2012.

[217] C. B. Holroyd, S. Nieuwenhuis, R. B. Mars, and M. G. Coles, "Anterior cingulate cortex, selection for action, and error processing," *Cognitive neuroscience of attention*, pp. 219–231, 2004.

[218] B. Stemmer, S. J. Segalowitz, W. Witzke, and P. W. Schönle, "Error detection in patients with lesions to the medial prefrontal cortex: an erp study," *Neuropsychologia*, vol. 42, no. 1, pp. 118–130, 2004.

[219] M. Brázdil, R. Roman, M. Falkenstein, P. Daniel, P. Jurák, and I. Rektor, "Error processing–evidence from intracerebral erp recordings," *Experimental Brain Research*, vol. 146, no. 4, pp. 460–466, 2002.

[220] M. Bear, B. Connors, and M. A. Paradiso, *Neuroscience: Exploring the Brain, Enhanced Edition: Exploring the Brain*, Jones & Bartlett Learning, 2020.

[221] J. C. Middlebrooks, "Sound localization," *Handbook of clinical neurology*, vol. 129, pp. 99–116, 2015.

[222] M. Risoud, J.-N. Hanson, F. Gauvrit, C. Renard, P.-E. Lemesre, N.-X. Bonne, and C. Vincent, "Sound source localization," *European annals of otorhinolaryngology, head and neck diseases*, vol. 135, no. 4, pp. 259–264, 2018.

[223] M. M. Van Wanrooij and A. J. Van Opstal, "Sound localization under perturbed binaural hearing," *Journal of neurophysiology*, vol. 97, no. 1, pp. 715–726, 2007.

[224] Y. Iwaya, Y. Suzuki, and D. Kimura, "Effects of head movement on front-back error in sound localization," *Acoustical science and technology*, vol. 24, no. 5, pp. 322–324, 2003.

[225] W. R. Thurlow and P. S. Runge, "Effect of induced head movements on localization of direction of sounds," *The Journal of the Acoustical Society of America*, vol. 42, no. 2, pp. 480–488, 1967.

[226] C. Valzolgher, M. Alzhaler, E. Gessa, M. Todeschini, P. Nieto, G. Verdelet, R. Salemme, V. Gaveau, M. Marx, E. Truy, et al., "The impact of a visual spatial frame on real sound-source localization in virtual reality," *Current Research in Behavioral Sciences*, vol. 1, pp. 100003, 2020.

[227] S. Perrett and W. Noble, "The effect of head rotations on vertical plane sound localization," *The Journal of the Acoustical Society of America*, vol. 102, no. 4, pp. 2325–2332, 1997.

[228] P. M. Hofman, J. G. Van Riswick, and A. J. Van Opstal, "Relearning sound localization with new ears," *Nature neuroscience*, vol. 1, no. 5, pp. 417–421, 1998.

[229] J. Blauert, *Spatial hearing: the psychophysics of human sound localization*, MIT press, 1997.

[230] J. C. Middlebrooks and D. M. Green, "Sound localization by human listeners," *Annual review of psychology*, vol. 42, no. 1, pp. 135–159, 1991.

[231] D. Morikawa and T. Hirahara, "Effect of head rotation on horizontal and median sound localization of band-limited noise," *Acoustical Science and Technology*, vol. 34, no. 1, pp. 56–58, 2013.

[232] S. Perrett and W. Noble, "The contribution of head motion cues to localization of low-pass noise," *Perception & psychophysics*, vol. 59, no. 7, pp. 1018–1026, 1997.

[233] S. R. Oldfield and S. P. Parker, "Acuity of sound localisation: a topography of auditory space. i. normal hearing conditions," *Perception*, vol. 13, no. 5, pp. 581–600, 1984.

[234] J. Kim, M. Barnett-Cowan, and E. A. Macpherson, "Integration of auditory input with vestibular and neck proprioceptive information in the interpretation of dynamic sound localization cues," in *Proceedings of meetings on acoustics ICA2013*. Acoustical Society of America, 2013, vol. 19, p. 050142.

[235] H. Wallach, "The role of head movements and vestibular and visual cues in sound localization.," *Journal of Experimental Psychology*, vol. 27, no. 4, pp. 339, 1940.

[236] F. L. Wightman and D. J. Kistler, "Resolution of front–back ambiguity in spatial hearing by listener and source movement," *The Journal of the Acoustical Society of America*, vol. 105, no. 5, pp. 2841–2853, 1999.

[237] M. Moerel, F. De Martino, K. Uğurbil, E. Yacoub, and E. Formisano, "Processing of frequency and location in human subcortical auditory structures," *Scientific reports*, vol. 5, no. 1, pp. 1–15, 2015.

[238] B. Grothe, M. Pecka, and D. McAlpine, "Mechanisms of sound localization in mammals," *Physiological reviews*, vol. 90, no. 3, pp. 983–1012, 2010.

[239] T. C. Yin, "Neural mechanisms of encoding binaural localization cues in the auditory brainstem," in *Integrative functions in the mammalian auditory pathway*, pp. 99–159. Springer, 2002.

[240] D. W. Muir, R. K. Clifton, and M. G. Clarkson, "The development of a human auditory localization response: a u-shaped function.," *Canadian Journal of Psychology/Revue canadienne de psychologie*, vol. 43, no. 2, pp. 199, 1989.

[241] R. Németh, G. P. Háden, M. Török, and I. Winkler, "Processing of horizontal sound localization cues in newborn infants," *Ear and hearing*, vol. 36, no. 5, pp. 550–556, 2015.

[242] R. Y. Litovsky and D. H. Ashmead, "Development of binaural and spatial hearing in infants and children," *Binaural and spatial hearing in real and virtual environments*, pp. 571–592, 1997.

[243] R. K. Clifton, J. Gwiazda, J. A. Bauer, M. G. Clarkson, and R. M. Held, "Growth in head size during infancy: Implications for sound localization.," *Developmental Psychology*, vol. 24, no. 4, pp. 477, 1988.

[244] P. Keating and A. J. King, "Sound localization in a changing world," *Current opinion in neurobiology*, vol. 35, pp. 35–43, 2015.

[245] M. Mishkin, L. G. Ungerleider, and K. A. Macko, "Object vision and spatial vision: two cortical pathways," *Trends in neurosciences*, vol. 6, pp. 414–417, 1983.

[246] M. Mishkin, M. E. Lewis, and L. G. Ungerleider, "Equivalence of parieto-preoccipital subareas for visuospatial ability in monkeys," *Behavioural brain research*, vol. 6, no. 1, pp. 41–55, 1982.

[247] M. A. Goodale and A. D. Milner, "Separate visual pathways for perception and action," *Trends in neurosciences*, vol. 15, no. 1, pp. 20–25, 1992.

[248] J. Lewald, K. A. Riederer, T. Lentz, and I. G. Meister, "Processing of sound location in human cortex," *European Journal of Neuroscience*, vol. 27, no. 5, pp. 1261–1270, 2008.

[249] R. J. Zatorre, M. Bouffard, P. Ahad, and P. Belin, "Where is' where'in the human auditory cortex?," *Nature neuroscience*, vol. 5, no. 9, pp. 905–909, 2002.

[250] R. A. Weeks, A. Aziz-Sultan, K. O. Bushara, B. Tian, C. M. Wessinger, N. Dang, J. P. Rauschecker, and M. Hallett, "A pet study of human auditory spatial processing," *Neuroscience Letters*, vol. 262, no. 3, pp. 155–158, 1999.

[251] L. Y. Deouell, A. S. Heller, R. Malach, M. D'Esposito, and R. T. Knight, "Cerebral responses to change in spatial location of unattended sounds," *Neuron*, vol. 55, no. 6, pp. 985–996, 2007.

[252] J. Ahveninen, I. P. Jääskeläinen, T. Raij, G. Bonmassar, S. Devore, M. Hämäläinen, S. Levänen, F.-H. Lin, M. Sams, B. G. Shinn-Cunningham, T. Witzel, and J. W. Belliveau, "Task-modulated "what" and "where" pathways in human auditory cortex," *Proceedings of the National Academy of Sciences*, vol. 103, no. 39, pp. 14608–14613, 2006.

[253] D. J. Barrett and D. A. Hall, "Response preferences for "what" and "where" in human non-primary auditory cortex," *Neuroimage*, vol. 32, no. 2, pp. 968–977, 2006.

[254] S. Getzmann and J. Lewald, "Effects of natural versus artificial spatial cues on electrophysiological correlates of auditory motion," *Hearing Research*, vol. 259, no. 1, pp. 44–54, 2010.

[255] N. Kopčo, S. Huang, J. W. Belliveau, T. Raij, C. Tengshe, and J. Ahveninen, "Neuronal representations of distance in human auditory cortex," *Proceedings of the National Academy of Sciences*, vol. 109, no. 27, pp. 11019–11024, 2012.

[256] K. Krumbholz, M. Schönwiesner, R. Rübsamen, K. Zilles, G. R. Fink, and D. Y. Von Cramon, "Hierarchical processing of sound location and motion in the human brainstem and planum temporale," *European Journal of Neuroscience*, vol. 21, no. 1, pp. 230–238, 2005.

[257] M. S. Tata and L. M. Ward, "Early phase of spatial mismatch negativity is localized to a posterior "where" auditory pathway," *Experimental Brain Research*, vol. 167, no. 3, pp. 481–486, 2005.

[258] J. D. Warren, B. A. Zielinski, G. G. Green, J. P. Rauschecker, and T. D. Griffiths, "Perception of sound-source motion by the human brain," *Neuron*, vol. 34, no. 1, pp. 139–148, 2002.

[259] J. D. Warren and T. D. Griffiths, "Distinct mechanisms for processing spatial sequences and pitch sequences in the human auditory brain," *Journal of Neuroscience*, vol. 23, no. 13, pp. 5799–5804, 2003.

[260] C. Poirier, S. Baumann, P. Dheerendra, O. Joly, D. Hunter, F. Balezeau, L. Sun, A. Rees, C. I. Petkov, A. Thiele, et al., "Auditory motion-specific mechanisms in the primate brain," *PLoS biology*, vol. 15, no. 5, pp. e2001379, 2017.

[261] J. Lewald, H. Foltys, and R. Töpper, "Role of the posterior parietal cortex in spatial hearing," *Journal of Neuroscience*, vol. 22, no. 3, pp. RC207–RC207, 2002.

[262] C. Battal, M. Rezk, S. Mattioni, J. Vadlamudi, and O. Collignon, "Representation of auditory motion directions and sound source locations in the human planum temporale," *Journal of Neuroscience*, vol. 39, no. 12, pp. 2208–2220, 2019.

[263] T. D. Griffiths and J. D. Warren, "The planum temporale as a computational hub," *Trends in neurosciences*, vol. 25, no. 7, pp. 348–353, 2002.

[264] S. Carlile and J. Leung, "The perception of auditory motion," *Trends in hearing*, vol. 20, pp. 2331216516644254, 2016.

[265] C. Y. Ducommun, M. M. Murray, G. Thut, A. Bellmann, I. Viaud-Delmon, S. Clarke, and C. M. Michel, "Segregated processing of auditory motion and auditory location: an erp mapping study," *Neuroimage*, vol. 16, no. 1, pp. 76–88, 2002.

[266] Z.-L. Lu, S. Williamson, and L. Kaufman, "Behavioral lifetime of human auditory sensory memory predicted by physiological measures," *Science*, vol. 258, no. 5088, pp. 1668–1670, 1992.

[267] I. P. Jääskeläinen, J. Ahveninen, G. Bonmassar, A. M. Dale, R. J. Ilmoniemi, S. Levänen, F.-H. Lin, P. May, J. Melcher, S. Stufflebeam,

et al., "Human posterior auditory cortex gates novel sounds to consciousness," *Proceedings of the National Academy of Sciences*, vol. 101, no. 17, pp. 6809–6814, 2004.

[268] M. Sams, R. Hari, J. Rif, and J. Knuutila, "The human auditory sensory memory trace persists about 10 sec: neuromagnetic evidence," *Journal of cognitive neuroscience*, vol. 5, no. 3, pp. 363–370, 1993.

[269] V. Leavitt, S. Molholm, M. Gomez-Ramirez, and J. Foxe, ""what" and "where" in auditory sensory processing: A high-density electrical mapping study of distinct neural processes underlying sound object recognition and sound localization," *Frontiers in Integrative Neuroscience*, vol. 5, pp. 23, 2011.

[270] H. Tiitinen, N. H. Salminen, K. J. Palomäki, V. T. Mäkinen, P. Alku, and P. J. May, "Neuromagnetic recordings reveal the temporal dynamics of auditory spatial processing in the human cortex," *Neuroscience Letters*, vol. 396, no. 1, pp. 17–22, 2006.

[271] L. Spierer, A. Bellmann-Thiran, P. Maeder, M. M. Murray, and S. Clarke, "Hemispheric competence for auditory spatial representation," *Brain*, vol. 132, no. 7, pp. 1953–1966, 2009.

[272] L. Y. Deouell, A. Parnes, N. Pickard, and R. T. Knight, "Spatial location is accurately tracked by human auditory sensory memory: evidence from the mismatch negativity," *European Journal of Neuroscience*, vol. 24, no. 5, pp. 1488–1494, 2006.

[273] K. van der Heijden, J. P. Rauschecker, E. Formisano, G. Valente, and B. de Gelder, "Active sound localization sharpens spatial tuning in human primary auditory cortex," *Journal of Neuroscience*, vol. 38, no. 40, pp. 8574–8587, 2018.

[274] C.-C. Lee and J. C. Middlebrooks, "Auditory cortex spatial sensitivity sharpens during task performance," *Nature neuroscience*, vol. 14, no. 1, pp. 108–114, 2011.

[275] J. B. Fritz, S. V. David, S. Radtke-Schuller, P. Yin, and S. A. Shamma, "Adaptive, behaviorally gated, persistent encoding of task-relevant auditory information in ferret frontal cortex," *Nature neuroscience*, vol. 13, no. 8, pp. 1011–1019, 2010.

[276] P. S. Goldman-Rakic, "The prefrontal landscape: implications of functional architecture for understanding human mentation and the central executive," *Philosophical Transactions of the Royal Society of London. Series B: Biological Sciences*, vol. 351, no. 1346, pp. 1445–1453, 1996.

[277] C. Alain, K. L. McDonald, N. Kovacevic, and A. R. McIntosh, "Spatiotemporal analysis of auditory "what" and "where" working memory," *Cerebral Cortex*, vol. 19, no. 2, pp. 305–314, 2009.

[278] I. Anourova, V. V. Nikouline, R. J. Ilmoniemi, J. Hotta, H. J. Aronen, and S. Carlson, "Evidence for dissociation of spatial and nonspatial auditory information processing," *Neuroimage*, vol. 14, no. 6, pp. 1268–1277, 2001.

[279] P. Rämä, L. Paavilainen, I. Anourova, K. Alho, K. Reinikainen, S. Sipilä, and S. Carlson, "Modulation of slow brain potentials by working memory load in spatial and nonspatial auditory tasks," *Neuropsychologia*, vol. 38, no. 7, pp. 913–922, 2000.

[280] X. Zhang, Q. Zhang, X. Hu, and B. Zhang, "Neural representation of three-dimensional acoustic space in the human temporal lobe," *Frontiers in human neuroscience*, vol. 9, pp. 203, 2015.

[281] P. M. Briley, A. M. Goman, and A. Q. Summerfield, "Asymmetries in the representation of space in the human auditory cortex depend on the global stimulus context," *NeuroReport*, vol. 27, no. 4, pp. 242–246, 2016.

[282] N. H. Salminen, H. Tiitinen, I. Miettinen, P. Alku, and P. J. May, "Asymmetrical representation of auditory space in human cortex," *Brain research*, vol. 1306, pp. 93–99, 2010.

[283] P. M. Briley, A. M. Goman, and A. Q. Summerfield, "Physiological evidence for a midline spatial channel in human auditory cortex," *Journal of the Association for Research in Otolaryngology*, vol. 17, no. 4, pp. 331–340, 2016.

[284] R. N. Dingle, S. E. Hall, and D. P. Phillips, "A midline azimuthal channel in human spatial hearing," *Hearing research*, vol. 268, no. 1-2, pp. 67–74, 2010.

[285] J. A. Healey and R. W. Picard, "Detecting stress during real-world driving tasks using physiological sensors," *IEEE Transactions on intelligent transportation systems*, vol. 6, no. 2, pp. 156–166, 2005.

[286] S.-H. Hsu and T.-P. Jung, "Monitoring alert and drowsy states by modeling eeg source nonstationarity," *Journal of neural engineering*, vol. 14, no. 5, pp. 056012, 2017.

[287] Z. Ren, R. Li, B. Chen, H. Zhang, Y. Ma, C. Wang, Y. Lin, and Y. Zhang, "Eeg-based driving fatigue detection using a two-level learning hierarchy radial basis function," *Frontiers in Neurorobotics*, vol. 15, 2021.

[288] Y. Ma, B. Chen, R. Li, C. Wang, J. Wang, Q. She, Z. Luo, and Y. Zhang, "Driving fatigue detection from eeg using a modified pcanet method," *Computational intelligence and neuroscience*, vol. 2019, 2019.

[289] Y. Ming, D. Wu, Y.-K. Wang, Y. Shi, and C.-T. Lin, "Eeg-based drowsiness estimation for driving safety using deep q-learning," *IEEE Transactions on Emerging Topics in Computational Intelligence*, 2020.

[290] E. J. Cheng, K.-Y. Young, and C.-T. Lin, "Temporal eeg imaging for drowsy driving prediction," *Applied Sciences*, vol. 9, no. 23, pp. 5078, 2019.

[291] Y. Li, "Recognition algorithm of driving fatigue related problems based on eeg signals," *NeuroQuantology*, vol. 16, no. 6, 2018.

[292] A. Chaudhuri and A. Routray, "Driver fatigue detection through chaotic entropy analysis of cortical sources obtained from scalp eeg signals," *IEEE Transactions on Intelligent Transportation Systems*, vol. 21, no. 1, pp. 185–198, 2020.

[293] C.-T. Lin, R.-C. Wu, S.-F. Liang, W.-H. Chao, Y.-J. Chen, and T.-P. Jung, "Eeg-based drowsiness estimation for safety driving using independent component analysis," *IEEE Transactions on Circuits and Systems I: Regular Papers*, vol. 52, no. 12, pp. 2726–2738, 2005.

[294] C.-T. Lin, J.-T. King, C.-H. Chuang, W. Ding, W.-Y. Chuang, L.-D. Liao, and Y.-K. Wang, "Exploring the brain responses to driving fa-

tigue through simultaneous eeg and fnirs measurements," *International journal of neural systems*, vol. 30, no. 01, pp. 1950018, 2020.

[295] T. Tuncer, S. Dogan, and A. Subasi, "Eeg-based driving fatigue detection using multilevel feature extraction and iterative hybrid feature selection," *Biomedical Signal Processing and Control*, vol. 68, pp. 102591, 2021.

[296] F. Wang, X. Zhang, R. Fu, and G. Sun, "Eeg characteristic analysis of coach bus drivers based on brain connectivity as revealed via a graph theoretical network," *RSC advances*, vol. 8, no. 52, pp. 29745–29755, 2018.

[297] I. Solís-Marcos and K. Kircher, "Event-related potentials as indices of mental workload while using an in-vehicle information system," *Cognition, Technology & Work*, vol. 21, no. 1, pp. 55–67, 2019.

[298] Y.-K. Wang, S.-A. Chen, and C.-T. Lin, "An eeg-based brain–computer interface for dual task driving detection," *Neurocomputing*, vol. 129, pp. 85–93, 2014.

[299] R. Aydarkhanov, M. Uščumlić, R. Chavarriaga, L. Gheorghe, and J. del R Millán, "Closed-loop eeg study on visual recognition during driving," *Journal of neural engineering*, vol. 18, no. 2, pp. 026010, 2021.

[300] J. Min, P. Wang, and J. Hu, "Driver fatigue detection through multiple entropy fusion analysis in an eeg-based system," *PLoS one*, vol. 12, no. 12, pp. e0188756, 2017.

[301] G. Borghini, L. Astolfi, G. Vecchiato, D. Mattia, and F. Babiloni, "Measuring neurophysiological signals in aircraft pilots and car drivers for the assessment of mental workload, fatigue and drowsiness," *Neuroscience Biobehavioral Reviews*, vol. 44, pp. 58–75, 2014, Applied Neuroscience: Models, methods, theories, reviews. A Society of Applied Neuroscience (SAN) special issue.

[302] I.-H. Kim, J.-W. Kim, S. Haufe, and S.-W. Lee, "Detection of braking intention in diverse situations during simulated driving based on eeg feature combination," *Journal of neural engineering*, vol. 12, no. 1, pp. 016001, 2014.

[303] S. Haufe, J.-W. Kim, I.-H. Kim, A. Sonnleitner, M. Schrauf, G. Curio, and B. Blankertz, "Electrophysiology-based detection of emergency braking intention in real-world driving," *Journal of neural engineering*, vol. 11, no. 5, pp. 056011, 2014.

[304] L. G. Hernández, O. M. Mozos, J. M. Ferrández, and J. M. Antelis, "Eeg-based detection of braking intention under different car driving conditions," *Frontiers in neuroinformatics*, vol. 12, pp. 29, 2018.

[305] T.-H. Nguyen and W.-Y. Chung, "Detection of driver braking intention using eeg signals during simulated driving," *Sensors*, vol. 19, no. 13, 2019.

[306] H. Zhang, R. Chavarriaga, Z. Khaliliardali, L. Gheorghe, I. Iturrate, and J. d R Millán, "Eeg-based decoding of error-related brain activity in a real-world driving task," *Journal of neural engineering*, vol. 12, no. 6, pp. 066028, 2015.

[307] L. Gheorghe, R. Chavarriaga, and J. d. R. Millán, "Steering timing prediction in a driving simulator task," in *2013 35th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*. IEEE, 2013, pp. 6913–6916.

[308] H. Zhang, R. Chavarriaga, L. Gheorghe, and J. d. R. Millán, "Brain correlates of lane changing reaction time in simulated driving," in *2015 IEEE International Conference on Systems, Man, and Cybernetics*. IEEE, 2015, pp. 3158–3163.

[309] L. Yang, R. Ma, H. M. Zhang, W. Guan, and S. Jiang, "Driving behavior recognition using eeg data from a simulated car-following experiment," *Accident Analysis Prevention*, vol. 116, pp. 30–40, 2018, Simulation of Traffic Safety in the Era of Advances in Technologies.

[310] B. Zou, Z. Xiao, and M. Liu, "Driving behavior recognition based on eeg data from a driver taking over experiment on a simulated autonomous vehicle," in *Journal of Physics: Conference Series*. IOP Publishing, 2020, vol. 1550, p. 042046.

[311] F. Yan, M. Liu, C. Ding, Y. Wang, and L. Yan, "Driving style recognition based on electroencephalography data from a simulated driving experiment," *Frontiers in psychology*, vol. 10, pp. 1254, 2019.

[312] G. Rupp, C. Berka, A. H. Meghdadi, M. S. Karić, M. Casillas, S. Smith, T. Rosenthal, K. McShea, E. Sones, and T. D. Marcotte, "Eeg-based neurocognitive metrics may predict simulated and on-road driving performance in older drivers," *Frontiers in human neuroscience*, vol. 12, pp. 532, 2019.

[313] Y. Wu, J. Zhang, B. Tang, and G. Guo, "Research on eeg-based novice and experienced drivers' identification using bp neural network during simulated driving," in *2020 4th CAA International Conference on Vehicular Control and Intelligence (CVCI)*, 2020, pp. 475–480.

[314] K. Inagaki, N. Wagatsuma, and S. Nobukawa, "The effects of driving experience on the p300 event-related potential during the perception of traffic scenes," *International Journal of Environmental Research and Public Health*, vol. 18, no. 19, 2021.

[315] Y. Yang, Y. Feng, S. M. Easa, X. Yang, J. Liu, and W. Lin, "Sound effects on physiological state and behavior of drivers in a highway tunnel," *Frontiers in psychology*, p. 2213, 2021.

[316] Q. Wang and Z. Mu, "Application of music in relief of driving fatigue based on eeg signals," *EURASIP Journal on Advances in Signal Processing*, vol. 2021, no. 1, pp. 1–15, 2021.

[317] A. E. Wester, K. B. Böcker, E. R. Volkerts, J. C. Verster, and J. L. Kenemans, "Event-related potentials and secondary task performance during simulated driving," *Accident Analysis & Prevention*, vol. 40, no. 1, pp. 1–7, 2008.

[318] M. Karthaus, E. Wascher, and S. Getzmann, "Distraction in the driving simulator: An event-related potential (erp) study with young, middle-aged, and older drivers," *Safety*, vol. 7, no. 2, 2021.

[319] R. M. A. van der Heiden, C. P. Janssen, S. F. Donker, L. E. S. Hardeman, K. Mans, and J. L. Kenemans, "Susceptibility to audio signals during autonomous driving," *PLOS ONE*, vol. 13, no. 8, pp. 1–16, 08 2018.

[320] N. Dahal, D. N. Nandagopal, B. Cocks, R. Vijayalakshmi, N. Dasari, and P. Gaertner, "Tvar modeling of eeg to detect audio distraction

during simulated driving," *Journal of neural engineering*, vol. 11, no. 3, pp. 036012, 2014.

[321] Q. Zhao, L. Zhang, and A. Cichocki, "Eeg-based asynchronous bci control of a car in 3d virtual reality environments," *Chinese Science Bulletin*, vol. 54, no. 1, pp. 78–87, 2009.

[322] D. Göhring, D. Latotzky, M. Wang, and R. Rojas, "Semi-autonomous car control using brain computer interfaces," in *Intelligent Autonomous Systems 12*, pp. 393–408. Springer, 2013.

[323] J. E. Scanlon, K. A. Townsend, D. L. Cormier, J. W. Kuziek, and K. E. Mathewson, "Taking off the training wheels: Measuring auditory p3 during outdoor cycling using an active wet eeg system," *Brain Research*, vol. 1716, pp. 50–61, 2019, SI: Brain in Motion.

[324] S. Debener, F. Minow, R. Emkes, K. Gandras, and M. de Vos, "How about taking a low-cost, small, and wireless eeg for a walk?," *Psychophysiology*, vol. 49, no. 11, pp. 1617–1621, 2012.

[325] D. Hölle, J. Meekes, and M. G. Bleichner, "Mobile ear-eeg to study auditory attention in everyday life," *Behavior Research Methods*, pp. 1–12, 2021.

[326] M. De Vos, K. Gandras, and S. Debener, "Towards a truly mobile auditory brain–computer interface: exploring the p300 to take away," *International journal of psychophysiology*, vol. 91, no. 1, pp. 46–53, 2014.

[327] D. E. Callan, G. Durantin, and C. Terzibas, "Classification of single-trial auditory events using dry-wireless eeg during real and motion simulated flight," *Frontiers in systems neuroscience*, vol. 9, pp. 11, 2015.

[328] S. Barua, M. Ahmed, C. Ahlstrom, S. Begum, and P. Funk, "Automated eeg artifact handling with application in driver monitoring," *IEEE Journal of Biomedical and Health Informatics*, vol. PP, 11 2017.

[329] J. A. Urigüen and B. Garcia-Zapirain, "Eeg artifact removal—state-of-the-art and guidelines," *Journal of neural engineering*, vol. 12, no. 3, pp. 031001, 2015.

[330] A. Bellotti, S. Antopolskiy, A. Marchenkova, A. Colucciello, P. Avanzini, G. Vecchiato, J. Ambeck-Madsen, and L. Ascari, "Brain-based control of car infotainment," in *2019 IEEE International Conference on Systems, Man and Cybernetics (SMC)*. IEEE, 2019, pp. 2166–2173.

[331] L. Ascari, A. Marchenkova, A. Bellotti, S. Lai, L. Moro, K. Koshmak, A. Mantoan, M. Barsotti, R. Brondi, G. Avveduto, D. Sechi, A. Compagno, P. Avanzini, J. Ambeck-Madsen, and G. Vecchiato, "Validation of a novel wearable multistream data acquisition and analysis system for ergonomic studies," *Sensors*, vol. 21, no. 24, 2021.

[332] C. A. Scholl, Y. M. Chi, M. Elconin, W. R. Gray, M. A. Chevillet, and E. A. Pohlmeyer, "Classification of pilot-induced oscillations during in-flight piloting exercises using dry eeg sensor recordings," in *2016 38th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*. IEEE, 2016, pp. 4467–4470.

[333] T. d. Silveira, A. d. J. Kozakevicius, and C. R. Rodrigues, "Drowsiness detection for single channel EEG by DWT best m-term approximation," *Research on Biomedical Engineering*, vol. 31, pp. 107 – 115, 06 2015.

[334] L. Gheorghe, R. Chavarriaga, and J. d. R. Millán, "Steering timing prediction in a driving simulator task," in *2013 35th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*, July 2013, pp. 6913–6916.

[335] H. Zhang, R. Chavarriaga, L. Gheorghe, and J. D. R. Millán, "Brain correlates of lane changing reaction time in simulated driving," in *2015 IEEE International Conference on Systems, Man, and Cybernetics*, Oct 2015, pp. 3158–3163.

[336] E. A. Kirchner and S. K. Kim, "Multi-tasking and choice of training data influencing parietal erp expression and single-trial detection—relevance for neuroscience and clinical applications," *Frontiers in neuroscience*, vol. 12, pp. 188, 2018.

[337] P. Garaizar and M. A. Vadillo, "Accuracy and precision of visual stimulus timing in psychopy: No timing errors in standard usage," *PloS one*, vol. 9, no. 11, pp. e112033, 2014.

[338] S. J. Luck and S. A. Hillyard, "Electrophysiological correlates of feature analysis during visual search," *Psychophysiology*, vol. 31, no. 3, pp. 291–308, 1994.

[339] U. Hoffmann, J.-M. Vesin, T. Ebrahimi, and K. Diserens, "An efficient p300-based brain–computer interface for disabled subjects," *Journal of Neuroscience methods*, vol. 167, no. 1, pp. 115–125, 2008.

[340] Y. Liu, Z. Zhou, and D. Hu, "Comparison of stimulus types in visual p300 speller of brain-computer interfaces," in *9th IEEE International Conference on Cognitive Informatics (ICCI'10)*. IEEE, 2010, pp. 273–279.

[341] J. E. Scanlon, K. A. Townsend, D. L. Cormier, J. W. Kuziek, and K. E. Mathewson, "Taking off the training wheels: Measuring auditory p3 during outdoor cycling using an active wet eeg system," *Brain research*, 2017.

[342] J. W. Kuziek, A. Shienh, and K. E. Mathewson, "Transitioning eeg experiments away from the laboratory using a raspberry pi 2," *Journal of neuroscience methods*, vol. 277, pp. 75–82, 2017.

[343] R. T. Schirrmeister, J. T. Springenberg, L. D. J. Fiederer, M. Glasstetter, K. Eggensperger, M. Tangermann, F. Hutter, W. Burgard, and T. Ball, "Deep learning with convolutional neural networks for eeg decoding and visualization," *Human brain mapping*, vol. 38, no. 11, pp. 5391–5420, 2017.

[344] L. Vareka and P. Mautner, "Using the windowed means paradigm for single trial p300 detection," in *2015 38th International Conference on Telecommunications and Signal Processing (TSP)*, July 2015, pp. 1–4.

[345] V. Abootalebi, M. H. Moradi, and M. A. Khalilzadeh, "A new approach for eeg feature extraction in p300-based lie detection," *Computer Methods and Programs in Biomedicine*, vol. 94, no. 1, pp. 48 – 57, 2009.

[346] J. R. Wolpaw, N. Birbaumer, D. J. McFarland, G. Pfurtscheller, and T. M. Vaughan, "Brain–computer interfaces for communication and control," *Clinical Neurophysiology*, vol. 113, no. 6, pp. 767–791, 2002.

[347] J. R. Pierce, "An introduction to information theory: Symbols," *Signals and Noise E*, vol. 2, 1980.

[348] S. Gao, Y. Wang, X. Gao, and B. Hong, "Visual and auditory brain–computer interfaces," *IEEE Transactions on Biomedical Engineering*, vol. 61, no. 5, pp. 1436–1447, 2014.

[349] A. Bellotti, M. Binelli, G. M. Di Liberto, L. Ascari, C. Raymaekers, and A. Farina, "Investigation on neural responses related to the localization of natural sounds," in *Forum Acusticum*, 2020, pp. 2271–2277.

[350] S. Getzmann and J. Lewald, "Effects of natural versus artificial spatial cues on electrophysiological correlates of auditory motion," *Hearing Research*, vol. 259, no. 1, pp. 44 – 54, 2010.

[351] K. van der Heijden, J. P. Rauschecker, B. de Gelder, and E. Formisano, "Cortical mechanisms of spatial hearing," *Nature Reviews Neuroscience*, vol. 20, no. 10, pp. 609 – 623, 2019.

[352] C. Alain, S. R. Arnott, S. Hevenor, S. Graham, and C. L. Grady, ""what" and "where" in the human auditory system," *Proceedings of the National Academy of Sciences*, vol. 98, no. 21, pp. 12301–12306, 2001.

[353] P. P. Maeder, R. A. Meuli, M. Adriani, A. Bellmann, E. Fornari, J.-P. Thiran, A. Pittet, and S. Clarke, "Distinct pathways involved in sound recognition and localization: A human fmri study," *NeuroImage*, vol. 14, no. 4, pp. 802 – 816, 2001.

[354] J. Ahveninen, I. P. Jääskeläinen, T. Raij, G. Bonmassar, S. Devore, M. Hämäläinen, S. Levänen, F.-H. Lin, M. Sams, B. G. Shinn-Cunningham, T. Witzel, and J. W. Belliveau, "Task-modulated "what" and "where" pathways in human auditory cortex," *Proceedings of the National Academy of Sciences*, vol. 103, no. 39, pp. 14608–14613, 2006.

[355] D. J. Barrett and D. A. Hall, "Response preferences for "what" and "where" in human non-primary auditory cortex," *NeuroImage*, vol. 32, no. 2, pp. 968 – 977, 2006.

[356] S. Arnott, M. Binns, C. Grady, and C. Alain, "Assessing the auditory dual-pathway model in humans," *NeuroImage*, vol. 22, pp. 401–8, 06 2004.

[357] A. Capra, S. Fontana, F. Adriaensen, A. Farina, and Y. Grenier, "Listening tests of the localization performance of stereodipole and ambisonic systems," *Audio Engineering Society - 123rd Audio Engineering Society Convention 2007*, vol. 2, 01 2012.

[358] O. Kirkeby, P. Rubak, and A. Farina, "Analysis of ill-conditioning of multi-channel deconvolution problems," in *Proceedings of the 1999 IEEE Workshop on Applications of Signal Processing to Audio and Acoustics. WASPAA'99 (Cat. No.99TH8452)*, 1999, pp. 155–158.

[359] Y. Ando, *Concert Hall Acoustics*, Springer, 1985.

[360] T. R. Mullen, C. A. E. Kothe, Y. M. Chi, A. Ojeda, T. Kerth, S. Makeig, T. Jung, and G. Cauwenberghs, "Real-time neuroimaging and cognitive monitoring using wearable dry eeg," *IEEE Transactions on Biomedical Engineering*, vol. 62, no. 11, pp. 2553–2567, Nov 2015.

[361] C. Chang, S. Hsu, L. Pion-Tonachini, and T. Jung, "Evaluation of artifact subspace reconstruction for automatic artifact components removal in multi-channel eeg recordings," *IEEE Transactions on Biomedical Engineering*, pp. 1–1, 2019.

[362] A. de Cheveigné and L. C. Parra, "Joint decorrelation, a versatile tool for multichannel data analysis," *NeuroImage*, vol. 98, pp. 487 – 505, 2014.

[363] M. A. Boudewyn, S. J. Luck, J. L. Farrens, and E. S. Kappenman, "How many trials does it take to get a significant erp effect? it depends," *Psychophysiology*, vol. 55, no. 6, pp. e13049, 2018.

[364] V. Bostanov, "Bci competition 2003-data sets ib and iib: feature extraction from event-related brain potentials with the continuous wavelet

transform and the t-value scalogram," *IEEE Transactions on Biomedical engineering*, vol. 51, no. 6, pp. 1057–1061, 2004.

[365] D. Farina, O. F. Do Nascimento, M.-F. Lucas, and C. Doncarli, "Optimization of wavelets for classification of movement-related cortical potentials generated by variation of force-related parameters," *Journal of neuroscience methods*, vol. 162, no. 1-2, pp. 357–363, 2007.

[366] P. Zanini, M. Congedo, C. Jutten, S. Said, and Y. Berthoumieu, "Transfer learning: A riemannian geometry framework with applications to brain–computer interfaces," *IEEE Transactions on Biomedical Engineering*, vol. 65, no. 5, pp. 1107–1116, 2018.

[367] M. Congedo, A. Barachant, and R. Bhatia, "Riemannian geometry for eeg-based brain-computer interfaces; a primer and a review," *Brain-Computer Interfaces*, vol. 4, no. 3, pp. 155–174, 2017.

[368] S. Nasiri Ghosheh Bolagh, M. Bagher Shamsollahi, C. Jutten, and M. Congedo, "Unsupervised Cross-Subject BCI Learning and Classification using Riemannian Geometry," in *ESANN 2016 - 24th European Symposium on Artificial Neural Networks, Computational Intelligence and Machine Learning*, Bruges, Belgium, Apr. 2016, European Neural Network Society.

[369] M. Congedo, A. Barachant, and A. Andreev, "A new generation of brain-computer interface based on riemannian geometry," 2013.

[370] A. Barachant, "Meg decoding using riemannian geometry and unsupervised classification," *Grenoble University: Grenoble, France*, 2014.

[371] L. Korczowski, M. Congedo, and C. Jutten, "Single-trial classification of multi-user p300-based brain-computer interface using riemannian geometry," in *2015 37th Annual International Conference of the IEEE Engineering in Medicine and Biology Society (EMBC)*, 2015, pp. 1769–1772.

[372] A. Barachant, S. Bonnet, M. Congedo, and C. Jutten, "Classification of covariance matrices using a riemannian-based kernel for bci applications," *Neurocomputing*, vol. 112, pp. 172–178, 2013, Advances in artificial neural networks, machine learning, and computational intelligence.

[373] A. Barachant, S. Bonnet, M. Congedo, and C. Jutten, "Multiclass brain–computer interface classification by riemannian geometry," *IEEE Transactions on Biomedical Engineering*, vol. 59, no. 4, pp. 920–928, 2012.

[374] H. Ye, T. Yu, S. Liu, and Z. Huang, "Unsupervised meg classification by riemannian geometry and class centroid matching," in *2020 International Conference on Artificial Intelligence and Computer Engineering (ICAICE)*, 2020, pp. 424–429.

[375] C. Simar, R. Petit, N. Bozga, A. Leroy, A.-M. Cebolla, M. Petieau, G. Bontempi, and G. Cheron, "Riemannian classification of single-trial surface eeg and sources during checkerboard and navigational images in humans," *PLOS ONE*, vol. 17, no. 1, pp. 1–22, 01 2022.

[376] B. Rivet, A. Souloumiac, V. Attina, and G. Gibert, "xdawn algorithm to enhance evoked potentials: Application to brain–computer interface," *Biomedical Engineering, IEEE Transactions on*, vol. 56, pp. 2035 – 2043, 09 2009.

[377] B. Rivet, H. Cecotti, A. Souloumiac, E. Maby, and J. Mattout, "Theoretical analysis of xdawn algorithm: Application to an efficient sensor selection in a p300 bci," in *2011 19th European Signal Processing Conference*, 2011, pp. 1382–1386.

[378] A. Dempster, F. Petitjean, and G. I. Webb, "Rocket: exceptionally fast and accurate time series classification using random convolutional kernels," *Data Mining and Knowledge Discovery*, vol. 34, no. 5, pp. 1454–1495, Jul 2020.

[379] C. Lundy and J. M. O'Toole, "Random convolution kernels with multi-scale decomposition for preterm eeg inter-burst detection," *2021 29th European Signal Processing Conference (EUSIPCO)*, pp. 1182–1186, 2021.

[380] M. A. Gerzon, "The design of precisely coincident microphone arrays for stereo and surround sound," in *Audio Engineering Society Convention 50*. Audio Engineering Society, 1975.

[381] N. M. Ferrers, *An elementary treatise on spherical harmonics and subjects connected with them*, Macmillan and Company, 1877.

[382] A. Farina, "Explicit formulas for high order ambisonics," 2017.

[383] R. González, J. Pearce, and T. Lokki, "Modular design for spherical microphone arrays," in *Audio Engineering Society Conference: 2018 AES International Conference on Audio for Virtual and Augmented Reality*. Audio Engineering Society, 2018.

[384] S. Moreau, J. Daniel, and S. Bertet, "3d sound field recording with higher order ambisonics–objective measurements and validation of a 4th order spherical microphone," in *120th Convention of the AES*, 2006, pp. 20–23.

[385] A. Farina, A. Capra, L. Conti, P. Mantignon, and F. M. Fazi, "Measuring spatial impulse responses in concert halls and opera houses employing a spherical microphone array," 2007.

[386] N. Peters and A. W. Schmeder, "Beamforming using a spherical microphone array based on legacy microphone characteristics," in *Proceedings of the ICSA International Conference on Spatial Audio*, 2011.

[387] S. Sakamoto, S. Hongo, T. Okamoto, Y. Iwaya, and Y. Suzuki, "Sound-space recording and binaural presentation system based on a 252-channel microphone array," *Acoustical Science and Technology*, vol. 36, no. 6, pp. 516–526, 2015.

[388] J. Meyer and G. Elko, "A highly scalable spherical microphone array based on an orthonormal decomposition of the soundfield," in *2002 IEEE International Conference on Acoustics, Speech, and Signal Processing*. IEEE, 2002, vol. 2, pp. II–1781.

[389] C. Nachbar, F. Zotter, E. Deleflie, and A. Sontacchi, "Ambix-a suggested ambisonics format," in *Ambisonics Symposium, Lexington*, 2011, p. 11.

[390] S. Delikaris-Manias and V. Pulkki, "Parametric spatial filter utilizing dual beamformer and snr-based smoothing," in *Audio Engineering Society Conference: 55th International Conference: Spatial Audio*. Audio Engineering Society, 2014.

[391] V. Pulkki, "Directional audio coding in spatial sound reproduction and stereo upmixing," in *Audio Engineering Society Conference: 28th*

International Conference: The Future of Audio Technology–Surround and Beyond. Audio Engineering Society, 2006.

[392] V. Pulkki, "Spatial sound reproduction with directional audio coding," *Journal of the Audio Engineering Society*, vol. 55, no. 6, pp. 503–516, 2007.

[393] S. Berge and N. Barrett, "High angular resolution planewave expansion," in *Proc. of the 2nd International Symposium on Ambisonics and Spherical Acoustics May*, 2010, pp. 6–7.

[394] V. Pulkki, A. Politis, M.-V. Laitinen, J. Vilkamo, and J. Ahonen, "First-order directional audio coding (dirac)," *Parametric Time-Frequency Domain Spatial Audio*, vol. 10, pp. 89–140, 2017.

[395] O. Kirkeby, F. Orduna, P. A. Nelson, and H. Hameda, "Inverse filtering in sound reproduction," *Measurement and Control*, vol. 26, no. 9, pp. 261–266, 1993.

[396] H. Tokuno, O. Kirkeby, P. A. Nelson, and H. Hamada, "Inverse filter of sound reproduction systems using regularization," *IEICE transactions on fundamentals of electronics, communications and computer sciences*, vol. 80, no. 5, pp. 809–820, 1997.

[397] A. Farina, A. Capra, L. Chiesi, and L. Scopece, "A spherical microphone array for synthesizing virtual directive microphones in live broadcasting and in post production," in *Audio Engineering Society Conference: 40th International Conference: Spatial Audio: Sense the Sound of Space*. Audio Engineering Society, 2010.

[398] A. Farina, S. Campanini, L. Chiesi, A. Amendola, and L. Ebri, "Spatial sound recording with dense microphone arrays," in *Audio Engineering Society Conference: 55th International Conference: Spatial Audio*. Audio Engineering Society, 2014.

[399] A. Farina, "Simultaneous measurement of impulse response and distortion with a swept-sine technique," in *Audio Engineering Society Convention 108*. Audio Engineering Society, 2000.

[400] R. H. Hardin and N. J. Sloane, "Mclaren's improved snub cube and other new spherical designs in three dimensions," *Discrete & Computational Geometry*, vol. 15, no. 4, pp. 429–441, 1996.

[401] D. Pinardi, "Spherical t-design for characterizing the spatial response of microphone arrays," in *2021 Immersive and 3D Audio: from Architecture to Automotive (I3DA)*. IEEE, 2021, pp. 1–8.

[402] L. McCormack, S. Delikaris-Manias, A. Farina, D. Pinardi, and V. Pulkki, "Real-time conversion of sensor array signals into spherical harmonic signals with applications to spatially localized sub-band sound-field analysis," in *Audio Engineering Society Convention 144*. Audio Engineering Society, 2018.

[403] L. McCormack, S. Delikaris-Manias, A. Politis, D. Pavlidi, A. Farina, D. Pinardi, and V. Pulkki, "Applications of spatially localized active-intensity vectors for sound-field visualization," *Journal of the Audio Engineering Society*, vol. 67, no. 11, pp. 840–854, 2019.

Appendix 1: spatial sound processing

Introduction The use of microphone arrays for spatial audio recordings dates to the seventies, when the Soundfield™ Microphone [380] was proposed, relying on the Ambisonics theory [12]: a method for representing the complete acoustical spatial information in one point of the space by means of a Spherical Harmonics (SH) expansion of the signals recorded by the capsules of the array [381, 382]. Microphone arrays equipped with four capsules, such as the Soundfield™, can encode the First Order Ambisonics (FOA), which exhibits a reduced spatial resolution. To overcome this limit, the first order approach was later extended to High Order Ambisonics (HOA), which requires more microphones and hence more channels.

Since 1978, many four channels microphone arrays came to market and several higher order compact spherical microphone arrays were built too, with a number of capsules ranging between 8 and 252 [383, 384, 385, 386, 387, 388]. In this work, the Eigenmike32™ (EM) was employed, a studio-quality HOA array of microphones (Figure 1), based on the pioneering work of Gary Elko [388]. It features 32 capsules arranged over the surface of a rigid sphere of 84 mm diameter.

Spatial audio theory recall The capsules of a microphone array detect the sound pressure and such set of signals is usually known as "A-format". Then, the operation of beamforming converts these signals in a complex combination of sound pressure and particle velocity, resulting in the so-called virtual microphones. In case of Ambisonics, the virtual microphones are



Figure 1: Eigenmike32™ microphone array

usually known as "B-format". Their directivity patterns are described by the SH (Figure 2), mathematical functions of various orders with orthonormal properties. In [382], the authors presented an explicit formulation of the SH functions up to order five. The Ambisonics format employed in this work follows the standard AmbiX [389], hence with SN3D normalization and ACN channel numbering. Beamforming can be approached in two different ways. When a linear processing is used, a matrix of filters synthesizes the virtual microphones from the capsule signals. In case of parametric processing, the raw capsule signals are employed for performing a parametric spatial analysis of the sound scene, extracting the single source signals and their locations, and then using the theoretical SH formulas for recreating the B-format signals [390, 391, 392, 393, 394].

In this work a linear processing was employed, thus relying on a matrix of Finite Impulse Response (FIR) filters, computed by solving at least squares the Kirkeby inversion [395] with modified Tichonov regularization:

$$|H[k]|_{m\times v} = [|C[k]|^*_{m\times d} \cdot |C[k]|_{d\times m} + \beta[k] \cdot |I|_{m\times m}]^{-1} |C[k]|^*_{m\times d} \cdot |Q[k]|_{d\times v} \cdot e^{-j\pi k} \tag{1}$$

where m=[1,...,M] are the capsules; v=[1,...,V] are the virtual microphones; k is the frequency index; d=[1,...,D] are the Directions of Arrival (DoA) of the sound waves; the matrix C is the complex response of each capsule m for each direction d; the matrix Q defines the frequency indepen-




Figure 2: The first 16 Spherical Harmonics, corresponding to Ambisonics 3^{rd} order.

dent amplitude of the target directivity patterns; $e^{-j\pi k}$ introduces a latency that ensures filters causality; $\cdot$ is the dot product; I is the identity matrix; $[]^*$ denotes the conjugate transpose; $[]^{-1}$ denotes the pseudo-inverse; $\beta_{[k]}$ is a frequency-dependent regularization parameter [396], which apply a frequency constraint to the inversion, thus preserving the Signal-to-Noise Ratio (SNR) in the frequency ranges where beamforming is physically limited by the distance between the capsules. $\beta_{[k]}$, shown in Figure 3, represents the most significant improvement of the Kirkeby method over the traditional Tikhonov regularization, where instead β is constant.

The regularization parameter $\beta_{[k]}$ was defined as follow: $\beta_i = 0.01$ for the in-band range, $\beta_o = 1$ for the out-band range, $\Delta f = 0.3$ octaves for the transition bandwidth, $f_low = 100$ Hz for the lower transition frequency, and $f_high = 10$ kHz for the higher transition frequency.

The EM was measured in an anechoic room [397, 398] with a two-axis turntable and a loudspeaker positioned at 1-meter distance. The schematic of the experimental setup is shown in Figure 4. The turntable is controlled by the PC via Ethernet. The test signal is sent from the PC to the interface board via Firewire. This system allows playing the test signal and synchronously recording all the 32 channels of the EM. The sound source is a Genelec studio monitor type 8351A, which provides a flat frequency response with an accuracy of $\pm$ 1.5 dB (38 Hz - 20 kHz).

The test signal is an Exponential Sine Sweep (ESS) [399], pre-equalized




Figure 3: Frequency-dependent regularization parameter β (β_i in-band and β_o out-band




Figure 4: Experimental setup for measuring the microphone array response C.

for further flatting the spectrum of the sound source in the range within The measurement was repeated for DoA, arranged over a T-design distribution [400, 401] of order T=21. After each measurement, the PC sends to turntable the new measurement direction and then the ESS is played and recorded.

IRs were calculated by convolving the recorded signals with the inverse sweep [399]. By applying the Fast Fourier Transform (FFT) of points on




Figure 5: Loudspeakers arrangement at Casa della Musica, Parma, Italy.

the IRs, the matrix of 1 is obtained, with dimensions Finally, the solution of 1 provides the filtering matrix H. It can be referred as MIC2SH matrix, since it provides the conversion from the 32 pressure signals captured by the capsules of the array into the Spherical Harmonics domain.

Ambisonics format can be reproduced with a loudspeaker array. A traditional linear decoder was employed to calculate a FIR filter matrix, which converts SH into the speaker feeds (SF) signals. Such Spherical Harmonics to Speaker Feeds (SH2SF) matrix was calculated to decode the Ambisonics 3^{rd} order over a spherical arrangement of 16 loudspeakers (Figure 5). Hence the dimension of the decoding matrix is 16x16. With this setup, it is possible to perform accurate listening tests.

Test sound processing The EM microphone array was measured inside an anechoic room with the studio monitor Genelec 8351A, on axis, at four different distances, 0.5m, 1m, 2, and 4m. The test signal employed was the ESS. After applying the convolution with the inverse ESS, four IRs of dimension 1x32 were obtained, namely SPK2MIC, since they represent the acoustic path between the sound source and the 32 capsules of the array. The further convolution between the SPK2MIC and the MIC2SH matrices provides the SPK2SH matrix, of dimension 1x16 in our case (Ambisonics 3^{rd} order).

Finally, mono test sounds were convolved with the SPK2SH matrix. Such

operation could be more easily obtained with a theoretical encoder, which makes use of the equations describing the interaction between a plane wave and a spherical rigid surface [402, 403]. However, this solution assumes the hypothesis of plane wave propagation, which in practice would result in sound sources always positioned at infinite distance from the array. Instead, having measured at short distances both SPK2MIC and MIC2SH matrices, the effective spherical curvature of the wave fronts is considered, allowing to render also the distance of the test sound in addition to the direction of arrival.

Since the EM microphone array was measured only from the front direction, rotations were applied in the SH domain, allowing to get test sounds from any direction. It was opted to use only four of the directions already employed in the previous experiment, characterized by 0° elevation and equispaced azimuth ranging between 0° and 360° with 90° steps. The four distances (0.5m, 1m, 2m, 4m) were rotated in all the four directions.

Each test was carried out by playing four impulses on the direction. The four impulses consist in the sequence of four distances. In this way, it was possible to render approaching or receding sounds for each direction.

The whole processing is resumed in Figure 6




Figure 6: Signal processing flow.